

# LCD TV

## chassis FL9.1

# SERVICE MANUAL


### Contents

32"	LC320SLX	SYLVANIA	(Serial No. : DS1A*****)
32"	LC320SLX	SYLVANIA	(Serial No. : DS2A*****)
32"	LC320SLX	SYLVANIA	(Serial No. : DS3A*****)
32"	LC320SLX	SYLVANIA	(Serial No. : DS4A*****)
32"	32MF339B/F7	MAGNAVOX	(Serial No. : DS1A*****)
32"	32MF339B/F7	MAGNAVOX	(Serial No. : DS2A*****)
32"	32MF339B/F7	MAGNAVOX	(Serial No. : DS3A*****)
32"	LC320SSX	SYLVANIA Limited	(Serial No. : DS1A*****)
32"	LC320SSX	SYLVANIA Limited	(Serial No. : DS2A*****)
32"	LC320SSX	SYLVANIA Limited	(Serial No. : DS3A*****)
32"	LC320EMX	EMERSON	(Serial No. : DS1A*****)
32"	LC320EMX	EMERSON	(Serial No. : DS2A*****)
32"	LC320EMX	EMERSON	(Serial No. : DS3A*****)
32"	LC320EMX	EMERSON	(Serial No. : DS4A*****)
32"	LC320EMXF	EMERSON	(Serial No. : DS1A*****)
32"	LC320EMXF	EMERSON	(Serial No. : DS2A*****)
32"	LC320EMXF	EMERSON	(Serial No. : DS4A*****)
32"	LC321SSX	SYLVANIA Limited	
32"	32MF369B/F7	MAGNAVOX	

© 2009 Funai Electric Co., Ltd.

All rights reserved. No part of this manual may be reproduced, copied, transmitted, disseminated, transcribed, downloaded or stored in any storage medium, in any form or for any purpose without the express prior written consent of Funai. Furthermore, any unauthorized commercial distribution of this manual or any revision hereto is strictly prohibited.

Information in this document is subject to change without notice. Funai reserves the right to change the content herein without the obligation to notify any person or organization of such changes.

**FUNAI** with the  design is a registered trademark of Funai Electric Co., Ltd and may not be used in any way without the express written consent of Funai. All other trademarks used herein remain the exclusive property of their respective owners. Nothing contained in this manual should be construed as granting, by implication or otherwise, any license or right to use any of the trademarks displayed herein. Misuse of any trademarks or any other content in this manual is strictly prohibited. Funai shall aggressively enforce its intellectual property rights to the fullest extent of the law.

A91F3UH/F0UH/F1UH/F4UH/FBUH/FEUH/F9UH/F8UH/F6UH/F7UH/FNUH/FGUH/FPUH/FFUH/FMUH/FCUH/  
FDUH/FSUH/FTUH

091013

## **IMPORTANT SAFETY NOTICE**

**Proper service and repair is important to the safe, reliable operation of all Funai Equipment. The service procedures recommended by Funai and described in this service manual are effective methods of performing service operations. Some of these service special tools should be used when and as recommended.**

**It is important to note that this service manual contains various CAUTIONS and NOTICES which should be carefully read in order to minimize the risk of personal injury to service personnel. The possibility exists that improper service methods may damage the equipment. It also is important to understand that these CAUTIONS and NOTICES ARE NOT EXHAUSTIVE. Funai could not possibly know, evaluate and advice the service trade of all conceivable ways in which service might be done or of the possible hazardous consequences of each way. Consequently, Funai has not undertaken any such broad evaluation. Accordingly, a servicer who uses a service procedure or tool which is not recommended by Funai must first use all precautions thoroughly so that neither his safety nor the safe operation of the equipment will be jeopardized by the service method selected.**

<p><b>The LCD panel is manufactured to provide many years of useful life. Occasionally a few non active pixels may appear as a tiny spec of color. This is not to be considered a defect in the LCD screen.</b></p>
---

# TABLE OF CONTENTS

Specifications . . . . .	1-1
Important Safety Precautions . . . . .	2-1
Standard Notes for Servicing . . . . .	3-1
Cabinet Disassembly Instructions . . . . .	4-1
Electrical Adjustment Instructions . . . . .	5-1
How to Initialize the LCD TV . . . . .	6-1
Firmware Renewal Mode . . . . .	7-1
Troubleshooting . . . . .	8-1
Block Diagrams . . . . .	9-1
Schematic Diagrams / CBA and Test Points . . . . .	10-1
Waveforms . . . . .	11-1
Wiring Diagram . . . . .	12-1
Exploded Views . . . . .	13-1
Mechanical Parts List . . . . .	14-1
Electrical Parts List . . . . .	15-1
Revision History . . . . .	16-1

# SPECIFICATIONS

## < TUNER / NTSC >

ANT. Input ----- 75  $\Omega$  Unbal., F type

Description	Condition	Unit	Nominal	Limit
1. AFT Pull-In Range	---	MHz	$\pm 2.3$	$\pm 2.1$
2. Synchronizing Sens.	TV.ch.4	dB $\mu$	18	20
	CA.ch.31	dB $\mu$	18	20
	CA.ch.87	dB $\mu$	18	23

## < TUNER / ATSC >

Description	Condition	Unit	Nominal	Limit
1. Received Freq. Range (-28dBm)	---	kHz	---	$\pm 100$
2. ATSC Dynamic Range (min / max)	ch.4	dBm	---	-76/0
	ch.10	dBm	---	-76/0
	ch.41	dBm	---	-76/+4

## < LCD PANEL >

Description	Condition	Unit	Nominal	Limit
1. Native Pixel Resolution	Horizontal	pixels	1366	---
	Vertical	pixels	768	---
2. Brightness (w / filter)	---	cd/m <sup>2</sup>	320	---
3. Viewing Angle	Horizontal	°	-88 to 88	---
	Vertical	°	-88 to 88	---

## < VIDEO >

Description	Condition	Unit	Nominal	Limit
1. Over Scan	Horizontal	%	5	5 $\pm$ 5
	Vertical	%	5	5 $\pm$ 5
2. Color Temperature	---	°K	12000	---
	x		0.272	$\pm 3\%$
	y		0.278	$\pm 3\%$
3. Resolution (composite video)	Horizontal	line	400	---
	Vertical	line	350	---

## < AUDIO >

All items are measured across 8  $\Omega$  load at speaker output terminal with L.P.F.

Description	Condition	Unit	Nominal	Limit
1. Audio Output 10% Distortion (ATSC 0 dBfs)	Lch/Rch	W	[LC320SLX, LC320EMX, LC320EMXF] 5.0/5.0	[LC320SLX, LC320EMX, LC320EMXF] 4.5/4.5
			[32MF339B/F7, 32MF369B/F7, LC320SSX, LC321SSX] 10.0/10.0	[32MF339B/F7, 32MF369B/F7, LC320SSX, LC321SSX] 9.0/9.0
2. Audio Distortion (NTSC)	500mW: Lch/Rch	%	0.5/0.5	2.0/2.0
3. Audio Freq. Response (NTSC)	-6dB: Lch	Hz	70 to 10 k	---
	-6dB: Rch	Hz	70 to 10 k	---



# IMPORTANT SAFETY PRECAUTIONS

Prior to shipment from the factory, our products are strictly inspected for recognized product safety and electrical codes of the countries in which they are to be sold. However, in order to maintain such compliance, it is equally important to implement the following precautions when a set is being serviced.


## Safety Precautions for LCD TV Circuit

1. **Before returning an instrument to the customer**, always make a safety check of the entire instrument, including, but not limited to, the following items:

- a. Be sure that no built-in protective devices are defective and have been defeated during servicing. (1) Protective shields are provided on this chassis to protect both the technician and the customer. Correctly replace all missing protective shields, including any removed for servicing convenience. (2) When reinstalling the chassis and/or other assembly in the cabinet, be sure to put back in place all protective devices, including but not limited to, nonmetallic control knobs, insulating fishpapers, adjustment and compartment covers/shields, and isolation resistor/capacitor networks. **Do not operate this instrument or permit it to be operated without all protective devices correctly installed and functioning. Servicers who defeat safety features or fail to perform safety checks may be liable for any resulting damage.**
- b. Be sure that there are no cabinet openings through which an adult or child might be able to insert their fingers and contact a hazardous voltage. Such openings include, but are not limited to, (1) spacing between the Liquid Crystal Panel and the cabinet mask, (2) excessively wide cabinet ventilation slots, and (3) an improperly fitted and/or incorrectly secured cabinet back cover.


- c. **Antenna Cold Check** - With the instrument AC plug removed from any AC source, connect an electrical jumper across the two AC plug prongs. Place the instrument AC switch in the on position. Connect one lead of an ohmmeter to the AC plug prongs tied together and touch the other ohmmeter lead in turn to each tuner antenna input exposed terminal screw and, if applicable, to the coaxial connector. If the measured resistance is less than 1.0 megohm or greater than 5.2 megohm, an abnormality exists that must be corrected before the instrument is returned to the customer. Repeat this test with the instrument AC switch in the off position.

- d. **Leakage Current Hot Check** - With the instrument completely reassembled, plug the AC line cord directly into a 120 V AC outlet. (Do not use an isolation transformer during this test.) Use a leakage current tester or a metering system that complies with American National Standards Institute (ANSI) C101.1 Leakage Current for Appliances and Underwriters Laboratories (UL) 1410, (50.7). With the instrument AC switch first in the on position and then in the off position, measure from a known earth ground (metal water pipe, conduit, etc.) to all exposed metal parts of the instrument (antennas, handle brackets, metal cabinet, screw heads, metallic overlays, control shafts, etc.), especially any exposed metal parts that offer an electrical return path to the chassis. Any current measured must not exceed 0.5 milli-ampere. Reverse the instrument power cord plug in the outlet and repeat the test.



**ANY MEASUREMENTS NOT WITHIN THE LIMITS SPECIFIED HEREIN INDICATE A POTENTIAL SHOCK HAZARD THAT MUST BE ELIMINATED BEFORE RETURNING THE INSTRUMENT TO THE CUSTOMER OR BEFORE CONNECTING THE ANTENNA OR ACCESSORIES.**

2. Read and comply with all caution and safety-related notes on or inside the receiver cabinet, on the receiver chassis, or on the Liquid Crystal Panel.

3. **Design Alteration Warning** - Do not alter or add to the mechanical or electrical design of this TV receiver. Design alterations and additions, including, but not limited to circuit modifications and the addition of items such as auxiliary audio and/or video output connections, might alter the safety characteristics of this receiver and create a hazard to the user. Any design alterations or additions will void the manufacturer's warranty and may make you, the servicer, responsible for personal injury or property damage resulting therefrom.
4. **Hot Chassis Warning** -
  - a. Some TV receiver chassis are electrically connected directly to one conductor of the AC power cord and maybe safety-serviced without an isolation transformer only if the AC power plug is inserted so that the chassis is connected to the ground side of the AC power source. To confirm that the AC power plug is inserted correctly, with an AC voltmeter, measure between the chassis and a known earth ground. If a voltage reading in excess of 1.0 V is obtained, remove and reinsert the AC power plug in the opposite polarity and again measure the voltage potential between the chassis and a known earth ground.
  - b. Some TV receiver chassis normally have 85V AC(RMS) between chassis and earth ground regardless of the AC plug polarity. This chassis can be safety-serviced only with an isolation transformer inserted in the power line between the receiver and the AC power source, for both personnel and test equipment protection.
  - c. Some TV receiver chassis have a secondary ground system in addition to the main chassis ground. This secondary ground system is not isolated from the AC power line. The two ground systems are electrically separated by insulation material that must not be defeated or altered.
5. Observe original lead dress. Take extra care to assure correct lead dress in the following areas: a. near sharp edges, b. near thermally hot parts-be sure that leads and components do not touch thermally hot parts, c. the AC supply, d. high voltage, and, e. antenna wiring. Always inspect in all areas for pinched, out of place, or frayed wiring. Check AC power cord for damage.
6. Components, parts, and/or wiring that appear to have overheated or are otherwise damaged should be replaced with components, parts, or wiring that meet original specifications. Additionally, determine the cause of overheating and/or damage and, if necessary, take corrective action to remove any potential safety hazard.
7. **Product Safety Notice** - Some electrical and mechanical parts have special safety-related characteristics which are often not evident from visual inspection, nor can the protection they give necessarily be obtained by replacing them with components rated for higher voltage, wattage, etc. Parts that have special safety characteristics are identified by a  on schematics and in parts lists. Use of a substitute replacement that does not have the same safety characteristics as the recommended replacement part might create shock, fire, and/or other hazards. The product's safety is under review continuously and new instructions are issued whenever appropriate. Prior to shipment from the factory, our products are strictly inspected to confirm they comply with the recognized product safety and electrical codes of the countries in which they are to be sold. However, in order to maintain such compliance, it is equally important to implement the following precautions when a set is being serviced.

## Precautions during Servicing

- A.** Parts identified by the **▲** symbol are critical for safety.  
Replace only with part number specified.
- B.** In addition to safety, other parts and assemblies are specified for conformance with regulations applying to spurious radiation. These must also be replaced only with specified replacements.  
Examples: RF converters, RF cables, noise blocking capacitors, and noise blocking filters, etc.
- C.** Use specified internal wiring. Note especially:
  - 1) Wires covered with PVC tubing
  - 2) Double insulated wires
  - 3) High voltage leads
- D.** Use specified insulating materials for hazardous live parts. Note especially:
  - 1) Insulation Tape
  - 2) PVC tubing
  - 3) Spacers
  - 4) Insulators for transistors.
- E.** When replacing AC primary side components (transformers, power cord, etc.), wrap ends of wires securely about the terminals before soldering.
- F.** Observe that the wires do not contact heat producing parts (heat sinks, oxide metal film resistors, fusible resistors, etc.)
- G.** Check that replaced wires do not contact sharp edged or pointed parts.
- H.** When a power cord has been replaced, check that 5~6 kg of force in any direction will not loosen it.
- I.** Also check areas surrounding repaired locations.
- J.** Use care that foreign objects (screws, solder droplets, etc.) do not remain inside the set.
- K.** When connecting or disconnecting the internal connectors, first, disconnect the AC plug from the AC supply outlet.
- L.** When installing parts or assembling the cabinet parts, be sure to use the proper screws and tighten certainly.

## Safety Check after Servicing

Examine the area surrounding the repaired location for damage or deterioration. Observe that screws, parts and wires have been returned to original positions. Afterwards, perform the following tests and confirm the specified values in order to verify compliance with safety standards.


### 1. Clearance Distance

When replacing primary circuit components, confirm specified clearance distance ( $d$ ) and ( $d'$ ) between soldered terminals, and between terminals and surrounding metallic parts. (See Fig. 1)

**Table 1: Ratings for selected area**

AC Line Voltage	Region	Clearance Distance ( $d$ ), ( $d'$ )
110 to 130 V	U.S.A. or Canada	$\geq 3.2$ mm (0.126 inches)

**Note:** This table is unofficial and for reference only. Be sure to confirm the precise values.




**Fig. 1**

### 2. Leakage Current Test

Confirm the specified (or lower) leakage current between B (earth ground, power cord plug prongs) and externally exposed accessible parts (RF terminals, antenna terminals, video and audio input and output terminals, microphone jacks, earphone jacks, etc.) is lower than or equal to the specified value in the table below.

#### Measuring Method: (Power ON)

Insert load  $Z$  between B (earth ground, power cord plug prongs) and exposed accessible parts. Use an AC voltmeter to measure across both terminals of load  $Z$ . See Fig. 2 and following table.



**Fig. 2**

**Table 2: Leakage current ratings for selected areas**


AC Line Voltage	Region	Load $Z$	Leakage Current ( $i$ )	Earth Ground (B) to:
110 to 130 V	U.S.A. or Canada	$0.15 \mu F$ CAP. & $1.5 k\Omega$ RES. Connected in parallel	$i \leq 0.5$ mA rms	Exposed accessible parts

**Note:** This table is unofficial and for reference only. Be sure to confirm the precise values.


# STANDARD NOTES FOR SERVICING

## Circuit Board Indications


1. The output pin of the 3 pin Regulator ICs is indicated as shown.



2. For other ICs, pin 1 and every fifth pin are indicated as shown.




3. The 1st pin of every male connector is indicated as shown.



## Pb (Lead) Free Solder

**Pb free mark will be found on PCBs which use Pb free solder. (Refer to figure.) For PCBs with Pb free mark, be sure to use Pb free solder. For PCBs without Pb free mark, use standard solder.**



Pb free mark

## How to Remove / Install Flat Pack-IC

### 1. Removal

**With Hot-Air Flat Pack-IC Desoldering Machine:**

1. Prepare the hot-air flat pack-IC desoldering machine, then apply hot air to the Flat Pack-IC (about 5 to 6 seconds). (Fig. S-1-1)





Fig. S-1-1

2. Remove the flat pack-IC with tweezers while applying the hot air.
3. Bottom of the flat pack-IC is fixed with glue to the CBA; when removing entire flat pack-IC, first apply soldering iron to center of the flat pack-IC and heat up. Then remove (glue will be melted). (Fig. S-1-6)
4. Release the flat pack-IC from the CBA using tweezers. (Fig. S-1-6)

### CAUTION:


1. The Flat Pack-IC shape may differ by models. Use an appropriate hot-air flat pack-IC desoldering machine, whose shape matches that of the Flat Pack-IC.
2. Do not supply hot air to the chip parts around the flat pack-IC for over 6 seconds because damage to the chip parts may occur. Put masking tape around the flat pack-IC to protect other parts from damage. (Fig. S-1-2)

3. The flat pack-IC on the CBA is affixed with glue, so be careful not to break or damage the foil of each pin or the solder lands under the IC when removing it.




#### With Soldering Iron:

1. Using desoldering braid, remove the solder from all pins of the flat pack-IC. When you use solder flux which is applied to all pins of the flat pack-IC, you can remove it easily. (Fig. S-1-3)



2. Lift each lead of the flat pack-IC upward one by one, using a sharp pin or wire to which solder will not adhere (iron wire). When heating the pins, use a fine tip soldering iron or a hot air desoldering machine. (Fig. S-1-4)





3. Bottom of the flat pack-IC is fixed with glue to the CBA; when removing entire flat pack-IC, first apply soldering iron to center of the flat pack-IC and heat up. Then remove (glue will be melted). (Fig. S-1-6)
4. Release the flat pack-IC from the CBA using tweezers. (Fig. S-1-6)

### With Iron Wire:



1. Using desoldering braid, remove the solder from all pins of the flat pack-IC. When you use solder flux which is applied to all pins of the flat pack-IC, you can remove it easily. (Fig. S-1-3)
2. Affix the wire to a workbench or solid mounting point, as shown in Fig. S-1-5.
3. While heating the pins using a fine tip soldering iron or hot air blower, pull up the wire as the solder melts so as to lift the IC leads from the CBA contact pads as shown in Fig. S-1-5.
4. Bottom of the flat pack-IC is fixed with glue to the CBA; when removing entire flat pack-IC, first apply soldering iron to center of the flat pack-IC and heat up. Then remove (glue will be melted). (Fig. S-1-6)
5. Release the flat pack-IC from the CBA using tweezers. (Fig. S-1-6)

**Note:** When using a soldering iron, care must be taken to ensure that the flat pack-IC is not being held by glue. When the flat pack-IC is removed from the CBA, handle it gently because it may be damaged if force is applied.



## 2. Installation

1. Using desoldering braid, remove the solder from the foil of each pin of the flat pack-IC on the CBA so you can install a replacement flat pack-IC more easily.
2. The "●" mark on the flat pack-IC indicates pin 1. (See Fig. S-1-7.) Be sure this mark matches the pin 1 on the PCB when positioning for installation. Then presolder the four corners of the flat pack-IC. (See Fig. S-1-8.)
3. Solder all pins of the flat pack-IC. Be sure that none of the pins have solder bridges.



# Instructions for Handling Semi-conductors



Electrostatic breakdown of the semi-conductors may occur due to a potential difference caused by electrostatic charge during unpacking or repair work.

## 1. Ground for Human Body

Be sure to wear a grounding band ( $1\text{ M}\Omega$ ) that is properly grounded to remove any static electricity that may be charged on the body.

## 2. Ground for Workbench

Be sure to place a conductive sheet or copper plate with proper grounding ( $1\text{ M}\Omega$ ) on the workbench or other surface, where the semi-conductors are to be placed. Because the static electricity charge on clothing will not escape through the body grounding band, be careful to avoid contacting semi-conductors with your clothing.






# CABINET DISASSEMBLY INSTRUCTIONS

## [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMXF]

### 1. Disassembly Flowchart

This flowchart indicates the disassembly steps for the cabinet parts, and the CBA in order to gain access to item(s) to be serviced. When reassembling, follow the steps in reverse order. Bend, route and dress the cables as they were.



### 2. Disassembly Method

Step/ Loc. No.	Part	Removal		
		Fig. No.	Remove/*Unhook/ Unlock/Release/ Unplug/Unclamp/ Desolder	Note
[1]	Stand Assembly	D1	4(S-1)	---
[2]	Rear Cabinet	D1	13(S-2), 2(S-3), 3(S-4)	---
[3]	[LC320SLX (Serial No. : DS1A*****), LC320SLX (Serial No. : DS2A*****), LC320SLX (Serial No. : DS4A*****), 32MF339B/F7, LC320SSX, LC320EMXF]			
	Inverter CBA	D2 D4	6(S-5), *CN1001, *CN1003, *CN1050, *CN1100, *CN1150, *CN1200, *CN1900	---

Step/ Loc. No.	Part	Removal		
		Fig. No.	Remove/*Unhook/ Unlock/Release/ Unplug/Unclamp/ Desolder	Note
	[LC320SLX (Serial No. : DS3A*****)]			
[3]	Inverter CBA	D2 D4	6(S-5), *CN1001, *CN1005, *CN1050, *CN1100, *CN1150, *CN1200, *CN1900	---
[4]	Jack CBA	D2 D4	2(S-6), *CL701B	---
[5]	Power Supply CBA	D2 D4	7(S-7), *CN101, *CN301, *CN302, *CN801, *CN802	---
[6]	Jack Holder	D2	2(S-8)	---
[7]	Digital Main CBA Unit	D2 D4	4(S-9), 2(S-10), 4(S-11), *CN3902, Shield Box	---
[8]	Speaker Holder (L,R)	D3	*Hook	---
[9]	Speaker(s)	D3	8(S-12)	---
[10]	Junction CBA	D3 D4	Desolder	---
[11]	IR Sensor CBA	D3 D4	2(S-13), *CL103C	---
[12]	Function CBA	D3 D4	2(S-14)	---
[13]	LCD Module Assembly	D3	(S-15)	---
[14]	Front Cabinet	D3	-----	---
↓ (1)	↓ (2)	↓ (3)	↓ (4)	↓ (5)


#### Note:

- (1) Order of steps in procedure. When reassembling, follow the steps in reverse order. These numbers are also used as the Identification (location) No. of parts in figures.
- (2) Parts to be removed or installed.
- (3) Fig. No. showing procedure of part location
- (4) Identification of parts to be removed, unhooked, unlocked, released, unplugged, unclamped, or desoldered.


P = Spring, L = Locking Tab, S = Screw,  
H = Hex Screw, CN = Connector  
\* = Unhook, Unlock, Release, Unplug, or Desolder

e.g. 2(S-2) = two Screws (S-2),  
2(L-2) = two Locking Tabs (L-2)

(5) Refer to the following "Reference Notes in the Table."



**Fig. D1**



**Fig. D2**




Fig. D3

# TV Cable Wiring Diagram





Fig. D4

# CABINET DISASSEMBLY INSTRUCTIONS

## [LC320EMX]

### 1. Disassembly Flowchart

This flowchart indicates the disassembly steps for the cabinet parts, and the CBA in order to gain access to item(s) to be serviced. When reassembling, follow the steps in reverse order. Bend, route and dress the cables as they were.



### 2. Disassembly Method

Step/ Loc. No.	Part	Removal		
		Fig. No.	Remove/*Unhook/ Unlock/Release/ Unplug/Unclamp/ Desolder	Note
[1]	Stand Assembly	D1	4(S-1)	---
[2]	Rear Cabinet	D1	13(S-2), 2(S-3), 3(S-4)	---
[3]	[LC320EMX (Serial No. : DS1A*****), LC320EMX (Serial No. : DS2A*****), LC320EMX (Serial No. : DS4A*****)]			
	Inverter CBA	D2 D4	6(S-5), *CN1001, *CN1003, *CN1050, *CN1100, *CN1150, *CN1200, *CN1900	---

Step/ Loc. No.	Part	Removal		
		Fig. No.	Remove/*Unhook/ Unlock/Release/ Unplug/Unclamp/ Desolder	Note
[3]	[LC320EMX (Serial No. : DS3A*****)]			
	Inverter CBA	D2 D4	6(S-5), *CN1001, *CN1005, *CN1050, *CN1100, *CN1150, *CN1200, *CN1900	---
[4]	Jack CBA	D2 D4	2(S-6), *CL701B	---
[5]	Power Supply CBA	D2 D4	7(S-7), *CN101, *CN301, *CN302, *CN801, *CN802	---
[6]	Jack Holder	D2	2(S-8)	---
[7]	Digital Main CBA Unit	D2 D4	4(S-9), 2(S-10), 4(S-11), *CN3902, Shield Box	---
[8]	LCD Module Assembly	D3	(S-12)	---
[9]	Speaker Holder(s) [R]	D3	2(S-13)	---
[10]	Speaker Holder(s) [L]	D3	2(S-14)	---
[11]	Speaker(s)	D3	-----	---
[12]	Junction CBA	D3 D4	Desolder	---
[13]	IR Sensor CBA	D3 D4	2(S-15), *CL103C	---
[14]	Function CBA	D3 D4	-----	---
[15]	Front Cabinet	D3	-----	---

↓ (1)      ↓ (2)      ↓ (3)      ↓ (4)      ↓ (5)


#### Note:


- (1) Order of steps in procedure. When reassembling, follow the steps in reverse order. These numbers are also used as the Identification (location) No. of parts in figures.
- (2) Parts to be removed or installed.
- (3) Fig. No. showing procedure of part location

- (4) Identification of parts to be removed, unhooked, unlocked, released, unplugged, unclamped, or desoldered.  
P = Spring, L = Locking Tab, S = Screw,  
H = Hex Screw, CN = Connector  
\* = Unhook, Unlock, Release, Unplug, or Desolder

e.g. 2(S-2) = two Screws (S-2),  
2(L-2) = two Locking Tabs (L-2)


- (5) Refer to the following "Reference Notes in the Table."





**Fig. D2**





**Fig. D3**

## TV Cable Wiring Diagram





Fig. D4

# CABINET DISASSEMBLY INSTRUCTIONS

## [LC321SSX, 32MF369B/F7]

### 1. Disassembly Flowchart

This flowchart indicates the disassembly steps for the cabinet parts, and the CBA in order to gain access to item(s) to be serviced. When reassembling, follow the steps in reverse order. Bend, route and dress the cables as they were.



### 2. Disassembly Method

Step/ Loc. No.	Part	Removal		
		Fig. No.	Remove/*Unhook/ Unlock/Release/ Unplug/Unclamp/ Desolder	Note
[1]	Stand Assembly	D1	4(S-1)	---
[2]	Rear Cabinet	D1	13(S-2), 2(S-3), 3(S-4)	---
[3]	Inverter Power CBA	D2 D4	5(S-5), *CN1001, *CN1003, *CN1900	---
[4]	Jack CBA	D2 D4	2(S-6), *CL701B	---
[5]	Power Supply CBA	D2 D4	7(S-7), *CN101, *CN301, *CN302, *CN801, *CN802	---
[6]	Jack Holder	D2	2(S-8)	---

Step/ Loc. No.	Part	Removal		
		Fig. No.	Remove/*Unhook/ Unlock/Release/ Unplug/Unclamp/ Desolder	Note
[7]	Digital Main CBA Unit	D2 D4	2(S-9), 2(S-10), 4(S-11), *CN3901, Shield Box	---
[8]	Speaker Holder[s] (L,R)	D3	*Hook, 8(S-12)	---
[9]	Speaker[s]	D3	-----	---
[10]	Junction CBA	D3 D4	Desolder	---
[11]	IR Sensor CBA	D3 D4	2(S-13), *CL103C	---
[12]	Function CBA	D3 D4	2(S-14)	---
[13]	LCD Module Assembly	D3	4(S-15), PCB Holder, Stand Holder	---
[14]	Front Cabinet	D3	-----	---
↓ (1)	↓ (2)	↓ (3)	↓ (4)	↓ (5)

#### Note:

- (1) Order of steps in procedure. When reassembling, follow the steps in reverse order. These numbers are also used as the Identification (location) No. of parts in figures.
- (2) Parts to be removed or installed.
- (3) Fig. No. showing procedure of part location
- (4) Identification of parts to be removed, unhooked, unlocked, released, unplugged, unclamped, or desoldered.  
P = Spring, L = Locking Tab, S = Screw,  
H = Hex Screw, CN = Connector  
\* = Unhook, Unlock, Release, Unplug, or Desolder  
e.g. 2(S-2) = two Screws (S-2),  
2(L-2) = two Locking Tabs (L-2)
- (5) Refer to the following "Reference Notes in the Table."






Fig. D1



**Fig. D2**



## TV Cable Wiring Diagram




Fig. D4

# ELECTRICAL ADJUSTMENT INSTRUCTIONS

**General Note: “CBA” is abbreviation for “Circuit Board Assembly.”**

**Note:** Electrical adjustments are required after replacing circuit components and certain mechanical parts. It is important to perform these adjustments only after all repairs and replacements have been completed. Also, do not attempt these adjustments unless the proper equipment is available.

## Test Equipment Required

1. NTSC Pattern Generator (Color Bar W/White Window, Red Color, Dot Pattern, Gray Scale, Monoscope, Multi-Burst)
2. Remote control unit
3. Color Analyzer

## How to make the Service remote control unit:

**[LC320SLX, LC320EMX, LC320EMXF]**

Cut “A” portion of the attached remote control unit as shown in Fig. 1.




Fig. 1

**[32MF339B/F7, 32MF369B/F7]**

Cut “A” portion of the attached remote control unit as shown in Fig. 2.




Fig. 2

**[LC320SSX, LC321SSX]**

Cut “A” portion of the attached remote control unit as shown in Fig. 3




Fig. 3

## How to set up the service mode:

### Service mode:

1. Use the service remote control unit.
2. Turn the power on.
3. Press the service button on the service remote control unit. The following screen appears.

“\*” differs depending on the models.

Code : \*\*\*\*\*\_\*  
Pic code : \*\*\_\*\_\*\_\*\_\*\_\*\_\*\_\*  
MIPS : Push 0key


Tuner : \*\*\*\*\_\*\_\*\_\*\_\*\_\*\_\*\_\*  
Safety : safety\_Non



## 1. Purity Check Mode

This mode cycles through full-screen displays of red, green, blue, and white to check for non-active pixels.


1. Enter the Service mode.
2. Each time pressing [7] button on the service remote control unit, the display changes as follows.



## 2. VCOM Adjustment

Test Point	Adj. Point
Screen	[CHANNEL UP/DOWN] buttons
M. EQ.	Spec.
Color analyzer	See below

**Figure**



Note: LC321SSX, 32MF369B/F7: VCOM adjustment is not required.

1. Operate the unit for more than 20 minutes.
2. Set the color analyzer and bring the optical receptor to the center on the LCD-Panel surface after zero point calibration as shown above.  
**Note:** The optical receptor must be set perpendicularly to the LCD Panel surface.
3. Enter the Service mode.
4. Press [3] button on the service remote control unit.  
[LC320SLX (Serial No. : DS1A \*\*\*\*\*),  
LC320SLX (Serial No. : DS2A \*\*\*\*\*),  
LC320SLX (Serial No. : DS4A \*\*\*\*\*),  
32MF339B/F7, LC320SSX, LC320EMXF  
LC320EMX (Serial No. : DS1A \*\*\*\*\*),  
LC320EMX (Serial No. : DS2A \*\*\*\*\*),  
LC320EMX (Serial No. : DS4A \*\*\*\*\*)]

Press [2] button on the service remote control unit.  
[LC320EMX (Serial No. : DS3A \*\*\*\*\*),  
LC320SLX (Serial No. : DS3A \*\*\*\*\*)]

5. Press [CHANNEL UP/DOWN] buttons on the service remote control unit so that the color analyzer value becomes minimum.

The white balance adjustment should be performed when replacing the LCD Panel or Digital CBA.

### 3. White Balance Adjustment

**Purpose:** To mix red, green and blue beams correctly for pure white.


**Symptom of Misadjustment:** White becomes bluish or reddish.

Test Point	Adj. Point	Mode	Input
Screen	[VOLUME DOWN] button	[VIDEO1] C/D	White Raster (APL 70%) or (APL 40%)
M. EQ.		Spec.	
Pattern Generator, Color analyzer		$x = 0.272 \pm 0.005$ $y = 0.278 \pm 0.005$	

**Figure**

To avoid interference from ambient light, this adjustment should be performed in a dark room.


Perpendicularity



L = 3 cm

INPUT: WHITE 70%, 40% Color Analyzer

1. Operate the unit for more than 20 minutes.
2. Input the White Raster(70%=70IRE, 40%=40IRE).



3. Set the color analyzer to the CHROMA mode and bring the optical receptor to the center on the LCD-Panel surface after zero point calibration as shown above.

**Note:** The optical receptor must be set perpendicularly to the LCD Panel surface.

4. Enter the Service mode. Press [VOLUME DOWN] button on the service remote control unit and select "C/D" mode.

#### 5. [CUTOFF]

Press [1] button to select "COR" for Red Cutoff adjustment. Press [3] button to select "COB" for Blue Cutoff adjustment.

#### [DRIVE]

Press [4] button to select "DR" for Red Drive adjustment. Press [6] button to select "DB" for Blue Drive adjustment.

6. In each color mode, press [CHANNEL UP/DOWN] buttons to adjust the values of color.
7. Adjust Cutoff and Drive so that the color temperature becomes 12000°K ( $x = 0.272$  /  $y = 0.278 \pm 0.005$ ).

# HOW TO INITIALIZE THE LCD TV

The purpose of initialization is to place the set in a new out of box condition. The customer will be prompted to select a language and program channels after the set has been initialized.

To put the program back at the factory-default, initialize the LCD TV using the following procedure.

1. Turn the power on.
2. To enter the service mode, press the service button on the service remote control unit.
  - To cancel the service mode, press [POWER] button on the service remote control unit.
3. Press [INFO] button on the service remote control unit to initialize the LCD television.
4. "INITIALIZED" will appear in the upper right of the screen. "INITIALIZED" color will change to green from red when initializing is complete.

# FIRMWARE RENEWAL MODE

## Equipment Required

- a. USB memory
- b. Remote Control Unit


## Firmware Update Procedure

**Note:** There are two states (the User Upgrade and the Factory Upgrade) in firmware update.


User Upgrade	Upgrade the firmware only. The setting values are not initialized.
Factory upgrade	Upgrade the firmware and initialize the setting values.

The identification of User Upgrade and Factory Upgrade are done by the filename.

1. Turn the power off and unplug the AC Cord.
2. Insert the USB memory to the USB port as shown below.



3. Plug the AC cord in the wall outlet and turn the power on.
4. The update will start and the following will appear on the screen.




**Note:** If the above screen isn't displayed, repeat from step 1.

The appearance shown in \*1 is described as follows.

Appearance	State
Downloading...	Downloading the firmware from the USB memory.
Writing...	Writing the downloaded firmware in flash memory.
Checking...	Checking the new firmware.

5. When the firmware update is completed, the following will appear on the screen.



Unplug the AC cord and kindly remove the USB memory from the USB port. Plug the AC cord in the wall outlet again and turn the power on.

### Note:


When the Factory Upgrade is used, after restarting TV, shift to initial screen menu in service mode. "INITIALIZED" will appear on the upper right of the screen. "INITIALIZED" color will change to green from red when initializing is complete.

# TROUBLESHOOTING


## [ Power Supply Section ]

(LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF)


### FLOW CHART NO.1




### FLOW CHART NO.2




### FLOW CHART NO.3




### FLOW CHART NO.4




### FLOW CHART NO.5




#### FLOW CHART NO.6




#### FLOW CHART NO.7



#### FLOW CHART NO.8




#### FLOW CHART NO.9




#### FLOW CHART NO.10

P-ON+5V is not output. (LCD+16V is outputted normally.)




#### FLOW CHART NO.11

P-ON+5V(TUNER+5V) is not output. (LCD+16V is outputted normally.)




#### FLOW CHART NO.12





AL+13V(M+13V) is not output.



#### FLOW CHART NO.13

P-ON+3V is not output.




**FLOW CHART NO.14****FLOW CHART NO.15****FLOW CHART NO.16****FLOW CHART NO.17**




## [ Power Supply Section ] (LC321SSX, 32MF369B/F7)


### FLOW CHART NO.1




### FLOW CHART NO.2




### FLOW CHART NO.3




### FLOW CHART NO.4




### FLOW CHART NO.5




#### FLOW CHART NO.6




#### FLOW CHART NO.7




#### FLOW CHART NO.8




#### FLOW CHART NO.9




#### FLOW CHART NO.10




#### FLOW CHART NO.11




#### FLOW CHART NO.12



#### FLOW CHART NO.13




#### FLOW CHART NO.14




## [ Video Signal Section ]


**FLOW CHART NO.1 [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMXF, LC321SSX, 32MF369B/F7]**




**FLOW CHART NO.1 [LC320EMX]**




**FLOW CHART NO.2**




**FLOW CHART NO.3**




#### FLOW CHART NO.4



#### FLOW CHART NO.5




#### FLOW CHART NO.6




## [ Audio Signal Section ]

### FLOW CHART NO.1




## FLOW CHART NO.2

Audio is not outputted normally.(Component Audio input)



### FLOW CHART NO.3







# BLOCK DIAGRAMS

## System Control Block Diagram


[LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]




System Control Block Diagram [LC321SSX, 32MF369B/F7]



# Video Block Diagram




Audio Block Diagram




# Digital Signal Process Block Diagram

[LC320SLX(Serial No.:DS1A\*\*\*\*\*, DS2A\*\*\*\*\*, DS3A\*\*\*\*\*), 32MF339B/F7,  
LC320SSX, LC320EMX(Serial No.:DS1A\*\*\*\*\*, DS2A\*\*\*\*\*, DS3A\*\*\*\*\*),  
LC320EMXF]




# Digital Signal Process Block Diagram

[LC320SLX(Serial No.:DS4A\*\*\*\*\*), LC320EMX(Serial No.:DS4A\*\*\*\*\*)]




# Digital Signal Process Block Diagram [LC321SSX, 32MF369B/F7]







# Inverter Block Diagram [LC321SSX, 32MF369B/F7]




**NOTE:**  
The voltage for parts in hot circuit is measured using hot GND as a common terminal.

**CAUTION ! :** For continued protection against risk of fire, replace only with same type 4 A, 125V fuse.

**ATTENTION :** Utiliser un fusible de rechange de même type de 4A, 125V.



**CAUTION !**  
Fixed voltage (or Auto voltage selectable) power supply circuit is used in this unit.  
If Main Fuse (F501) is blown, check to see that all components in the power supply circuit are not defective before you connect the AC plug to the AC power supply.  
Otherwise it may cause some components in the power supply circuit to fail.



# Power Supply Block Diagram [LC321SSX, 32MF369B/F7]

## CAUTION !

Fixed voltage (or Auto voltage selectable) power supply circuit is used in this unit.  
If Main Fuse (F601) is blown, check to see that all components in the power supply circuit are not defective before you connect the AC plug to the AC power supply.  
Otherwise it may cause some components in the power supply circuit to fail.




**CAUTION ! :** For continued protection against risk of fire,  
replace only with same type 4 A, 125V fuse.

**ATTENTION :** Utiliser un fusible de rechange de même type de 4A, 125V.

## NOTE:

The voltage for parts in hot circuit is measured using  
hot GND as a common terminal.



# SCHEMATIC DIAGRAMS / CBA AND TEST POINTS

## Standard Notes

### WARNING

Many electrical and mechanical parts in this chassis have special characteristics. These characteristics often pass unnoticed and the protection afforded by them cannot necessarily be obtained by using replacement components rated for higher voltage, wattage, etc. Replacement parts that have these special safety characteristics are identified in this manual and its supplements; electrical components having such features are identified by the mark “▲” in the schematic diagram and the parts list. Before replacing any of these components, read the parts list in this manual carefully. The use of substitute replacement parts that do not have the same safety characteristics as specified in the parts list may create shock, fire, or other hazards.

### Notes:

1. Do not use the part number shown on these drawings for ordering. The correct part number is shown in the parts list, and may be slightly different or amended since these drawings were prepared.
2. All resistance values are indicated in ohms ( $K = 10^3$ ,  $M = 10^6$ ).
3. Resistor wattages are 1/4W or 1/6W unless otherwise specified.
4. All capacitance values are indicated in  $\mu F$  ( $P = 10^{-6} \mu F$ ).
5. All voltages are DC voltages unless otherwise specified.
6. This schematic diagrams are masterized version that should cover the entire FL9.1 chassis models. Thus some parts in detail illustrated on this schematic diagrams may vary depend on the model within the FL9.1 chassis. Please refer to the parts lists for each models.
7. The Circuit Board layout illustrated on this service manual is the latest version for this chassis at the moment of making this service manual. Depend on the mass production date of each model, the actual layout of each Board may differ slightly from this version.

## LIST OF CAUTION, NOTES, AND SYMBOLS USED IN THE SCHEMATIC DIAGRAMS ON THE FOLLOWING PAGES:

### 1. CAUTION:

**CAUTION:** FOR CONTINUED PROTECTION AGAINST RISK OF FIRE, REPLACE ONLY WITH SAME TYPE\_A,\_V FUSE.

**ATTENTION:** UTILISER UN FUSIBLE DE RECHANGE DE MÊME TYPE DE\_A,\_V.

### 2. CAUTION:

Fixed Voltage (or Auto voltage selectable) power supply circuit is used in this unit.


If Main Fuse (F601) is blown, first check to see that all components in the power supply circuit are not defective before you connect the AC plug to the AC power supply. Otherwise it may cause some components in the power supply circuit to fail.

### 3. Note:

1. Do not use the part number shown on the drawings for ordering. The correct part number is shown in the parts list, and may be slightly different or amended since the drawings were prepared.
2. To maintain original function and reliability of repaired units, use only original replacement parts which are listed with their part numbers in the parts list section of the service manual.

### 4. Voltage indications on the schematics are as shown below:

Plug the TV power cord into a standard AC outlet.:




### 5. How to read converged lines

1-D3  
 ↑ Distinction Area  
 Line Number  
 (1 to 3 digits)

Examples:

1. "1-D3" means that line number "1" goes to the line number "1" of the area "D3".
2. "1-B1" means that line number "1" goes to the line number "1" of the area "B1".



### 6. Test Point Information

⊙ : Indicates a test point with a jumper wire across a hole in the PCB.

□→ : Used to indicate a test point with a component lead on foil side.

⊗ : Used to indicate a test point with no test pin.


● : Used to indicate a test point with a test pin.

Power Supply 1/4 Schematic Diagram [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]

**CAUTION !**  
Fixed voltage (or Auto voltage selectable) power supply circuit is used in this unit.  
If Main Fuse (F601) is blown , check to see that all components in the power supply circuit are not defective before you connect the AC plug to the AC power supply.  
Otherwise it may cause some components in the power supply circuit to fail.


**CAUTION ! :** For continued protection against risk of fire,  
replace only with same type 4 A, 125V fuse.  
**ATTENTION :** Utiliser un fusible de rechange de même type de 4A, 125V.

**NOTE:**  
The voltage for parts in hot circuit is measured using  
hot GND as a common terminal.




UNLESS OTHERWISE SPECIFIED:  
DIODES ARE 1SS133.

Power Supply 2/4 Schematic Diagram [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]



Power Supply 3/4 & Jack Schematic Diagram [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]








Power Supply 1/4 Schematic Diagram [LC321SSX, 32MF369B/F7]

CAUTION !


Fixed voltage (or Auto voltage selectable) power supply circuit is used in this unit.  
If Main Fuse (F601) is blown , check to see that all components in the power supply circuit are not defective before you connect the AC plug to the AC power supply.  
Otherwise it may cause some components in the power supply circuit to fail.




CAUTION ! : For continued protection against risk of fire,  
replace only with same type 4 A, 125V fuse.  
ATTENTION : Utiliser un fusible de rechange de même type de 4A, 125V.

NOTE:


The voltage for parts in hot circuit is measured using  
hot GND as a common terminal.




Power Supply 2/4 Schematic Diagram [LC321SSX, 32MF369B/F7]



Power Supply 3/4 & Jack Schematic Diagram [LC321SSX, 32MF369B/F7]



### Power Supply 4/4 Schematic Diagram [LC321SSX, 32MF369B/F7]









Inverter Power Schematic Diagram [LC321SSX, 32MF369B/F7]

NOTE:  
The voltage for parts in hot circuit is measured using  
hot GND as a common terminal.




Function Schematic Diagram [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]







Function Schematic Diagram [LC321SSX, 32MF369B/F7]



IR Sensor & Junction Schematic Diagram [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]




IR Sensor & Junction Schematic Diagram [LC321SSX, 32MF369B/F7]




Digital Main 1/5 Schematic Diagram [LC320SLX(Serial No.:DS1A\*\*\*\*\*, DS2A\*\*\*\*\*, DS3A\*\*\*\*\*), 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]

\*1 NOTE:  
The order of pins shown in this diagram is different from that of actual IC3301.  
IC3301 is divided into five and shown as IC3301 (1/5) ~ IC3301 (5/5) in this Digital Main Schematic Diagram Section.




Digital Main 2/5 Schematic Diagram [LC320SLX(Serial No.:DS1A\*\*\*\*\* , DS2A\*\*\*\*\* , DS3A\*\*\*\*\*), 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]

\*1 NOTE:  
The order of pins shown in this diagram is different from that of actual IC3301.  
IC3301 is divided into five and shown as IC3301 (1/5) ~ IC3301 (5/5) in this Digital Main Schematic Diagram Section.




Digital Main 3/5 Schematic Diagram [LC320SLX(Serial No.:DS1A\*\*\*\*\*, DS2A\*\*\*\*\*, DS3A\*\*\*\*\*), 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]

\*1 NOTE:  
The order of pins shown in this diagram is different from that of actual IC3301.  
IC3301 is divided into five and shown as IC3301 (1/5) ~ IC3301 (5/5) in this Digital Main Schematic Diagram Section.



Digital Main 4/5 Schematic Diagram [LC320SLX(Serial No.:DS1A\*\*\*\*\*, DS2A\*\*\*\*\*, DS3A\*\*\*\*\*), 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]

\*1 NOTE:  
The order of pins shown in this diagram is different from that of actual IC3301.  
IC3301 is divided into five and shown as IC3301 (1/5) ~ IC3301 (5/5) in this Digital Main Schematic Diagram Section.






**Digital Main 5/5 Schematic Diagram [LC320SLX(Serial No.:DS1A\*\*\*\*\*, DS2A\*\*\*\*\*, DS3A\*\*\*\*\*), 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]**

**\*1 NOTE:**

The order of pins shown in this diagram is different from that of actual IC3301.


IC3301 is divided into five and shown as IC3301 (1/5) ~ IC3301 (5/5) in this Digital Main Schematic Diagram Section.





Digital Main 1/5 Schematic Diagram [LC320SLX(Serial No.:DS4A\*\*\*\*\*), LC320EMX(Serial No.:DS4A\*\*\*\*\*)]


\*1 NOTE:  
The order of pins shown in this diagram is different from that of actual IC3301.  
IC3301 is divided into five and shown as IC3301 (1/5) ~ IC3301 (5/5) in this Digital Main Schematic Diagram Section.






Digital Main 3/5 Schematic Diagram [LC320SLX(Serial No.:DS4A\*\*\*\*\*), LC320EMX(Serial No.:DS4A\*\*\*\*\*)]

\*1 NOTE:  
The order of pins shown in this diagram is different from that of actual IC3301.  
IC3301 is divided into five and shown as IC3301 (1/5) ~ IC3301 (5/5) in this Digital Main Schematic Diagram Section.



Digital Main 4/5 Schematic Diagram [LC320SLX(Serial No.:DS4A\*\*\*\*\*), LC320EMX(Serial No.:DS4A\*\*\*\*\*)]


\*1 NOTE:  
The order of pins shown in this diagram is different from that of actual IC3301.  
IC3301 is divided into five and shown as IC3301 (1/5) ~ IC3301 (5/5) in this Digital Main Schematic Diagram Section.






Digital Main 5/5 Schematic Diagram [LC320SLX(Serial No.:DS4A\*\*\*\*\*), LC320EMX(Serial No.:DS4A\*\*\*\*\*)]

\*1 NOTE:  
The order of pins shown in this diagram is different from that of actual IC3301.  
IC3301 is divided into five and shown as IC3301 (1/5) ~ IC3301 (5/5) in this Digital Main Schematic Diagram Section.



Digital Main 1/5 Schematic Diagram [LC321SSX, 32MF369B/F7]


\*1 NOTE:  
The order of pins shown in this diagram is different from that of actual IC3301.  
IC3301 is divided into five and shown as IC3301 (1/5) ~ IC3301 (5/5) in this Digital Main Schematic Diagram Section.





Digital Main 3/5 Schematic Diagram [LC321SSX, 32MF369B/F7]


\*1 NOTE:  
The order of pins shown in this diagram is different from that of actual IC3301.  
IC3301 is divided into five and shown as IC3301 (1/5) ~ IC3301 (5/5) in this Digital Main Schematic Diagram Section.





Digital Main 4/5 Schematic Diagram [LC321SSX, 32MF369B/F7]

\*1 NOTE:  
The order of pins shown in this diagram is different from that of actual IC3301.  
IC3301 is divided into five and shown as IC3301 (1/5) ~ IC3301 (5/5) in this Digital Main Schematic Diagram Section.







# Power Supply CBA Top View [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]

Because a hot chassis ground is present in the power supply circuit, an isolation transformer must be used. Also, in order to have the ability to increase the input slowly,when troubleshooting this type power supply circuit, a variable isolation transformer is required.

**NOTE:**  
The voltage for parts in hot circuit is measured using hot GND as a common terminal.


**CAUTION !**  
Fixed voltage (or Auto voltage selectable) power supply circuit is used in this unit.  
If Main Fuse (F601) is blown , check to see that all components in the power supply circuit are not defective before you connect the AC plug to the AC power supply.  
Otherwise it may cause some components in the power supply circuit to fail.

 **CAUTION ! :** For continued protection against risk of fire, replace only with same type 4 A, 125V fuse.  
**ATTENTION :** Utiliser un fusible de rechange de même type de 4A, 125V.





Power Supply CBA Bottom View [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]




**CAUTION ! :** For continued protection against risk of fire,  
replace only with same type 4 A, 125V fuse.  
**ATTENTION :** Utiliser un fusible de rechange de même type de 4A, 125V.

Because a hot chassis ground is present in the power supply circuit, an isolation transformer must be used. Also, in order to have the ability to increase the input slowly, when troubleshooting this type power supply circuit, a variable isolation transformer is required.

**NOTE:**  
The voltage for parts in hot circuit is measured using hot GND as a common terminal.

**CAUTION !**  
Fixed voltage (or Auto voltage selectable) power supply circuit is used in this unit. If Main Fuse (F601) is blown, check to see that all components in the power supply circuit are not defective before you connect the AC plug to the AC power supply. Otherwise it may cause some components in the power supply circuit to fail.



**WF1**  
PIN 4 OF  
CN302

**WF3**  
PIN 6 OF  
CN302

**WF2**  
PIN 8 OF  
CN302

**WF7**  
PIN 13 OF  
CN302

**WF4**  
PIN 15 OF  
CN302

**WF5**  
PIN 17 OF  
CN302


**WF6**  
PIN 19 OF  
CN302


Power Supply CBA Top View [LC321SSX, 32MF369B/F7]

Because a hot chassis ground is present in the power supply circuit, an isolation transformer must be used. Also, in order to have the ability to increase the input slowly,when troubleshooting this type power supply circuit, a variable isolation transformer is required.

**NOTE:**  
The voltage for parts in hot circuit is measured using hot GND as a common terminal.

**CAUTION !**  
Fixed voltage (or Auto voltage selectable) power supply circuit is used in this unit. If Main Fuse (F601) is blown , check to see that all components in the power supply circuit are not defective before you connect the AC plug to the AC power supply. Otherwise it may cause some components in the power supply circuit to fail.

 **CAUTION ! :** For continued protection against risk of fire, replace only with same type 4 A, 125V fuse.  
**ATTENTION :** Utiliser un fusible de rechange de même type de 4A, 125V.






Power Supply CBA Bottom View [LC321SSX, 32MF369B/F7]

Because a hot chassis ground is present in the power supply circuit, an isolation transformer must be used. Also, in order to have the ability to increase the input slowly, when troubleshooting this type power supply circuit, a variable isolation transformer is required.

**CAUTION !**  
Fixed voltage (or Auto voltage selectable) power supply circuit is used in this unit. If Main Fuse (F601) is blown, check to see that all components in the power supply circuit are not defective before you connect the AC plug to the AC power supply. Otherwise it may cause some components in the power supply circuit to fail.




4A/125V

**CAUTION ! :** For continued protection against risk of fire, replace only with same type 4 A, 125V fuse.

**ATTENTION :** Utiliser un fusible de rechange de même type de 4A, 125V.

**NOTE:**  
The voltage for parts in hot circuit is measured using hot GND as a common terminal.




- WF1  
PIN 4 OF  
CN302
- WF3  
PIN 6 OF  
CN302
- WF2  
PIN 8 OF  
CN302
- WF7  
PIN 13 OF  
CN302
- WF4  
PIN 15 OF  
CN302
- WF5  
PIN 17 OF  
CN302
- WF6  
PIN 19 OF  
CN302

Inverter CBA Top View [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]

Because a hot chassis ground is present in the power supply circuit, an isolation transformer must be used. Also, in order to have the ability to increase the input slowly,when troubleshooting this type power supply circuit, a variable isolation transformer is required.


**NOTE:**  
The voltage for parts in hot circuit is measured using hot GND as a common terminal.



Inverter CBA Bottom View [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]

Because a hot chassis ground is present in the power supply circuit, an isolation transformer must be used. Also, in order to have the ability to increase the input slowly,when troubleshooting this type power supply circuit, a variable isolation transformer is required.

**NOTE:**  
The voltage for parts in hot circuit is measured using hot GND as a common terminal.








Inverter Power CBA Bottom View [LC321SSX, 32MF369B/F7]

Because a hot chassis ground is present in the power supply circuit, an isolation transformer must be used. Also, in order to have the ability to increase the input slowly,when troubleshooting this type power supply circuit, a variable isolation transformer is required.

**NOTE:**  
The voltage for parts in hot circuit is measured using hot GND as a common terminal.



C


B

A


2

1

Function CBA Top View  
[LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]




Junction CBA Top & Bottom View  
[LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]




BA94F0F01034

Function CBA Bottom View  
[LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]




BA94F0F01034-B

Function CBA Top View [LC321SSX, 32MF369B/F7]




Junction CBA Top & Bottom View [LC321SSX, 32MF369B/F7]




BA91FSF01031

Function CBA Bottom View [LC321SSX, 32MF369B/F7]




BA91FSF01031-B


**IR Sensor CBA Top View**  
 [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]




**Jack CBA Top View**  
 [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]




**IR Sensor CBA Bottom View**  
 [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]




**Jack CBA Bottom View**  
 [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]




### IR Sensor CBA Top View [LC321SSX, 32MF369B/F7]




**Jack CBA Top View [LC321SSX, 32MF369B/F7]**



### IR Sensor CBA Bottom View [LC321SSX, 32MF369B/F7]



### Jack CBA Bottom View [LC321SSX, 32MF369B/F7]



BA91FSF01031-C


BA91FSF01022-B

# WAVEFORMS


**WF1 ~ WF7 =** Waveforms to be observed at  
Waveform check points.  
(Shown in Schematic Diagram.)

**Input:** NTSC Color Bar Signal (with 1kHz Audio Signal)


**WF1** Pin 4 of CN302




**WF5** Pin 17 of CN302




**WF2** Pin 8 of CN302




**WF6** Pin 19 of CN302




**WF3** Pin 6 of CN302



**WF7** Pin 13 of CN302




**WF4** Pin 15 of CN302



# WIRING DIAGRAM


[LC320SLX, 32MF339B/F7, LC320SSX, LC320EMX, LC320EMXF]





# WIRING DIAGRAM

[LC321SSX, 32MF369B/F7]




EXPLODED VIEWS


Cabinet [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMXF]

Comparison Chart of Models and Marks

Model	Mark
LC320SLX	A
32MF339B/F7	B
LC320SSX	C
LC320EMXF	D




Cabinet [LC320EMX]




See Electrical Parts List for parts with this mark.

### Cabinet [LC321SSX, 32MF369B/F7]




# **Packing [LC320SLX, 32MF339B/F7, LC320SSX, LC320EMXF, LC321SSX, 32MF369B/F7]**






Packing [LC320EMX]



# MECHANICAL PARTS LIST

## [ LC320SLX (Serial No. : DS1A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.


**NOTE:** Parts that are not assigned part numbers (-----) are not available.

Ref. No.	Description	Part No.
X4	DRY BATTERY R03/2S	XB0M451T0006
X6	QUICK START GUIDE A91F3UH	1EMN24639
X8	CHILD SAFETY SHEET A94F1UH	1EMN24522
X10	REGISTRATION CARD (SYLVANIA) A94F1UH	1EMN24700

Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F1UH	1ESA19883
A1	FRONT CABINET A91F3UH	1EM023528
A2	CONTROL PLATE A91F3UH	1EM325778
A5	DECORATION PLATE A91F3UH	1EM123373
A6	REAR CABINET A91F0UH	1EM023565
A8	AC CORD HOLDER A94F0UH	1EM325557
A10 	RATING LABEL A91F3UH	-----
A11	JACK LABEL A91F0UH	1EM428377
A13	JACK HOLDER A94F0UH	1EM123173
A15	LOGO LABEL A8A71UH	-----
B1	SHIELD BOX A94F0UH	1EM222764
B4	STAND HOLDER 32W A94F0UH	1EM222763
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A94F0UH	1EM123233
B9	SPEAKER HOLDER (R) A94F0UH	1EM123234
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A8AF0UH	1EM425861
CL201	WIRE ASSEMBLY 15PIN FFC 15PIN 140MM	WX1A94F0-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 310MM RED BLACK	WX1A94F0-202
CL802	WIRE ASSEMBLY 2PIN 2PIN 100MM RED BLACK	WX1A94F0-203
CL1003	WIRE ASSEMBLY 11PIN FFC 11PIN 110MM	WX1A94F0-105
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRE ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3902	WIRE ASSEMBLY 24PIN FFC 24PIN 80MM	WX1A94F0-106
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392A
L9	STAND SCREW KIT A91F0UH	1ESA19881
LCD1	LCD MODULE CMO 6BIT A GRADE	UH32MXA
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91F3UH	1EM428077
S2	STYROFOAM TOP A91F0UH	1EM023566
S3	STYROFOAM BOTTOM A91F0UH	1EM023567
S4	SET BAG (900X850) A8AFFUH	1EM324904
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
S9	STAND HOLD PAD A94F1UH	1EM023746
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91F3UH	1EMN24299
X3	REMOTE CONTROL NH000UD NF000UD	NH000UD

# MECHANICAL PARTS LIST

## [ LC320SLX (Serial No. : DS2A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

**NOTE:** Parts that are not assigned part numbers (-----) are not available.


Ref. No.	Description	Part No.
X4	DRY BATTERY R03/2S	XB0M451T0006
X6	QUICK START GUIDE A91F3UH	1EMN24639
X8	CHILD SAFETY SHEET A94F1UH	1EMN24522
X10	REGISTRATION CARD (SYLVANIA) A94F1UH	1EMN24700

Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F1UH	1ESA19883
A1	FRONT CABINET A91F3UH	1EM023528
A2	CONTROL PLATE A91F3UH	1EM325778
A5	DECORATION PLATE A91F3UH	1EM123373
A6	REAR CABINET A91F0UH	1EM023565
A8	AC CORD HOLDER A94F0UH	1EM325557
A10 	RATING LABEL A91F8UH	-----
A11	JACK LABEL A91F0UH	1EM428377
A13	JACK HOLDER A94F0UH	1EM123173
A15	LOGO LABEL A8A71UH	-----
B1	SHIELD BOX A94F0UH	1EM222764
B4	STAND HOLDER 32W A94F0UH	1EM222763
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A94F0UH	1EM123233
B9	SPEAKER HOLDER (R) A94F0UH	1EM123234
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A8AF0UH	1EM425861
CL201	WIRE ASSEMBLY 15PIN FFC 15PIN 140MM	WX1A94F0-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 310MM RED BLACK	WX1A94F0-212
CL802	WIRE ASSEMBLY 2PIN 2PIN 100MM RED BLACK	WX1A94F0-213
CL1003	WIRE ASSEMBLY 11PIN FFC 11PIN 129MM	WX1A91F6-101
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRE ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3902	WIRE ASSEMBLY 24PIN FFC 24PIN 117.5MM	WX1A91F6-102
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392B
L9	STAND SCREW KIT A91F0UH	1ESA19881
LCD1	LCD MODULE CPT 6BIT A GRADE	UH32PXA
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91F3UH	1EM428077
S2	STYROFOAM TOP A91F0UH	1EM023566
S3	STYROFOAM BOTTOM A91F0UH	1EM023567
S4	SET BAG (900X850) A8AFFUH	1EM324904A
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
S9	STAND HOLD PAD A94F1UH	1EM023746
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91F3UH	1EMN24299A
X3	REMOTE CONTROL NH000UD	NH000UD



# MECHANICAL PARTS LIST

## [ LC320SLX (Serial No. : DS3A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.


**NOTE:** Parts that are not assigned part numbers (-----) are not available.

Ref. No.	Description	Part No.
X4	DRY BATTERY R03/2S	XB0M451T0006
X6	QUICK START GUIDE A91F3UH	1EMN24639
X8	CHILD SAFETY SHEET A94F1UH	1EMN24522
X10	REGISTRATION CARD (SYLVANIA) A94F1UH	1EMN24700

Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F1UH	1ESA19883
A1	FRONT CABINET A91F3UH	1EM023528
A2	CONTROL PLATE A91F3UH	1EM325778
A5	DECORATION PLATE A91F3UH	1EM123373
A6	REAR CABINET A91F0UH	1EM023565
A8	AC CORD HOLDER A94F0UH	1EM325557
A10 	RATING LABEL A91FEUH	-----
A11	JACK LABEL A91F0UH	1EM428377
A13	JACK HOLDER A94F0UH	1EM123173
A15	LOGO LABEL A8A71UH	-----
B1	SHIELD BOX A94F0UH	1EM222764
B4	STAND HOLDER 32W A94F0UH	1EM222763
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A94F0UH	1EM123233
B9	SPEAKER HOLDER (R) A94F0UH	1EM123234
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A8AF0UH	1EM425861
CL201	WIRE ASSEMBLY 15PIN FFC 15PIN 140MM	WX1A94F0-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 310MM RED BLACK	WX1A94F0-212
CL802	WIRE ASSEMBLY 2PIN 2PIN 100MM RED BLACK	WX1A94F0-213
CL1003	WIRE ASSEMBLY 11PIN 11PIN 135MM	WX1A91FB-101
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRE ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3902	WIRE ASSEMBLY 24PIN FFC 24PIN 190MM	WX1A91FB-102
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392A
L9	STAND SCREW KIT A91F0UH	1ESA19881
LCD1	LCD MODULE LG 8BIT A GRADE	UH32LXA
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91F3UH	1EM428077
S2	STYROFOAM TOP A91F0UH	1EM023566
S3	STYROFOAM BOTTOM A91F0UH	1EM023567
S4	SET BAG (900X850) A8AFFUH	1EM324904
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
S9	STAND HOLD PAD A94F1UH	1EM023746
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91F3UH	1EMN24299A
X3	REMOTE CONTROL NH000UD	NH000UD

# MECHANICAL PARTS LIST

## [ 32MF339B/F7 (Serial No. : DS1A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.


**NOTE:** Parts that are not assigned part numbers (-----) are not available.

Ref. No.	Description	Part No.
X4	DRY BATTERY R03/2S	XB0M451T0006
X6	QUICK START GUIDE A91F0UH	1EMN24479
X8	CHILD SAFETY SHEET A94F0UH	1EMN24439
X10	REGISTRATION CARD (MAGNAVOX) A94F0UH	1EMN24699

Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F0UH	1ESA19880
A1	FRONT CABINET A91F0UH	1EM023625
A2	CONTROL PLATE A91F0UH	1EM325799
A5	DECORATION PLATE A91F0UH	1EM123273
A6	REAR CABINET A91F0UH	1EM023565
A8	AC CORD HOLDER A94F0UH	1EM325557
A10 	RATING LABEL A91F0UH	-----
A11	JACK LABEL A91F0UH	1EM428377
A12	POP LABEL A91F0UH	-----
A13	JACK HOLDER A94F0UH	1EM123173
B1	SHIELD BOX A94F0UH	1EM222764
B4	STAND HOLDER 32W A94F0UH	1EM222763
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A94F0UH	1EM123233
B9	SPEAKER HOLDER (R) A94F0UH	1EM123234
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A8AF0UH	1EM425861
CL201	WIRE ASSEMBLY 15PIN FFC 15PIN 140MM	WX1A94F0-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 310MM RED BLACK	WX1A94F0-202
CL802	WIRE ASSEMBLY 2PIN 2PIN 100MM RED BLACK	WX1A94F0-203
CL1003	WIRE ASSEMBLY 11PIN FFC 11PIN 110MM	WX1A94F0-105
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRE ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3902	WIRE ASSEMBLY 24PIN FFC 24PIN 80MM	WX1A94F0-106
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392A
L9	STAND SCREW KIT A91F0UH	1ESA19881
LCD1	LCD MODULE CMO 6BIT A GRADE	UH32MXA
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91F0UH	1EM428117
S2	STYROFOAM TOP A91F0UH	1EM023566
S3	STYROFOAM BOTTOM A91F0UH	1EM023567
S4	SET BAG (900X850) A8AFFUH	1EM324904
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
S9	STAND HOLD PAD A94F0UH	1EM023745
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91F0UH	1EMN24339
X3	REMOTE CONTROL NF802UD NF802UD	NF802UD

# MECHANICAL PARTS LIST

## [ 32MF339B/F7 (Serial No. : DS2A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.


**NOTE:** Parts that are not assigned part numbers (-----) are not available.

Ref. No.	Description	Part No.
X4	DRY BATTERY R03/2S	XB0M451T0006
X6	QUICK START GUIDE A91F0UH	1EMN24479
X8	CHILD SAFETY SHEET A94F0UH	1EMN24439
X10	REGISTRATION CARD (MAGNAVOX) A94F0UH	1EMN24699

Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F0UH	1ESA19880
A1	FRONT CABINET A91F0UH	1EM023625
A2	CONTROL PLATE A91F0UH	1EM325799
A5	DECORATION PLATE A91F0UH	1EM123273
A6	REAR CABINET A91F0UH	1EM023565
A8	AC CORD HOLDER A94F0UH	1EM325557
A10 	RATING LABEL A91F6UH	-----
A11	JACK LABEL A91F0UH	1EM428377
A12	POP LABEL A91F0UH	-----
A13	JACK HOLDER A94F0UH	1EM123173
B1	SHIELD BOX A94F0UH	1EM222764
B4	STAND HOLDER 32W A94F0UH	1EM222763
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A94F0UH	1EM123233
B9	SPEAKER HOLDER (R) A94F0UH	1EM123234
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A8AF0UH	1EM425861
CL201	WIRE ASSEMBLY 15PIN FFC 15PIN 140MM	WX1A94F0-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 310MM RED BLACK	WX1A94F0-212
CL802	WIRE ASSEMBLY 2PIN 2PIN 100MM RED BLACK	WX1A94F0-213
CL1003	WIRE ASSEMBLY 11PIN FFC 11PIN 129MM	WX1A91F6-101
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRA ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3902	WIRE ASSEMBLY 24PIN FFC 24PIN 117.5MM	WX1A91F6-102
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392B
L9	STAND SCREW KIT A91F0UH	1ESA19881
LCD1	LCD MODULE CPT 6BIT A GRADE	UH32PXA
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91F0UH	1EM428117
S2	STYROFOAM TOP A91F0UH	1EM023566
S3	STYROFOAM BOTTOM A91F0UH	1EM023567
S4	SET BAG (900X850) A8AFFUH	1EM324904A
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
S9	STAND HOLD PAD A94F0UH	1EM023745
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91F0UH	1EMN24339B
X3	REMOTE CONTROL NF802UD	NF802UD

# MECHANICAL PARTS LIST

## [ LC320SSX (Serial No. : DS1A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.


**NOTE:** Parts that are not assigned part numbers (-----) are not available.

Ref. No.	Description	Part No.
X3	REMOTE CONTROL NF015UD 170/ ECNLC501/NF015UD	NF015UD
X4	DRY BATTERY(SUNRISE) R6SSE/2S	XB0M451MS002
X6	QUICK START GUIDE A91F1UH	1EMN24679
X8	CHILD SAFETY SHEET A94F1UH	1EMN24522
X10	REGISTRATION CARD (SYLVANIA) A94F1UH	1EMN24700

Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F1UH	1ESA19883
A1	FRONT CABINET A91F1UH	1EM023705
A2	CONTROL PLATE A91F0UH	1EM325799
A5	DECORATION PLATE A91F1UH	1EM123274
A6	REAR CABINET A91F0UH	1EM023565
A8	AC CORD HOLDER A94F0UH	1EM325557
A10 	RATING LABEL A91F1UH	-----
A11	JACK LABEL A91F0UH	1EM428377
A12	POP LABEL A91F0UH	-----
A13	JACK HOLDER A94F0UH	1EM123173
B1	SHIELD BOX A94F0UH	1EM222764
B4	STAND HOLDER 32W A94F0UH	1EM222763
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A94F0UH	1EM123233
B9	SPEAKER HOLDER (R) A94F0UH	1EM123234
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A84F0UH	1EM425861
CL201	WIRE ASSEMBLY 15PIN FFC 15PIN 140MM	WX1A94F0-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 310MM RED BLACK	WX1A94F0-202
CL802	WIRE ASSEMBLY 2PIN 2PIN 100MM RED BLACK	WX1A94F0-203
CL1003	WIRE ASSEMBLY 11PIN FFC 11PIN 110MM	WX1A94F0-105
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRE ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3902	WIRE ASSEMBLY 24PIN FFC 24PIN 80MM	WX1A94F0-106
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392A
L9	STAND SCREW KIT A91F0UH	1ESA19881
LCD1	LCD MODULE CMO 6BIT A GRADE	UH32MXA
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91F1UH	1EM428119
S2	STYROFOAM TOP A91F0UH	1EM023566
S3	STYROFOAM BOTTOM A91F0UH	1EM023567
S4	SET BAG (900X850) A8AFFUH	1EM324904
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
S9	STAND HOLD PAD A94F1UH	1EM023746
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91F1UH	1EMN24340

# MECHANICAL PARTS LIST

## [ LC320EMX (Serial No. : DS1A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.


**NOTE:** Parts that are not assigned part numbers (-----) are not available.

Ref. No.	Description	Part No.
X6	QUICK START GUIDE A91F4UH	1EMN24640
X7	FCC ADDENDUM SHEET A94F0UH	1EMN24959
X8	CHILD SAFETY SHEET A94F1UH	1EMN24522
X10	REGISTRATION CARD (EMERSON) A91F4UH	1EMN24701

Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F4UH	1ESA20186
A1	FRONT CABINET A91F4UH	1EM023925
A2	CONTROL PLATE A91F4UH	1EM325918
A3	FUNCTION KNOB A91F4UH	1EM123473
A4	LED LENS A91F4UH	1EM325919
A6	REAR CABINET A91F4UH	1EM023926
A10 	RATING LABEL A91F4UH	-----
A11	JACK LABEL A91F0UH	1EM428377
A13	JACK HOLDER A94F0UH	1EM123173
A15	LOGO LABEL A8A71UH	-----
B1	SHIELD BOX A94F0UH	1EM222764
B4	STAND HOLDER 32W A94F0UH	1EM222763
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A8AF1UH	1EM323480
B9	SPEAKER HOLDER (R) A8AF1UH	1EM323800
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A8AF0UH	1EM425861
CL201	WIRE ASSEMBLY 15PIN FFC 15PIN 140MM	WX1A94F0-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 310MM RED BLACK	WX1A94F0-202
CL802	WIRE ASSEMBLY 2PIN 2PIN 100MM RED BLACK	WX1A94F0-203
CL1003	WIRE ASSEMBLY 11PIN FFC 11PIN 110MM	WX1A94F0-105
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRE ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3902	WIRE ASSEMBLY 24PIN FFC 24PIN 80MM	WX1A94F0-106
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392A
L9	STAND SCREW KIT A91F0UH	1ESA19881
LCD1	LCD MODULE CMO 6BIT A GRADE	UH32MXA
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91F4UH	1EM428079
S2	STYROFOAM TOP A91F4UH	1EM023985
S3	STYROFOAM BOTTOM A91F4UH	1EM023986
S4	SET BAG (900X850) A8AFFUH	1EM324904
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91F4UH	1EMN24300
X3	REMOTE CONTROL NH000UD NH000UD	NH000UD
X4	DRY BATTERY R03/2S	XB0M451T0006

# MECHANICAL PARTS LIST

## [ LC320EMX (Serial No. : DS2A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.


**NOTE:** Parts that are not assigned part numbers (-----) are not available.

Ref. No.	Description	Part No.
X6	QUICK START GUIDE A91F4UH	1EMN24640
X8	CHILD SAFETY SHEET A94F1UH	1EMN24522
X10	REGISTRATION CARD (EMERSON) A91F4UH	1EMN24701

Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F4UH	1ESA20186
A1	FRONT CABINET A91F4UH	1EM023925
A2	CONTROL PLATE A91F4UH	1EM325918
A3	FUNCTION KNOB A91F4UH	1EM123473
A4	LED LENS A91F4UH	1EM325919
A6	REAR CABINET A91F4UH	1EM023926
A10 	RATING LABEL A91F9UH	-----
A11	JACK LABEL A91F0UH	1EM428377
A13	JACK HOLDER A94F0UH	1EM123173
A15	LOGO LABEL A8A71UH	-----
B1	SHIELD BOX A94F0UH	1EM222764
B4	STAND HOLDER 32W A94F0UH	1EM222763
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A8AF1UH	1EM323480
B9	SPEAKER HOLDER (R) A8AF1UH	1EM323800
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A8AF0UH	1EM425861
CL201	WIRE ASSEMBLY 15PIN FFC 15PIN 140MM	WX1A94F0-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 310MM RED BLACK	WX1A94F0-212
CL802	WIRE ASSEMBLY 2PIN 2PIN 100MM RED BLACK	WX1A94F0-213
CL1003	WIRE ASSEMBLY 11PIN FFC 11PIN 129MM	WX1A91F6-101
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRE ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3902	WIRE ASSEMBLY 24PIN FFC 24PIN 117.5MM	WX1A91F6-102
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392A
L9	STAND SCREW KIT A91F0UH	1ESA19881
LCD1	LCD MODULE CPT 6BIT A GRADE	UH32PXA
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91F4UH	1EM428079
S2	STYROFOAM TOP A91F4UH	1EM023985
S3	STYROFOAM BOTTOM A91F4UH	1EM023986
S4	SET BAG (900X850) A8AFFUH	1EM324904A
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91F4UH	1EMN24300A
X3	REMOTE CONTROL NH000UD NH000UD	NH000UD
X4	DRY BATTERY R03/2S	XB0M451T0006

# MECHANICAL PARTS LIST

## [ LC320EMX (Serial No. : DS3A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.


**NOTE:** Parts that are not assigned part numbers (-----) are not available.

Ref. No.	Description	Part No.
X6	QUICK START GUIDE A91F4UH	1EMN24640
X8	CHILD SAFETY SHEET A94F1UH	1EMN24522
X10	REGISTRATION CARD (EMERSON) A91F4UH	1EMN24701

Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F4UH	1ESA20186
A1	FRONT CABINET A91F4UH	1EM023925
A2	CONTROL PLATE A91F4UH	1EM325918
A3	FUNCTION KNOB A91F4UH	1EM123473
A4	LED LENS A91F4UH	1EM325919
A6	REAR CABINET A91F4UH	1EM023926
A10 	RATING LABEL A91FBUH	-----
A11	JACK LABEL A91F0UH	1EM428377
A13	JACK HOLDER A94F0UH	1EM123173
A15	LOGO LABEL A8A71UH	-----
B1	SHIELD BOX A94F0UH	1EM222764
B4	STAND HOLDER 32W A94F0UH	1EM222763
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A8AF1UH	1EM323480
B9	SPEAKER HOLDER (R) A8AF1UH	1EM323800
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A8AF0UH	1EM425861
CL201	WIRE ASSEMBLY 15PIN FFC 15PIN 140MM	WX1A94F0-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 310MM RED BLACK	WX1A94F0-202
CL802	WIRE ASSEMBLY 2PIN 2PIN 100MM RED BLACK	WX1A94F0-203
CL1003	WIRE ASSEMBLY 11PIN 11PIN 135MM	WX1A91FB-101
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRE ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3902	WIRE ASSEMBLY 24PIN FFC 24PIN 190MM	WX1A91FB-102
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392A
L9	STAND SCREW KIT A91F0UH	1ESA19881
LCD1	LCD MODULE LG 8BIT A GRADE	UH32LXA
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91F4UH	1EM428079
S2	STYROFOAM TOP A91F4UH	1EM023985
S3	STYROFOAM BOTTOM A91F4UH	1EM023986
S4	SET BAG (900X850) A8AFFUH	1EM324904
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91F4UH	1EMN24300
X3	REMOTE CONTROL NH000UD NH000UD	NH000UD
X4	DRY BATTERY R03/2S	XB0M451T0006

# MECHANICAL PARTS LIST

## [ LC320EMXF (Serial No. : DS1A\*\*\*\*\*) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

**NOTE:** Parts that are not assigned part numbers (-----) are not available.


Ref. No.	Description	Part No.
X4	DRY BATTERY R03/2S	XB0M451T0006
X6	QUICK START GUIDE A91FNUH	1EMN25280
X8	CHILD SAFETY SHEET A94F1UH	1EMN24522
X10	REGISTRATION CARD (EMERSON) A91F4UH	1EMN24701

Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F1UH	1ESA19883
A1	FRONT CABINET A91FNUH	1EM024585
A2	CONTROL PLATE A91F3UH	1EM325778
A5	DECORATION PLATE A91FNUH	1EM123913
A6	REAR CABINET A91F0UH	1EM023565
A8	AC CORD HOLDER A94F0UH	1EM325557
A10 	RATING LABEL A91FNUH	-----
A11	JACK LABEL A91F0UH	1EM428377
A13	JACK HOLDER A94F0UH	1EM123173
A15	LOGO LABEL A8A71UH	-----
B1	SHIELD BOX A94F0UH	1EM222764
B4	STAND HOLDER 32W A94F0UH	1EM222763
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A94F0UH	1EM123233
B9	SPEAKER HOLDER (R) A94F0UH	1EM123234
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A8AF0UH	1EM425861
CL201	WIRE ASSEMBLY 15PIN FFC 15PIN 140MM	WX1A94F0-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 310MM RED BLACK	WX1A94F0-212
CL802	WIRE ASSEMBLY 2PIN 2PIN 100MM RED BLACK	WX1A94F0-213
CL1003	WIRE ASSEMBLY 11PIN FFC 11PIN 110MM	WX1A94F0-105
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRE ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3902	WIRE ASSEMBLY 24PIN FFC 24PIN 80MM	WX1A94F0-106
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392B
L9	STAND SCREW KIT A91F0UH	1ESA19881
LCD1	LCD MODULE CMO 6BIT A GRADE	UH32MXA
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91FNUH	1EM429801
S2	STYROFOAM TOP A91F0UH	1EM023566
S3	STYROFOAM BOTTOM A91F0UH	1EM023567
S4	SET BAG (900X850) A8AFFUH	1EM324904A
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
S9	STAND HOLD PAD A94F1UH	1EM023746
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91FNUH	1EMN25279A
X3	REMOTE CONTROL NH000UD NH000UD	NH000UD



# MECHANICAL PARTS LIST

## [ LC320EMXF (Serial No. : DS2A\*\*\*\*\*) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.


**NOTE:** Parts that are not assigned part numbers (-----) are not available.

Ref. No.	Description	Part No.
X4	DRY BATTERY R03/2S	XB0M451T0006
X6	QUICK START GUIDE A91FNUH	1EMN25280
X8	CHILD SAFETY SHEET A94F1UH	1EMN24522
X10	REGISTRATION CARD (EMERSON) A91F4UH	1EMN24701

Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F1UH	1ESA19883
A1	FRONT CABINET A91FNUH	1EM024585
A2	CONTROL PLATE A91F3UH	1EM325778
A5	DECORATION PLATE A91FNUH	1EM123913
A6	REAR CABINET A91F0UH	1EM023565
A8	AC CORD HOLDER A94F0UH	1EM325557
A10 	RATING LABEL A91FPUH	-----
A11	JACK LABEL A91F0UH	1EM428377
A13	JACK HOLDER A94F0UH	1EM123173
A15	LOGO LABEL A8A71UH	-----
B1	SHIELD BOX A94F0UH	1EM222764
B4	STAND HOLDER 32W A94F0UH	1EM222763
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A94F0UH	1EM123233
B9	SPEAKER HOLDER (R) A94F0UH	1EM123234
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A8AF0UH	1EM425861
CL201	WIRE ASSEMBLY 15PIN FFC 15PIN 140MM	WX1A94F0-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 310MM RED BLACK	WX1A94F0-212
CL802	WIRE ASSEMBLY 2PIN 2PIN 100MM RED BLACK	WX1A94F0-213
CL1003	WIRE ASSEMBLY 11PIN FFC 11PIN 129MM	WX1A91F6-101
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRE ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3902	WIRE ASSEMBLY 24PIN FFC 24PIN 117.5MM	WX1A91F6-102
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392B
L9	STAND SCREW KIT A91F0UH	1ESA19881
LCD1	LCD MODULE CPT 6BIT A GRADE	UH32PXA
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91FNUH	1EM429801
S2	STYROFOAM TOP A91F0UH	1EM023566
S3	STYROFOAM BOTTOM A91F0UH	1EM023567
S4	SET BAG (900X850) A8AFFUH	1EM324904A
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
S9	STAND HOLD PAD A94F1UH	1EM023746
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91FNUH	1EMN25279A
X3	REMOTE CONTROL NH000UD NH000UD	NH000UD

# MECHANICAL PARTS LIST

## [ LC320EMXF (Serial No. : DS4A\*\*\*\*\*) ]


**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

**NOTE:** Parts that are not assigned part numbers (-----) are not available.


Ref. No.	Description	Part No.
X4	DRY BATTERY R03/2S	XB0M451T0006
X6	QUICK START GUIDE A91FNUH	1EMN25280
X8	CHILD SAFETY SHEET A94F1UH	1EMN24522
X10	REGISTRATION CARD (EMERSON) A91F4UH	1EMN24701

Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F1UH	1ESA19883
A1	FRONT CABINET A91FNUH	1EM024585
A2	CONTROL PLATE A91F3UH	1EM325778
A5	DECORATION PLATE A91FNUH	1EM123913
A6	REAR CABINET A91F0UH	1EM023565
A8	AC CORD HOLDER A94F0UH	1EM325557
A10 	RATING LABEL A91FNUH	-----
A11	JACK LABEL A91F0UH	1EM428377
A13	JACK HOLDER A94F0UH	1EM123173
A15	LOGO LABEL A8A71UH	-----
B1	SHIELD BOX A94F0UH	1EM222764
B4	STAND HOLDER 32W A94F0UH	1EM222763
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A94F0UH	1EM123233
B9	SPEAKER HOLDER (R) A94F0UH	1EM123234
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A8AF0UH	1EM425861
CL201	WIRE ASSEMBLY 15PIN FFC 15PIN 140MM	WX1A94F0-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 310MM RED BLACK	WX1A94F0-212
CL802	WIRE ASSEMBLY 2PIN 2PIN 100MM RED BLACK	WX1A94F0-213
CL1003	WIRE ASSEMBLY 11PIN FFC 11PIN 129MM	WX1A91F6-101
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRA ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3902	WIRE ASSEMBLY 24PIN FFC 24PIN 117.5MM	WX1A91F6-102
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392B
L9	STAND SCREW KIT A91F0UH	1ESA19881
LCD1	LCD MODULE CMO 6BIT A GRADE	UH32MXF
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91FNUH	1EM429801
S2	STYROFOAM TOP A91F0UH	1EM023566
S3	STYROFOAM BOTTOM A91F0UH	1EM023567
S4	SET BAG (900X850) A8AFFUH	1EM324904A
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
S9	STAND HOLD PAD A94F1UH	1EM023746
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91FNUH	1EMN25279A
X3	REMOTE CONTROL NH000UD NH000UD	NH000UD

# MECHANICAL PARTS LIST [ LC321SSX ]


**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

**NOTE:** Parts that are not assigned part numbers (-----) are not available.


Ref. No.	Description	Part No.
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91F1UH	1EMN24340B
X3	REMOTE CONTROL NF015UD 170/ ECNLC501/NF015UD	NF015UD
X4	DRY BATTERY(SUNRISE) R6SSE/2S	XB0M451MS002
X6	QUICK START GUIDE A91F1UH	1EMN24679
X8	CHILD SAFETY SHEET A94F1UH	1EMN24522
X10	REGISTRATION CARD (SYLVANIA) A94F1UH	1EMN24700


Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F1UH	1ESA19883
A1	FRONT CABINET A91FSUH	1EM024385
A2	CONTROL PLATE A91F0UH	1EM325799
A5	DECORATION PLATE A91FSUH	1EM123854
A6	REAR CABINET A91FSUH	1EM024386
A8	AC CORD HOLDER A94F0UH	1EM325557
A10 	RATING LABEL A91FSUH	-----
A11	JACK LABEL A91F0UH	1EM428377
A12	POP LABEL A91FSUH	-----
A13	JACK HOLDER A91FSUH	1EM123833
B1	SHIELD BOX A91FSUH	1EM123853
B4	STAND HOLDER 32W A91FSUH	1EM223483
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A94F0UH	1EM123233
B9	SPEAKER HOLDER (R) A94F0UH	1EM123234
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A8AF0UH	1EM425861
B29	GASKET(10X50XT2) A91FSUH	1EM430237
B39	PCB HOLDER A91FSUH	1EM024387
B40	STAND HOLDER BRACKET A91FSUH	1EM223484
B41	STAND RUBBER FOOT A94N0UH	1EM428126
B42	GASKET A71F0UH	1EM424393
CL201	WIRE ASSEMBLY 5PIN FFC 5PIN 80MM	WX1A91FS-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 260MM RED BLACK	WX1A91FS-202
CL802	WIRE ASSEMBLY 2PIN 2PIN 190MM RED BLACK	WX1A91FS-203
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRA ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3901	WIRE ASSEMBLY 30P-31P 30PIN-31PIN/ 350MM	WX1A91FS-301
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392B
L9	STAND SCREW KIT A91F0UH	1ESA19881
L13	SCREW SEMS M4X8 PAN HEAD +	FPJ34080
LCD1	LCD MODULE LTA320AP01	UDULCD0SM001
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91FSUH	1EM429579
S2	STYROFOAM TOP A91FSUH	1EM024388
S3	STYROFOAM BOTTOM A91FSUH	1EM024389
S4	SET BAG A71FCUH	1EM323657
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
S9	STAND HOLD PAD A94F1UH	1EM023746

# MECHANICAL PARTS LIST [ 32MF369B/F7 ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.


**NOTE:** Parts that are not assigned part numbers (-----) are not available.

Ref. No.	Description	Part No.
	STAND ASSEMBLY A91F0UH	1ESA19880
A1	FRONT CABINET A91FTUH	1EM024665
A2	CONTROL PLATE A91F0UH	1EM325799
A5	DECORATION PLATE A91FTUH	1EM123993
A6	REAR CABINET A91FSUH	1EM024386
A8	AC CORD HOLDER A94F0UH	1EM325557
A10 	RATING LABEL A91FTUH	-----
A11	JACK LABEL A91F0UH	1EM428377
A12	POP LABEL A91FTUH	-----
A13	JACK HOLDER A91FSUH	1EM123833
B1	SHIELD BOX A91FSUH	1EM123853
B4	STAND HOLDER 32W A91FSUH	1EM223483
B5	WALL MOUNT BRACKET A84N0UH	1EM323797
B8	SPEAKER HOLDER (L) A94F0UH	1EM123233
B9	SPEAKER HOLDER (R) A94F0UH	1EM123234
B15	CLOTH(10X180XT0.5) L0336JG	0EM408827
B27	GASKET A8AF0UH	1EM425861
B29	GASKET(10X50XT2) A91FSUH	1EM430237
B39	PCB HOLDER A91FSUH	1EM024387
B40	STAND HOLDER BRACKET A91FSUH	1EM223484
B41	STAND RUBBER FOOT A94N0UH	1EM428126
B42	GASKET A71F0UH	1EM424393
CL201	WIRE ASSEMBLY 5PIN FFC 5PIN 80MM	WX1A91FS-104
CL801	WIRE ASSEMBLY 2PIN 2PIN 260MM RED BLACK	WX1A91FS-202
CL802	WIRE ASSEMBLY 2PIN 2PIN 190MM RED BLACK	WX1A91FS-203
CL3701	WIRE ASSEMBLY 29PIN FFC 29PIN 50MM	WX1A94F0-101
CL3702	WIRA ASSEMBLY 29PIN FFC 29PIN 70MM	WX1A94F0-111
CL3901	WIRE ASSEMBLY 30P-31P 30PIN-31PIN/ 350MM	WX1A91FS-301
L1	SCREW P-TIGHT M4X14 BIND HEAD+BLK	GBHP4140
L2	SCREW P-TIGHT 3X10 BIND HEAD+	GBHP3100
L6	SCREW S-TIGHT M3X8 BIND HEAD+	GBHS3080
L7	DOUBLE SEMS SCREW M4X10 + BLK	FPH34100
L8	ASSEMBLED SCREW ( D9 M3X6 ) A71F0UH	1EM424392B
L9	STAND SCREW KIT A91F0UH	1ESA19881
L13	SCREW SEMS M4X8 PAN HEAD +	FPJ34080
LCD1	LCD MODULE LTA320AP01	UDULCD0SM001
SP801	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
SP802	SPEAKER MAGNETIC S0412F06A	DSD0809XQ006
<b>PACKING</b>		
S1	CARTON A91FTUH	1EM429997
S2	STYROFOAM TOP A91FSUH	1EM024388
S3	STYROFOAM BOTTOM A91FSUH	1EM024389
S4	SET BAG A71FCUH	1EM323657
S5	SERIAL NO. LABEL TD812HC	-----
S6	STAND BAG A94F0UH	1EM428757
S9	STAND HOLD PAD A94F0UH	1EM023745

Ref. No.	Description	Part No.
<b>ACCESSORIES</b>		
X1	BAG POLYETHYLENE 235X365XT0.03	0EM408420A
X2 	OWNERS MANUAL A91F0UH	1EMN24339B
X3	REMOTE CONTROL NF802UD	NF802UD
X4	DRY BATTERY R03/2S	XB0M451T0006
X6	QUICK START GUIDE A91F0UH	1EMN24479
X8	CHILD SAFETY SHEET A94F0UH	1EMN24439
X10	REGISTRATION CARD (MAGNAVOX) A94F0UH	1EMN24699
X15	HDMI CABLE HIGH SPEED 1500/BLACK	WPZ152JVE001

# ELECTRICAL PARTS LIST

## [ LC320SLX (Serial No. : DS1A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

### NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91F3MMA-002

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91F0MPWS001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C202	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C203	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C204	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C207	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C210	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C216	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C217	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C218	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C219	ELECTROLYTIC CAP. 47μF/25V M	CE1EMASDL470
C221	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 470μF/25V M	CE1EMASDL471
C223	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C224	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C302	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 330μF/10V M	CE1AMASDL331
C305	CHIP CERAMIC CAP.(1608) F Z 0.1μF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470

Ref. No.	Description	Part No.
C501	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C601▲	METALIZED FILM CAP. 0.47μF/250V	CT2E474MS037
C602▲	METALIZED FILM CAP. 0.47μF/250V	CT2E474MS037
C605	CAP ELECTROLYTIC 470μF/200V M	CA2D471DYG07
C609	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.068μF/100V J	CA2A683DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015μF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C632	ELECTROLYTIC CAP. 220μF/25V M	CE1EMASDL221
C633	ELECTROLYTIC CAP. 2200μF/10V M	CE1AMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 220μF/50V M	CE1JMASDL221
C639	ELECTROLYTIC CAP. 1000μF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C644	ELECTROLYTIC CAP 3300μF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTOLYTIC 2200μF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022μF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100μF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C656	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C676	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C734	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C735	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C736	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C743	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102

Ref. No.	Description	Part No.
C809	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C815	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C816	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C829	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C871	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN602	WIRE ASSEMBLY 2PIN 2PIN 145MM RED BLACK	WX1A94F0-201
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D202	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D203	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA07JY036

Ref. No.	Description	Part No.
D205	DIODE ZENER 24BSB-T26	NDTC024BST26
D206	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D207	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D208	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D209	DIODE ZENER 39BSB-T26	NDTB039BST26
D210	DIODE ZENER 6V2BSB-T26	NDTB6R2BST26
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D405	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D406	DIODE ZENER 15BSB-T26	NDTB015BST26
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D416	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE 1N5406	NDLZ001N5406
D602▲	DIODE 1N5406	NDLZ001N5406
D603▲	DIODE 1N5406	NDLZ001N5406
D604▲	DIODE 1N5406	NDLZ001N5406
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	DIODE FR154	NDLZ000FR154
D632	DIODE FR104-B	NDLZ000FR104
D633	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D635	DIODE ZENER 24BSB-T26	NDTB024BST26
D636	RES. CARBON FILM J 1/2W J 2.7 Ω	RCX22R7T1003
D637	SCHOTTKY BARRIER DIODE SB160	NDWZ000SB160
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSB-T26	NDTB010BST26
D645	SHUNT REGULATOR KIA431B-AT/P	NSZBA07JY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA07JY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26

Ref. No.	Description	Part No.
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC201	IC TL3472CDR	NSZBA0TTY115
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRM137
IC871	IC OP AMP NJM4558M(Te1)-#ZZZB	QSZBA0TJR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L804	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q201	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q202	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q203	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q204	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q205	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	TRANSISTOR 2SD400(E)	QQUE002SD400
Q210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q401	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q501	TRANSISTOR 2SC2120-Y(Te2 F T)	QQSY2SC2120F
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-Q(Te2 F T)	QQS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (Te2 F T)	QQS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y(Te2 F T)	QQSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y(Te2 F T)	QQSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y(Te2 F T)	QQSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P

Ref. No.	Description	Part No.
<b>RESISTORS</b>		
R171	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R201	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R202	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R204	RES CARBON FILM T 1/4W J 560 Ω	RCX4561T1001
R206	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R207	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R208	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R209	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R210	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R211	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R212	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R213	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R214	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R216	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R217	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R218	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R219	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R220	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R223	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R225	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R226	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 1W J 2.7 Ω	RN012R7ZU001
R228	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R229	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R231	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R232	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R233	CHIP RES. 1/10W F 750 Ω	RRXAFR5H7500
R234	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 330 Ω	RCX4331T1001
R236	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R237	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R238	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R240	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R241	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R242	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R243	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R245	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R247	METAL OXIDE FILM RES. 1W J 2.7 Ω	RN012R7ZU001
R248	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R301	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R302	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R304	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R305	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R311	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R403	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R404	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R405	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R407	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R408	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 43.0 k Ω	RRXAFR5H4302
R411	CHIP RES. 1/10W F 56k Ω	RRXAFR5H5602
R412	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R601▲	RES. CARBON FILM J 1/2W J 560k Ω	RCX2564T1003
R602▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10

Ref. No.	Description	Part No.
R604	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R606	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R611	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R616	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R637	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R638	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R641	RES CHIP.(1608) 1/10W D 1.1k Ω	RRXADR5H1101
R642	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R644	CHIP RES. 1/10W F 820 Ω	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R651	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R658	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R660	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R661	RES. CARBON FILM J 1/2W J 390 Ω	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 15 Ω	RCX4150T1001
R663	RES CARBON FILM T 1/4W J 1.8k Ω	RCX4182T1001
R664	RES CARBON FILM T 1/4W J 1.8k Ω	RCX4182T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0 Ω	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620 Ω	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	METAL OXIDE FILM RES. 1W J 0.47 Ω	RN01R47ZU001
R673	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R675	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R677	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R678	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R679	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R680	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R682	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22 Ω	RCX4220T1001
R686	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R687	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R693	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R694	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R695	RES CARBON FILM T 1/4W J 33 Ω	RCX4330T1001
R696	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001
R697	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001

Ref. No.	Description	Part No.
R723	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R724	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R763	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R801	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R802	CHIP RES. 1/10W F 27k Ω	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R807	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R810	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R813	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R820	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R842	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R843	CHIP RES. 1/10W J 110 Ω	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220 Ω	RRXAJR5Z0221
R846	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R847	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R875	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R876	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R877	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R879	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R887	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R888	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102



Ref. No.	Description	Part No.
R891	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R892	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD W/O A GND WIRE UL/CSA 1770 NO BLACK	WAC0172LW022
B11	POW HEAT SINK A7120UH	1EM423993
B12	MODULE HEAT SINK PMC P7150UT	1EM423968
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS202	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9932	LT2PC0XB043
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM UC020AF	UTUNNTUSP035

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C757	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
C758	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R762	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		

Ref. No.	Description	Part No.
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91F0M1V-001
	INVERTER CBA	A91F0M1V-001-IV
	FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91F0M1V-001-FNIRJN

## INVERTER CBA

Ref. No.	Description	Part No.
	INVERTER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C1001	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1002	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1003	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1004	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1005	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1006	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1007	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1008	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1009	ELECTROLYTIC CAP. 100 $\mu$ F/25V M	CE1EMASDL101
C1011	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1012	POLYESTER FILM CAP. (PB FREE) 0.0039 $\mu$ F/100V J	CA2A392DT018
C1013	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1014	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C1040	CHIP CERAMIC CAP.(1608) B K 0.47 $\mu$ F/10V	CHD1AK30B474
C1052	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1053	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1056	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1061	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1062	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1063	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1064	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1065	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1066	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1067	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1068	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1072	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1111	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1112	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1113	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1114	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1115	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1116	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1117	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1118	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1122	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1161	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1162	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1163	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1164	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1165	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1166	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061

Ref. No.	Description	Part No.
C1167	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1168	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1172	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1211	CAP CERAMIC HV 15pF/6KV/SLJ	CCA1500TE009
C1212	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1213	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1214	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1215	CAP CERAMIC HV 15pF/6KV/SLJ	CCA1500TE009
C1216	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1217	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1218	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1222	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1500	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1502	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1550	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1552	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1600	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1620	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C1702	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1703	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1800	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1801	ELECTROLYTIC CAP. 22μF/35V M	CE1GMASDL220
C1802	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 1000pF/2KV	CA3D102PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.027μF/100V J	CA2A273DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1940	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKP0B103
C1970	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C1981	CHIP CERAMIC CAP. F Z 0.01μF/50V	CHD1JZ30F103
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CERAMIC CAP. B K 820pF/1KV	CCD3AKP0B821
C1992▲	ELECTROLYTIC CAP 470μF/100V	CE2AMZNDL471
<b>CONNECTORS</b>		
CN1001	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN1003	FFC CONNECTOR IMSA-9615S-11A-PP-A	JC96J11ER007
CN1050▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1100▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1150▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1200▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1000	DIODE ZENER 15BSB-T26	NDTB015BST26
D1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1003	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1004	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1005	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1006	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1040	DIODE ZENER 36BSB-T26	NDTB036BST26
D1060	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1061	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1062	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1063	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1064	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1065	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1066	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1067	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1068	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1069	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1070	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1071	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1072	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1073	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1074	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1110	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1111	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1112	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1113	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1114	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1115	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1116	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1117	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1118	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1119	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1120	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1121	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1122	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1123	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1124	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1160	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1161	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1162	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1163	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1164	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1165	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1166	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1167	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1168	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1169	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1170	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1171	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1172	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1173	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1174	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1210	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1212	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1213	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1214	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1215	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1216	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1217	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1218	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1219	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1220	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1221	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1222	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1223	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1224	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1500	DIODE ZENER 20BSB-T26	NDTB020BST26
D1550	DIODE ZENER 20BSB-T26	NDTB020BST26
D1630	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1700	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1701	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1702	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1703	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1801	DIODE ZENER 10BSB-T26	NDTB010BST26
D1802	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1933	SWITCHING DIODE 1SS133(T-77)	QDT001SS133
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1940	DIODE FAST RECOVERY FR155-B/P	NDWZ0FR155BP
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER 30BSB-T26	NDTB030BST26
D1973	SWITCHING DIODE 1SS133(T-77)	QDT001SS133
D1990	DIODE FAST RECOVERY 31DF4-FC	QDWZ031DF4FC
D1994	DIODE ZENER 1ZB100BB	NDWZ001ZB100
<b>ICS</b>		
IC1000	IC PULSE-WIDTH-MODULATION CONT TL494CDR	NSCA0T0TY006
IC1700	IC BA10324AF-E2	QSZBA0TRM032
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>TRANSISTORS</b>		
Q1001	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1003	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1004	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1005	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1060	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1061	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1110	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1111	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1160	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1161	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1500	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1501	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1502	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1503	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1550	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1551	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1552	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1553	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1600	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1621	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1801	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1803	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1804	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1815	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1970	NPN TRANSISTOR KTC3200-GR-AT/P	NQSGKTC3200P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R1001	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1002	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R1003	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1004	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1005	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1006	RES CARBON FILM T 1/4W J 56k Ω	RCX4563T1001
R1007	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1008	CHIP RES. 1/10W J 2.2k Ω	RRXAJR5Z0222
R1009	CHIP RES. 1/10W J 82k Ω	RRXAJR5Z0823
R1010	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1011	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R1012	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R1013	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000

Ref. No.	Description	Part No.
R1014	CHIP RES. 1/10W F 4.7k Ω	RRXAFR5H4701
R1015	CHIP RES. 1/10W F 7.50 k Ω	RRXAFR5H7501
R1016	CHIP RES. 1/10W J 120k Ω	RRXAJR5Z0124
R1017	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1018	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R1019	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R1021	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1022	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R1023	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R1024	CHIP RES. 1/10W F 100k Ω	RRXAFR5H1003
R1026	CHIP RES. 1/10W F 220 Ω	RRXAFR5H2200
R1028	CHIP RES. 1/10W F 36k Ω	RRXAFR5H3602
R1030	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1031	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R1032	RES CARBON FILM T 1/4W J 24k Ω	RCX4243T1001
R1033	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1034	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1035	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R1036	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1040	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1041	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1043	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1044	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1060	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1061	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1062	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1063	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1064	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1065	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1066	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1067	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1068	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1069	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1070	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1071	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1072	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1080	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1081	CHIP RES. 1/10W J 5.6k Ω	RRXAJR5Z0562
R1110	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1111	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1112	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1113	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1114	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1115	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1116	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1117	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1118	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1119	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1120	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1121	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1122	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1160	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1161	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1162	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1163	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1164	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1165	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1166	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1167	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1168	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1169	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1170	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1171	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001

Ref. No.	Description	Part No.
R1172	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1210	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1211	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1212	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1213	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1214	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1215	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1216	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1217	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1218	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1219	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1220	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1221	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1222	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1500	CHIP RES. 1/10W J 12k $\Omega$	RRXAJR5Z0123
R1501	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1502	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1503	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1504	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1505	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1506	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1550	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1551	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1552	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1553	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1554	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1555	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1556	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1600	CHIP RES. 1/10W J 18k $\Omega$	RRXAJR5Z0183
R1601	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1620	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1621	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1630	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1631	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1700	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R1701	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1800	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1801	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1802	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1803	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1804	RES CARBON FILM T 1/4W J 1.2 $\Omega$	RCX41R2T1001
R1805	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R1806	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1807	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1808	CHIP RES. 1/10W J 5.1k $\Omega$	RRXAJR5Z0512
R1809	CHIP RES. 1/10W J 1.5k $\Omega$	RRXAJR5Z0152
R1810	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1811	RES CARBON FILM T 1/4W J 100k $\Omega$	RCX4104T1001
R1812	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1930	RES CARBON FILM T 1/4W J 47 $\Omega$	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k $\Omega$	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1933	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1934	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1935	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R1936	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.33 $\Omega$	RN02R33ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1940	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1941	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 180k $\Omega$	RCX4184T1001
R1943	RES CARBON FILM T 1/4W J 820k $\Omega$	RCX4824T1001
R1944	RES CARBON FILM T 1/4W J 820k $\Omega$	RCX4824T1001

Ref. No.	Description	Part No.
R1945	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R1946	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1947	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1948	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1967	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1968	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1969	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1970	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R1971	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1972	CHIP RES. 1/10W J 68k $\Omega$	RRXAJR5Z0683
R1973	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1974	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R1975	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1976	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1977	CHIP RES. 1/10W F 27k $\Omega$	RRXAFR5H2702
R1979	CHIP RES. 1/10W F 6.8k $\Omega$	RRXAFR5H6801
R1980	CHIP RES. 1/10W F 360 $\Omega$	RRXAFR5H3600
R1981	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R1982	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1983	RES CARBON FILM T 1/4W J 33k $\Omega$	RCX4333T1001
R1984	RES CARBON FILM T 1/4W J 15k $\Omega$	RCX4153T1001
R1986	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1988	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
<b>MISCELLANEOUS</b>		
B13	HEAT SINK PNA A94FOUH	1EM428121
B14	HEAT SINK PNB ASSEMBLY A94FOUH	1EM428123
BC1301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC1500	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1501	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1550	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1551	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1050▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1100▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1150▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1200▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1950▲	TRANS POWER BCK-35-0607	LTT3PC0XB048

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C108	CAP CERAMIC (AX) 0.1 $\mu$ F/50V/F/Z	CA1J104TU062
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k $\Omega$	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k $\Omega$	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k $\Omega$	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k $\Omega$	RCX4183T1002
<b>SWITCHES</b>		
SW101A	TACT SWITCH SKHHLMA010	SST0101AL049
SW103A	TACT SWITCH SKHHLMA010	SST0101AL049
SW104A	TACT SWITCH SKHHLMA010	SST0101AL049
SW105A	TACT SWITCH SKHHLMA010	SST0101AL049
SW106A	TACT SWITCH SKHHLMA010	SST0101AL049
SW107A	TACT SWITCH SKHHLMA010	SST0101AL049

## IR SENSOR CBA


Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C113	ELECTROLYTIC CAP. 47 $\mu$ F/16V M H7	CE1CMAVSL470
C115	CHIP CERAMIC CAP. CH J 330pF/50V	CHD1JJ3CH331
<b>DIODES</b>		
D104	LED GREEN 333GT/E(FNA)	NPWZ33GTEFNA
D105	LED L-53HT	NP4Z000L53HT
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R126	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		
CL101	WIRE ASSEMBLY 8P 8PIN/170MM	WX1A94F0-001
CL103	WIRE ASSEMBLY 4P 4PIN/250MM	WX1A94F0-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJRSKK044

## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002

# ELECTRICAL PARTS LIST

## [ LC320SLX (Serial No. : DS2A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

### NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91F8MMA-001

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91F6MPWS001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C202	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C203	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C204	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C207	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C210	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C216	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C217	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C218	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C219	ELECTROLYTIC CAP. 47μF/25V M	CE1EMASDL470
C221	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 470μF/25V M	CE1EMASDL471
C223	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C224	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C302	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C305	CHIP CERAMIC CAP.(1608) F Z 0.1μF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470

Ref. No.	Description	Part No.
C501	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C601▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C602▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C605	CAP ELECTROLYTIC 470μF/200V M	CA2D471DYG07
C609	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.068μF/100V J	CA2A683DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015μF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C632	ELECTROLYTIC CAP. 220μF/25V M	CE1EMASDL221
C633	ELECTROLYTIC CAP. 2200μF/10V M	CE1AMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 220μF/50V M	CE1JMASDL221
C639	ELECTROLYTIC CAP. 1000μF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C644	ELECTROLYTIC CAP 3300μF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTOLYTIC 2200μF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022μF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100μF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C656	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C676	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C734	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C735	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C736	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C743	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102

Ref. No.	Description	Part No.
C809	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C815	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C816	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C829	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C871	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN602	WIRE ASSEMBLY 2PIN 2PIN 145MM RED BLACK	WX1A94F0-201
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D202	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D203	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036

Ref. No.	Description	Part No.
D205	DIODE ZENER 30BSB-T26	NDTB030BST26
D206	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D207	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D208	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D209	DIODE ZENER 39BSB-T26	NDTB039BST26
D210	DIODE ZENER 6V2BSB-T26	NDTB6R2BST26
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D405	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D406	DIODE ZENER 27BSA-T26	NDTA027BST26
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D416	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D602▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D603▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D604▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	DIODE FR154	NDLZ000FR154
D632	DIODE FR104-B	NDLZ000FR104
D633	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D635	DIODE ZENER 24BSB-T26	NDTB024BST26
D637	SCHOTTKY BARRIER DIODE SB160	NDWZ000SB160
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSB-T26	NDTB010BST26
D645	SHUNT REGULATOR KIA431B-AT/P	NSZBA0TJY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002

Ref. No.	Description	Part No.
D675	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D676	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC201	IC TL3472CDR	NSZBA0TTY115
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SSS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRM137
IC871	IC OP AMP NJM4558M(Te1)-#ZZZB	QSZBA0JR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG020Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG020Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L804	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q201	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q202	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q203	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q204	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q205	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	TRANSISTOR 2SD400(E)	QQUE002SD400
Q210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q401	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q501	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-O (TE2 F T)	QQS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P

Ref. No.	Description	Part No.
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
<b>RESISTORS</b>		
R171	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R201	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R202	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R204	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R206	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R207	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R208	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R209	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R210	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R211	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R212	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R213	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R214	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R216	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R217	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R218	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R219	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R220	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R223	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R225	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R226	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 2W J 4.7 Ω	RN024R7ZU001
R228	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R229	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R231	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R232	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R233	CHIP RES. 1/10W F 120 Ω	RRXAFR5H1200
R234	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 100 Ω	RCX4101T1001
R236	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R237	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R238	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R240	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R241	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R242	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R243	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R245	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R247	METAL OXIDE FILM RES. 2W J 4.7 Ω	RN024R7ZU001
R248	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R301	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R302	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R304	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R305	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R311	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R403	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R404	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R405	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R407	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R408	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 43.0 k Ω	RRXAFR5H4302
R411	CHIP RES. 1/10W F 56k Ω	RRXAFR5H5602
R412	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R601▲	RES. CARBON FILM J 1/2W J 560k Ω	RCX2564T1003



Ref. No.	Description	Part No.
R602▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R604	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R606	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R611	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R616	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R636	RES. CARBON FILM J 1/2W J 2.7 Ω	RCX22R7T1003
R637	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R638	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R641	RES CHIP.(1608) 1/10W D 1.1k Ω	RRXADR5H1101
R642	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R644	CHIP RES. 1/10W F 820 Ω	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R651	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R658	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R660	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R661	RES. CARBON FILM J 1/2W J 390 Ω	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 15 Ω	RCX4150T1001
R663	RES CARBON FILM T 1/4W J 1.8k Ω	RCX4182T1001
R664	RES CARBON FILM T 1/4W J 1.8k Ω	RCX4182T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0 Ω	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620 Ω	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	METAL OXIDE FILM RES. 1W J 0.47 Ω	RN01R47ZU001
R673	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R675	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R677	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R678	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R679	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R680	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R682	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22 Ω	RCX4220T1001
R686	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R687	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R693	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R694	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R695	RES CARBON FILM T 1/4W J 33 Ω	RCX4330T1001

Ref. No.	Description	Part No.
R696	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001
R697	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001
R723	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R724	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R763	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R801	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R802	CHIP RES. 1/10W F 27k Ω	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R807	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R810	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R813	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R820	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R842	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R843	CHIP RES. 1/10W J 110 Ω	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220 Ω	RRXAJR5Z0221
R846	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R847	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R875	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R876	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R877	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R879	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104

Ref. No.	Description	Part No.
R887	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R888	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R891	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R892	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD W/O A GND WIRE UL/CSA 1770 NO BLACK	WAC0172LW022
B11	POW HEAT SINK A7120UH	1EM423993
B12	MODULE HEAT SINK PMC P7150UT	1EM423968
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS202	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	INDUCTOR 22 $\mu$ H-K-5FT	LLARKBSTU220
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+-10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9932	LTT2PC0XB043
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM UC020AF	UTUNNTUSP035

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C757	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
C758	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393

Ref. No.	Description	Part No.
R762	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91F6M1V-001
	INVERTER CBA	A91F6M1V-001-IV
	FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91F6M1V-001-FNIRJN

## INVERTER CBA

Ref. No.	Description	Part No.
	INVERTER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C115	CHIP CERAMIC CAP. CH J 330pF/50V	CHD1JJ3CH331
C1001	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1002	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1003	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1004	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1005	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1006	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1007	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1008	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1009	ELECTROLYTIC CAP. 100 $\mu$ F/25V M	CE1EMASDL101
C1011	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1012	POLYESTER FILM CAP. (PB FREE) 0.0039 $\mu$ F/100V J	CA2A392DT018
C1013	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1014	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C1040	CHIP CERAMIC CAP.(1608) B K 0.47 $\mu$ F/10V	CHD1AK30B474
C1052	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1053	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1056	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1061	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1062	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1063	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1064	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1065	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1066	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1067	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1068	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1072	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1111	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1112	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1113	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1114	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1115	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1116	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1117	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1118	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1122	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1161	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1162	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1163	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100

Ref. No.	Description	Part No.
C1164	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1165	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1166	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1167	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1168	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1172	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1211	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1212	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1213	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1214	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1215	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1216	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1217	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1218	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1222	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1500	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1502	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1550	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1552	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1600	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1620	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1J33CH102
C1702	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1703	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1800	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1801	ELECTROLYTIC CAP. 22μF/35V M	CE1GMASDL220
C1802	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 820pF/2KV	CA3D821PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.027μF/100V J	CA2A273DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1940	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKN0B103
C1970	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C1981	CHIP CERAMIC CAP. F Z 0.01μF/50V	CHD1JZ30F103
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CAP CERAMIC HV 820pF/1KV B K	CA3A821TE006
C1992▲	ELECTROLYTIC CAP 470μF/100V	CE2AMZNDL471
<b>CONNECTORS</b>		
CN1001	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN1003	FFC CONNECTOR IMSA-9615S-11A-PP-A	JC96J11ER007
CN1050▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1100▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1150▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1200▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1000	DIODE ZENER 15BSB-T26	NDTB015BST26
D1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1003	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1004	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1005	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1006	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1040	DIODE ZENER 36BSB-T26	NDTB036BST26
D1060	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1061	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1062	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1063	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1064	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1065	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1066	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1067	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1068	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1069	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1070	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1071	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1072	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1073	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1074	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1110	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1111	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1112	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1113	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1114	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1115	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1116	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1117	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1118	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1119	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1120	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1121	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1122	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1123	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1124	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1160	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1161	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1162	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1163	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1164	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1165	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1166	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1167	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1168	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1169	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1170	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1171	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1172	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1173	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1174	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1210	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1212	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1213	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1214	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1215	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1216	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1217	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1218	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1219	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1220	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1221	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1222	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1223	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1224	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1500	DIODE ZENER 20BSB-T26	NDTB020BST26
D1550	DIODE ZENER 20BSB-T26	NDTB020BST26
D1630	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1700	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1701	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1702	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1703	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1801	DIODE ZENER 10BSB-T26	NDTB010BST26
D1802	WIRE COPPER 6111-06003-0120	XZ40C0SHG002

Ref. No.	Description	Part No.
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1933	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1940	DIODE FAST RECOVERY FR155-B/P	NDWZ0FR155BP
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER 30BSB-T26	NDTB030BST26
D1973	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1990	DIODE FAST RECOVERY 31DF4-FC	QDWZ031DF4FC
D1994	DIODE ZENER 1ZB100BB	NDWZ001ZB100
<b>ICS</b>		
IC1000	IC PULSE-WIDTH-MODULATION CONT TL494CDR	NSCA0T0TY006
IC1700	IC BA10324AF-E2	QSZBA0TRM032
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>TRANSISTORS</b>		
Q1001	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1003	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1004	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1005	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1060	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1061	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1110	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1111	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1160	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1161	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1500	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1501	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1502	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1503	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1550	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1551	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1552	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1553	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1600	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1621	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1801	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1803	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1804	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1815	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1970	NPN TRANSISTOR KTC3200-GR-AT/P	NQSGKTC3200P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R126	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1001	CHIP RES. 1/10W F 22k $\Omega$	RRXAFR5H2202
R1002	CHIP RES. 1/10W F 1.0k $\Omega$	RRXAFR5H1001
R1003	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1004	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R1005	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1006	RES CARBON FILM T 1/4W J 56k $\Omega$	RCX4563T1001
R1007	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1008	CHIP RES. 1/10W J 2.2k $\Omega$	RRXAJR5Z0222
R1009	CHIP RES. 1/10W J 82k $\Omega$	RRXAJR5Z0823

Ref. No.	Description	Part No.
R1010	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R1011	CHIP RES. 1/10W F 10k $\Omega$	RRXAFR5H1002
R1012	CHIP RES. 1/10W F 24k $\Omega$	RRXAFR5H2402
R1013	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R1014	CHIP RES. 1/10W F 4.7k $\Omega$	RRXAFR5H4701
R1015	CHIP RES. 1/10W F 7.5k $\Omega$	RRXAFR5H7501
R1016	CHIP RES. 1/10W J 120k $\Omega$	RRXAJR5Z0124
R1017	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1018	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R1019	WIRE COPPER 6111-06003-0120	XZ40C05HG002
R1021	RES CARBON FILM T 1/4W J 10k $\Omega$	RCX4103T1001
R1022	CHIP RES. 1/10W F 2.2k $\Omega$	RRXAFR5H2201
R1023	CHIP RES. 1/10W F 3.3k $\Omega$	RRXAFR5H3301
R1024	CHIP RES. 1/10W F 100k $\Omega$	RRXAFR5H1003
R1026	CHIP RES. 1/10W F 220 $\Omega$	RRXAFR5H2200
R1028	CHIP RES. 1/10W F 36k $\Omega$	RRXAFR5H3602
R1030	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1031	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R1032	RES CARBON FILM T 1/4W J 24k $\Omega$	RCX4243T1001
R1033	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1034	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1035	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R1036	RES CARBON FILM T 1/4W J 10k $\Omega$	RCX4103T1001
R1040	METAL OXIDE FILM RES. 2W J 0.39 $\Omega$	RN02R39ZU001
R1041	RES CARBON FILM T 1/4W J 33k $\Omega$	RCX4333T1001
R1043	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1044	METAL OXIDE FILM RES. 2W J 0.39 $\Omega$	RN02R39ZU001
R1060	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1061	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1062	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1063	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1064	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1065	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1066	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1067	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1068	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1069	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1070	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1071	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1072	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1080	CHIP RES. 1/10W F 22k $\Omega$	RRXAFR5H2202
R1081	CHIP RES. 1/10W J 5.6k $\Omega$	RRXAJR5Z0562
R1110	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1111	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1112	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1113	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1114	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1115	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1116	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1117	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1118	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1119	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1120	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1121	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1122	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1160	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1161	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1162	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1163	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1164	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1165	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1166	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1167	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203

Ref. No.	Description	Part No.
R1168	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1169	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1170	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1171	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1172	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1210	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1211	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1212	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1213	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1214	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1215	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1216	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1217	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1218	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1219	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1220	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1221	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1222	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1500	CHIP RES. 1/10W J 12k Ω	RRXAJR5Z0123
R1501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R1502	RES CARBON FILM T 1/4W J 150 Ω	RCX4151T1001
R1503	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1504	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1505	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1506	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1550	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1551	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R1552	RES CARBON FILM T 1/4W J 150 Ω	RCX4151T1001
R1553	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1554	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1555	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1556	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1600	CHIP RES. 1/10W J 18k Ω	RRXAJR5Z0183
R1601	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1620	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1621	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1630	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1631	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R1700	CHIP RES. 1/10W J 8.2k Ω	RRXAJR5Z0822
R1701	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1800	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1801	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1802	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1803	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R1804	RES CARBON FILM T 1/4W J 1.2 Ω	RCX41R2T1001
R1805	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R1806	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1807	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1808	CHIP RES. 1/10W J 5.1k Ω	RRXAJR5Z0512
R1809	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R1810	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R1811	RES CARBON FILM T 1/4W J 100k Ω	RCX4104T1001
R1812	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1930	RES CARBON FILM T 1/4W J 47 Ω	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 82 Ω	RCX4820T1001
R1933	RES CARBON FILM T 1/4W J 82 Ω	RCX4820T1001
R1934	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R1935	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R1936	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.33 Ω	RN02R33ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1940	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001

Ref. No.	Description	Part No.
R1941	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 180k Ω	RCX4184T1001
R1943	RES CARBON FILM T 1/4W J 820k Ω	RCX4824T1001
R1944	RES CARBON FILM T 1/4W J 820k Ω	RCX4824T1001
R1945	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R1946	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1947	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1948	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1967	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1968	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1969	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1970	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R1971	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1972	CHIP RES. 1/10W J 68k Ω	RRXAJR5Z0683
R1973	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1975	CHIP RES. 1/10W F 30k Ω	RRXAFR5H3002
R1976	CHIP RES. 1/10W F 30k Ω	RRXAFR5H3002
R1977	CHIP RES. 1/10W F 27k Ω	RRXAFR5H2702
R1979	CHIP RES. 1/10W F 6.8k Ω	RRXAFR5H6801
R1980	CHIP RES. 1/10W F 360 Ω	RRXAFR5H3600
R1981	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1982	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R1983	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1984	RES CARBON FILM T 1/4W J 15k Ω	RCX4153T1001
R1986	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1988	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
<b>MISCELLANEOUS</b>		
B13	HEAT SINK PNA A94FOUH	1EM428121
B14	HEAT SINK PNB ASSEMBLY A94FOUH	1EM428123
BC1301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC1500	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1501	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1550	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1551	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1050▲	TRANS INVERTER HVT-153	LTZ3PZ0XB009
T1100▲	TRANS INVERTER HVT-153	LTZ3PZ0XB009
T1150▲	TRANS INVERTER HVT-153	LTZ3PZ0XB009
T1200▲	TRANS INVERTER HVT-153	LTZ3PZ0XB009
T1950▲	TRANS POWER BCK-35-0607	LTT3PC0XB048

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C108	CAP CERAMIC (AX) 0.1μF/50V/F/Z	CA1J104TU062
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k Ω	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k Ω	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k Ω	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k Ω	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k Ω	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k Ω	RCX4183T1002
<b>SWITCHES</b>		
SW101A	TACT SWITCH SKH-HLMA010	SST0101AL049
SW103A	TACT SWITCH SKH-HLMA010	SST0101AL049
SW104A	TACT SWITCH SKH-HLMA010	SST0101AL049
SW105A	TACT SWITCH SKH-HLMA010	SST0101AL049

Ref. No.	Description	Part No.
SW106A	TACT SWITCH SKHHLMA010	SST0101AL049
SW107A	TACT SWITCH SKHHLMA010	SST0101AL049

## IR SENSOR CBA


Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C113	ELECTROLYTIC CAP. 47 $\mu$ F/16V M H7	CE1CMAVSL470
<b>DIODES</b>		
D104	LED GREEN 333GT/E(FNA)	NPWZ33GTEFNA
D105	LED L-53HT	NP4Z000L53HT
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		
CL101	WIRE ASSEMBLY 8P 8PIN/170MM	WX1A94F0-001
CL103	WIRE ASSEMBLY 4P 4PIN/250MM	WX1A94F0-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJRSKK044

## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002

# ELECTRICAL PARTS LIST

## [ LC320SLX (Serial No. : DS3A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

### NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91FEMMA-002

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91FBMPWS001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C202	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C203	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C204	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C218	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C219	ELECTROLYTIC CAP. 47μF/25V M	CE1EMASDL470
C221	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 470μF/25V M	CE1EMASDL471
C223	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C224	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C302	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C305	CHIP CERAMIC CAP.(1608) F Z 0.1μF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C501	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C601▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C602▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C605	CAP ELECTROLYTIC 470μF/200V M	CA2D471DYG07

Ref. No.	Description	Part No.
C609	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.068μF/100V J	CA2A683DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015μF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C632	ELECTROLYTIC CAP. 220μF/25V M	CE1EMASDL221
C633	ELECTROLYTIC CAP. 2200μF/10V M	CE1AMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 220μF/50V M	CE1JMASDL221
C639	ELECTROLYTIC CAP. 1000μF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C644	ELECTROLYTIC CAP 3300μF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTROLYTIC 2200μF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022μF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100μF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C656	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C675	ELECTROLYTIC CAP. 330μF/10V M	CE1AMASDL331
C676	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C734	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C735	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C736	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C743	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C809	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP.(1608) B K 0.47μF/16V	CHD1CK30B474

Ref. No.	Description	Part No.
C815	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C816	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C829	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP.(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP.(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP.(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP.(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP.(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP.(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP.(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C871	CHIP CERAMIC CAP.(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP.(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP.(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP.(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN602	WIRE ASSEMBLY 2PIN 2PIN 145MM RED BLACK	WX1A94F0-201
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D203	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D205	DIODE ZENER 30BSB-T26	NDTD030BST26
D206	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D207	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D208	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D209	DIODE ZENER 39BSB-T26	NDTB039BST26
D210	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D405	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D406	DIODE ZENER 27BSA-T26	NDTA027BST26
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D416	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D602▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D603▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D604▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	DIODE FR154	NDLZ000FR154
D632	DIODE FR104-B	NDLZ000FR104
D633	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D635	DIODE ZENER 24BSB-T26	NDTB024BST26
D637	SCHOTTKY BARRIER DIODE SB160	NDWZ000SB160
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSB-T26	NDTB010BST26
D645	SHUNT REGULATOR KIA431B-AT/P	NSZBA0TJY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D675	DIODE SCHOTTKY SB120BB	NDWZ000SB120
D676	DIODE SCHOTTKY SB120BB	NDWZ000SB120
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26



Ref. No.	Description	Part No.
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SSS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRM137
IC871	IC OP AMP NJM4558M(TE1)-#ZZZB	QSZBA0TJR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L804	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q201	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q205	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	TRANSISTOR 2SD400(E)	QQUE002SD400
Q210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q401	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q501	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-O(TE2 F T)	QOS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
<b>RESISTORS</b>		
R171	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R201	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R206	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R207	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000

Ref. No.	Description	Part No.
R209	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R216	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R217	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R218	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R219	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R220	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R223	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R225	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R226	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 2W J 5.6 Ω	RN025R6ZU001
R228	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R229	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R231	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R232	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R233	CHIP RES. 1/10W F 120 Ω	RRXAFR5H1200
R234	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 27 Ω	RCX4270T1001
R236	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R237	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R238	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R240	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R241	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R242	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R243	RES CARBON FILM T 1/4W J 33 Ω	RCX4330T1001
R245	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R247	METAL OXIDE FILM RES. 2W J 5.6 Ω	RN025R6ZU001
R248	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R249	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R301	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R302	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R304	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R305	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R311	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R403	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R404	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R405	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R407	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R408	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 43.0 k Ω	RRXAFR5H4302
R411	CHIP RES. 1/10W F 56k Ω	RRXAFR5H5602
R412	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R601▲	RES. CARBON FILM J 1/2W J 560k Ω	RCX2564T1003
R602▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R604	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R606	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R611	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R616	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R636	RES. CARBON FILM J 1/2W J 2.7 Ω	RCX22R7T1003
R637	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R638	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001

Ref. No.	Description	Part No.
R641	RES CHIP.(1608) 1/10W D 1.1kΩ	RRXADR5H1001
R642	RES CHIP.(1608) 1/10W D 10kΩ	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10kΩ	RRXADR5H1002
R644	CHIP RES. 1/10W F 820Ω	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270Ω	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180Ω	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0kΩ	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 4.7kΩ	RCX4472T1001
R651	CHIP RES. 1/10W J 1Ω	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24kΩ	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10kΩ	RRXAJR5Z0103
R658	CHIP RES. 1/10W J 10kΩ	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47kΩ	RRXAJR5Z0473
R660	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R661	RES. CARBON FILM J 1/2W J 390Ω	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 15Ω	RCX4150T1001
R663	RES CARBON FILM T 1/4W J 1.8kΩ	RCX4182T1001
R664	RES CARBON FILM T 1/4W J 1.8kΩ	RCX4182T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0Ω	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620Ω	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0kΩ	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	METAL OXIDE FILM RES. 1W J 0.47Ω	RN01R47ZU001
R673	RES CARBON FILM T 1/4W J 22kΩ	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.0kΩ	RCX4102T1001
R675	CHIP RES. 1/10W J 10kΩ	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 22kΩ	RRXAJR5Z0223
R677	RES CARBON FILM T 1/4W J 270Ω	RCX4271T1001
R678	RES CARBON FILM T 1/4W J 10Ω	RCX4100T1001
R679	CHIP RES. 1/10W F 3.3kΩ	RRXAFR5H3301
R680	CHIP RES. 1/10W F 6.8kΩ	RRXAFR5H6801
R682	RES CARBON FILM T 1/4W J 2.7Ω	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7Ω	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22Ω	RCX4220T1001
R686	RES CARBON FILM T 1/4W J 1.0kΩ	RCX4102T1001
R687	RES CARBON FILM T 1/4W J 10Ω	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10Ω	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2kΩ	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7Ω	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7Ω	RCX42R7T1001
R693	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R694	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R695	RES CARBON FILM T 1/4W J 33Ω	RCX4330T1001
R696	METAL OXIDE FILM RES. 1W J 3.3Ω	RN013R3ZU001
R697	METAL OXIDE FILM RES. 1W J 3.3Ω	RN013R3ZU001
R723	CHIP RES. 1/10W J 15kΩ	RRXAJR5Z0153
R724	CHIP RES. 1/10W J 15kΩ	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39kΩ	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39kΩ	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75Ω	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75Ω	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75Ω	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10Ω	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10Ω	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10Ω	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15kΩ	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15kΩ	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39kΩ	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39kΩ	RRXAJR5Z0393

Ref. No.	Description	Part No.
R763	RES CARBON FILM T 1/4W J 10kΩ	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10kΩ	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10kΩ	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10kΩ	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10kΩ	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100kΩ	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100kΩ	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100kΩ	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100kΩ	RRXAJR5Z0104
R801	CHIP RES.(1608) 1/10W 0Ω	RRXAZR5Z0000
R802	CHIP RES. 1/10W F 27kΩ	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11kΩ	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11kΩ	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7kΩ	RRXAJR5Z0472
R807	CHIP RES.(1608) 1/10W 0Ω	RRXAZR5Z0000
R810	CHIP RES.(1608) 1/10W 0Ω	RRXAZR5Z0000
R813	CHIP RES. 1/10W J 10kΩ	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3kΩ	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10kΩ	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3kΩ	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100kΩ	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10kΩ	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22kΩ	RCX4223T1001
R820	CHIP RES. 1/10W J 22kΩ	RRXAJR5Z0223
R842	CHIP RES.(1608) 1/10W 0Ω	RRXAZR5Z0000
R843	CHIP RES. 1/10W J 110Ω	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220Ω	RRXAJR5Z0221
R846	CHIP RES.(1608) 1/10W 0Ω	RRXAZR5Z0000
R847	CHIP RES. 1/10W J 4.7kΩ	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7kΩ	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560Ω	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560Ω	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100kΩ	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100kΩ	RRXAJR5Z0104
R875	CHIP RES.(1608) 1/10W 0Ω	RRXAZR5Z0000
R876	CHIP RES.(1608) 1/10W 0Ω	RRXAZR5Z0000
R877	CHIP RES. 1/10W J 1kΩ	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0kΩ	RCX4102T1001
R879	CHIP RES. 1/10W J 47kΩ	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47kΩ	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100Ω	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100Ω	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100kΩ	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100kΩ	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100kΩ	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100kΩ	RRXAJR5Z0104
R887	CHIP RES. 1/10W J 22kΩ	RRXAJR5Z0223
R888	CHIP RES. 1/10W J 1kΩ	RRXAJR5Z0102
R891	CHIP RES. 1/10W J 20kΩ	RRXAJR5Z0203
R892	CHIP RES. 1/10W J 20kΩ	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22kΩ	RRXAJR5Z0223
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD W/O A GND WIRE UL/CSA 1770 NO BLACK	WAC0172LW022
B11	POW HEAT SINK A7120UH	1EM423993
B12	MODULE HEAT SINK PMC P7150UT	1EM423968
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030

Ref. No.	Description	Part No.
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS201	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	INDUCTOR 22μH-K-5FT	LLARKBSTU220
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+-10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9932	LTT2PC0XB043
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM UC020AF	UTUNNTUSP035

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C757	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C758	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R762	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91FEM1V-001
	INVERTER CBA	A91FEM1V-001-IV
	FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91FEM1V-001-FNIRJN

## INVERTER CBA

Ref. No.	Description	Part No.
	INVERTER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C1001	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1002	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1003	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1004	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1005	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1006	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1007	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1008	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1009	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1011	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1012	POLYESTER FILM CAP. (PB FREE) 0.0039μF/100V J	CA2A392DT018
C1013	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1014	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C1040	CHIP CERAMIC CAP.(1608) B K 0.47μF/10V	CHD1AK30B474
C1050	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKN0B103
C1051	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKN0B103
C1052	ELECTROLYTIC CAP 100μF/100V	CE2AMZNDL101
C1053	ELECTROLYTIC CAP 100μF/100V	CE2AMZNDL101
C1056	ELECTROLYTIC CAP 100μF/100V	CE2AMZNDL101
C1061	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1062	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1063	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1064	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1065	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1066	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1067	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1068	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1072	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1111	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1112	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1113	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1114	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1115	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1116	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1117	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1118	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1122	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1161	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1162	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1163	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1164	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1165	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1166	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1167	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1168	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1172	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1211	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1212	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061

Ref. No.	Description	Part No.
C1213	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1214	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1215	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1216	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1217	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1218	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1222	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1500	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1502	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1550	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1552	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1600	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1620	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C1702	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1703	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1800	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1801	ELECTROLYTIC CAP. 22μF/35V M	CE1GMASDL220
C1802	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 820pF/2KV	CA3D821PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.027μF/100V J	CA2A273DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1940	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKN0B103
C1970	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C1981	CHIP CERAMIC CAP. F Z 0.01μF/50V	CHD1JZ30F103
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CAP CERAMIC HV 820pF/1KV B K	CA3A821TE006
C1992▲	ELECTROLYTIC CAP 470μF/100V	CE2AMZNDL471
<b>CONNECTORS</b>		
CN1001	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN1005	FFC CONNECTOR IMSA-9615S-11A-PP-A	JC96J11ER007
CN1050▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1100▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1150▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1200▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1000	DIODE ZENER 15BSB-T26	NDTB015BST26
D1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1003	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1004	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1005	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1006	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1040	DIODE ZENER 36BSB-T26	NDTB036BST26
D1050	DIODE FR104-B	NDLZ000FR104
D1051	DIODE FR104-B	NDLZ000FR104
D1060	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1061	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1062	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1063	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1064	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1065	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1066	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1067	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1068	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1069	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1070	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1071	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1072	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1073	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1074	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1110	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1111	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1112	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1113	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1114	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1115	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1116	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1117	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1118	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1119	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1120	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1121	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1122	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1123	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1124	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1160	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1161	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1162	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1163	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1164	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1165	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1166	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1167	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1168	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1169	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1170	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1171	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1172	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1173	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1174	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1210	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1212	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1213	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1214	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1215	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1216	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1217	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1218	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1219	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1220	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1221	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1222	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1223	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1224	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1500	DIODE ZENER 20BSB-T26	NDTB020BST26
D1550	DIODE ZENER 20BSB-T26	NDTB020BST26
D1630	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1700	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1701	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1702	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1703	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1801	DIODE ZENER 10BSB-T26	NDTB010BST26
D1802	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1933	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1940	DIODE FAST RECOVERY FR155-B/P	NDWZ0FR155BP

Ref. No.	Description	Part No.
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER 30BSB-T26	NDTB030BST26
D1973	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1990	DIODE FAST RECOVERY 31DF4-FC	QDWZ031DF4FC
D1994	DIODE ZENER 1ZB100BB	NDWZ001ZB100
<b>ICS</b>		
IC1000	IC PULSE-WIDTH-MODULATION CONT TL494CDR	NSCA0T0TY006
IC1700	IC BA10324AF-E2	QSZBA0TRM032
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>TRANSISTORS</b>		
Q1001	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1003	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1004	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1005	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1060	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1061	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1110	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1111	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1160	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1161	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1500	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1501	TRANSISTOR 2SC2120-Y(T2 F T)	QOSY2SC2120F
Q1502	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q1503	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1550	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1551	TRANSISTOR 2SC2120-Y(T2 F T)	QOSY2SC2120F
Q1552	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q1553	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1600	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1621	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1801	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1803	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1804	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1815	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y(T2 F T)	QOSY2SC2120F
Q1970	NPN TRANSISTOR KTC3200-GR-AT/P	NQSGKTC3200P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R1001	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1002	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R1003	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1004	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1005	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1006	RES CARBON FILM T 1/4W J 56k Ω	RCX4563T1001
R1007	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1008	CHIP RES. 1/10W J 2.2k Ω	RRXAJR5Z0222
R1009	CHIP RES. 1/10W J 82k Ω	RRXAJR5Z0823
R1010	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1011	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R1012	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R1013	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1014	CHIP RES. 1/10W F 4.7k Ω	RRXAFR5H4701
R1015	CHIP RES. 1/10W F 7.50 k Ω	RRXAFR5H7501
R1016	CHIP RES. 1/10W J 120k Ω	RRXAJR5Z0124

Ref. No.	Description	Part No.
R1017	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1018	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R1019	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R1021	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1022	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R1023	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R1024	CHIP RES. 1/10W F 100k Ω	RRXAFR5H1003
R1026	CHIP RES. 1/10W F 220 Ω	RRXAFR5H2200
R1028	CHIP RES. 1/10W F 36k Ω	RRXAFR5H3602
R1030	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1031	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R1032	RES CARBON FILM T 1/4W J 24k Ω	RCX4243T1001
R1033	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1034	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1035	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R1036	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1040	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1041	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1043	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1044	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1050	METAL OXIDE RES. 1W J 8.2k Ω	RN01822ZU001
R1051	METAL OXIDE RES. 1W J 8.2k Ω	RN01822ZU001
R1060	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1061	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1062	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1063	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1064	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1065	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1066	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1067	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1068	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1069	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1070	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1071	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1072	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1080	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1081	CHIP RES. 1/10W J 5.6k Ω	RRXAJR5Z0562
R1110	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1111	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1112	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1113	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1114	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1115	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1116	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1117	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1118	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1119	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1120	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1121	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1122	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1160	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1161	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1162	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1163	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1164	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1165	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1166	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1167	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1168	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1169	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1170	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1171	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1172	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105

Ref. No.	Description	Part No.
R1210	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1211	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1212	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1213	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1214	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1215	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1216	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1217	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1218	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1219	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1220	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1221	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1222	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1500	CHIP RES. 1/10W J 12k Ω	RRXAJR5Z0123
R1501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R1502	RES CARBON FILM T 1/4W J 150 Ω	RCX4151T1001
R1503	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1504	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1505	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1506	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1550	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1551	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R1552	RES CARBON FILM T 1/4W J 150 Ω	RCX4151T1001
R1553	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1554	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1555	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1556	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1600	CHIP RES. 1/10W J 18k Ω	RRXAJR5Z0183
R1601	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1620	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1621	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1630	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1631	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R1700	CHIP RES. 1/10W J 8.2k Ω	RRXAJR5Z0822
R1701	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1800	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1801	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1802	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1803	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R1804	RES CARBON FILM T 1/4W J 1.2 Ω	RCX41R2T1001
R1805	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R1806	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1807	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1808	CHIP RES. 1/10W J 5.1k Ω	RRXAJR5Z0512
R1809	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R1810	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R1811	RES CARBON FILM T 1/4W J 100k Ω	RCX4104T1001
R1812	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1930	RES CARBON FILM T 1/4W J 47 Ω	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 82 Ω	RCX4820T1001
R1933	RES CARBON FILM T 1/4W J 82 Ω	RCX4820T1001
R1934	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R1935	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R1936	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.33 Ω	RN02R33ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1940	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1941	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 180k Ω	RCX4184T1001
R1943	RES CARBON FILM T 1/4W J 820k Ω	RCX4824T1001
R1944	RES CARBON FILM T 1/4W J 820k Ω	RCX4824T1001
R1945	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001

Ref. No.	Description	Part No.
R1946	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1947	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1948	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1967	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1968	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1969	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1970	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R1971	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1972	CHIP RES. 1/10W J 68k Ω	RRXAJR5Z0683
R1973	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1975	CHIP RES. 1/10W F 30k Ω	RRXAFR5H3002
R1976	CHIP RES. 1/10W F 30k Ω	RRXAFR5H3002
R1977	CHIP RES. 1/10W F 27k Ω	RRXAFR5H2702
R1979	CHIP RES. 1/10W F 6.8k Ω	RRXAFR5H6801
R1980	CHIP RES. 1/10W F 360 Ω	RRXAFR5H3600
R1981	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1982	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R1983	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1984	RES CARBON FILM T 1/4W J 15k Ω	RCX4153T1001
R1986	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1988	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
<b>MISCELLANEOUS</b>		
B13	HEAT SINK PNA A94F0UH	1EM428121
B14	HEAT SINK PNB ASSEMBLY A94F0UH	1EM428123
BC1301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC1500	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1501	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1550	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1551	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1050▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1100▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1150▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1200▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1950▲	TRANS POWER BCK-28-9919	LTT2PC0XB051

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C108	CAP CERAMIC (AX) 0.1μF/50V/F/Z	CA1J104TU062
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k Ω	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k Ω	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k Ω	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k Ω	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k Ω	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k Ω	RCX4183T1002
<b>SWITCHES</b>		
SW101A	TACT SWITCH SKHHLMA010	SST0101AL049
SW103A	TACT SWITCH SKHHLMA010	SST0101AL049
SW104A	TACT SWITCH SKHHLMA010	SST0101AL049
SW105A	TACT SWITCH SKHHLMA010	SST0101AL049
SW106A	TACT SWITCH SKHHLMA010	SST0101AL049
SW107A	TACT SWITCH SKHHLMA010	SST0101AL049

## IR SENSOR CBA


Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C113	ELECTROLYTIC CAP. 47 $\mu$ F/16V M H7	CE1CMAVSL470
C115	CHIP CERAMIC CAP. CH J 330pF/50V	CHD1JJ3CH331
<b>DIODES</b>		
D104	LED GREEN 333GT/E(FNA)	NPWZ33GTEFNA
D105	LED L-53HT	NP4Z000L53HT
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R126	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		
CL101	WIRE ASSEMBLY 8P 8PIN/170MM	WX1A94F0-001
CL103	WIRE ASSEMBLY 4P 4PIN/250MM	WX1A94F0-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJRSKK044

## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002

# ELECTRICAL PARTS LIST

## [ 32MF339B/F7 (Serial No. : DS1A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

### NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91F0MMA-002

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91F0MPWS001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C202	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C203	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C204	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C207	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C210	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C216	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C217	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C218	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C219	ELECTROLYTIC CAP. 47μF/25V M	CE1EMASDL470
C221	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 470μF/25V M	CE1EMASDL471
C223	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C224	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C302	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 330μF/10V M	CE1AMASDL331
C305	CHIP CERAMIC CAP.(1608) F Z 0.1μF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470

Ref. No.	Description	Part No.
C501	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C601▲	CAP METALLIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C602▲	CAP METALLIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C605	CAP ELECTROLYTIC 470μF/200V M	CA2D471DYG07
C609	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.068μF/100V J	CA2A683DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015μF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C632	ELECTROLYTIC CAP. 220μF/25V M	CE1EMASDL221
C633	ELECTROLYTIC CAP. 2200μF/10V M	CE1AMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 220μF/50V M	CE1JMASDL221
C639	ELECTROLYTIC CAP. 1000μF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C644	ELECTROLYTIC CAP 3300μF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTROLYTIC 2200μF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022μF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100μF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C656	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C676	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C734	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C735	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C736	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C743	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102



Ref. No.	Description	Part No.
C809	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C815	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C816	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C829	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C871	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN602	WIRE ASSEMBLY 2PIN 2PIN 145MM RED BLACK	WX1A94F0-201
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D202	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D203	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036

Ref. No.	Description	Part No.
D205	DIODE ZENER 24BSC-T26	NDTC024BST26
D206	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D207	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D208	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D209	DIODE ZENER 39BSB-T26	NDTB039BST26
D210	DIODE ZENER 6V2BSB-T26	NDTB6R2BST26
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D405	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D406	DIODE ZENER 15BSB-T26	NDTB015BST26
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D416	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE 1N5406	NDLZ001N5406
D602▲	DIODE 1N5406	NDLZ001N5406
D603▲	DIODE 1N5406	NDLZ001N5406
D604▲	DIODE 1N5406	NDLZ001N5406
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	DIODE FR154	NDLZ000FR154
D632	DIODE FR104-B	NDLZ000FR104
D633	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D635	DIODE ZENER 24BSB-T26	NDTB024BST26
D637	SCHOTTKY BARRIER DIODE SB160	NDWZ000SB160
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSB-T26	NDTB010BST26
D645	SHUNT REGULATOR KIA431-B-AT/P	NSZBA0TJY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002

Ref. No.	Description	Part No.
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC201	IC TL3472CDR	NSZBA0TTY115
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRM137
IC871	IC OP AMP NJM4558M(Te1)-#ZZZB	QSZBA0TJR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L804	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q201	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q202	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q203	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q204	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q205	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	TRANSISTOR 2SD400(E)	QQUE002SD400
Q210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q401	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q501	TRANSISTOR 2SC2120-Y(Te2 F T)	QOSY2SC2120F
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-Q(Te2 F T)	QOS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (Te2 F T)	QOS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QOWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y(Te2 F T)	QOSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y(Te2 F T)	QOSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y(Te2 F T)	QOSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
<b>RESISTORS</b>		

Ref. No.	Description	Part No.
R171	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R201	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R202	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R204	RES CARBON FILM T 1/4W J 560 Ω	RCX4561T1001
R206	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R207	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R208	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R209	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R210	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R211	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R212	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R213	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R214	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R216	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R217	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R218	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R219	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R220	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R223	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R225	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R226	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 1W J 2.7 Ω	RN012R7ZU001
R228	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R229	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R231	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R232	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R233	CHIP RES. 1/10W F 750 Ω	RRXAFR5H7500
R234	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 330 Ω	RCX4331T1001
R236	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R237	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R238	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R240	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R241	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R242	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R243	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R245	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R247	METAL OXIDE FILM RES. 1W J 2.7 Ω	RN012R7ZU001
R248	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R301	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R302	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R304	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R305	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R311	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R403	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R404	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R405	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R407	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R408	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 43.0 k Ω	RRXAFR5H4302
R411	CHIP RES. 1/10W F 56k Ω	RRXAFR5H5602
R412	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R601▲	RES. CARBON FILM J 1/2W J 560k Ω	RCX2564T1003
R602▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R604	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001

Ref. No.	Description	Part No.
R606	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R611	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 $\Omega$	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R616	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 $\Omega$ H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R636	RES. CARBON FILM J 1/2W J 2.7 $\Omega$	RCX22R7T1003
R637	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R638	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R641	RES CHIP.(1608) 1/10W D 1.1k $\Omega$	RRXADR5H1101
R642	RES CHIP.(1608) 1/10W D 10k $\Omega$	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10k $\Omega$	RRXADR5H1002
R644	CHIP RES. 1/10W F 820 $\Omega$	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0k $\Omega$	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R651	CHIP RES. 1/10W J 1 $\Omega$	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24k $\Omega$	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R658	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R660	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R661	RES. CARBON FILM J 1/2W J 390 $\Omega$	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 15 $\Omega$	RCX4150T1001
R663	RES CARBON FILM T 1/4W J 1.8k $\Omega$	RCX4182T1001
R664	RES CARBON FILM T 1/4W J 1.8k $\Omega$	RCX4182T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0 $\Omega$	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620 $\Omega$	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0k $\Omega$	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	METAL OXIDE FILM RES. 1W J 0.47 $\Omega$	RN01R47ZU001
R673	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R675	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R677	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R678	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R679	CHIP RES. 1/10W F 3.3k $\Omega$	RRXAFR5H3301
R680	CHIP RES. 1/10W F 10k $\Omega$	RRXAFR5H1002
R682	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22 $\Omega$	RCX4220T1001
R686	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R687	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R693	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R694	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R695	RES CARBON FILM T 1/4W J 33 $\Omega$	RCX4330T1001
R696	METAL OXIDE FILM RES. 1W J 3.3 $\Omega$	RN01R33ZU001
R697	METAL OXIDE FILM RES. 1W J 3.3 $\Omega$	RN01R33ZU001
R723	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153

Ref. No.	Description	Part No.
R724	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R763	RES CARBON FILM T 1/4W J 10k $\Omega$	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R801	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R802	CHIP RES. 1/10W F 27k $\Omega$	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11k $\Omega$	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11k $\Omega$	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R807	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R810	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R813	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R820	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R842	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R843	CHIP RES. 1/10W J 110 $\Omega$	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220 $\Omega$	RRXAJR5Z0221
R846	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R847	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560 $\Omega$	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560 $\Omega$	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R875	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R876	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R877	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R879	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100 $\Omega$	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100 $\Omega$	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R887	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R888	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R891	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203

Ref. No.	Description	Part No.
R892	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD W/O A GND WIRE UL/CSA 1770 NO BLACK	WAC0172LW022
B11	POW HEAT SINK A7120UH	1EM423993
B12	MODULE HEAT SINK PMC P7150UT	1EM423968
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS202	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9932	LTT2PC0XB043
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM UC020AF	UTUNNTUSP035

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C757	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
C758	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R762	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03

Ref. No.	Description	Part No.
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91F0M1V-001
	INVERTER CBA	A91F0M1V-001-IV
	FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91F0M1V-001-FNIRJN

## INVERTER CBA

Ref. No.	Description	Part No.
	INVERTER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C1001	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1002	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1003	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1004	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1005	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1006	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1007	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1008	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1009	ELECTROLYTIC CAP. 100 $\mu$ F/25V M	CE1EMASDL101
C1011	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1012	POLYESTER FILM CAP. (PB FREE) 0.0039 $\mu$ F/100V J	CA2A392DT018
C1013	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1014	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C1040	CHIP CERAMIC CAP.(1608) B K 0.47 $\mu$ F/10V	CHD1AK30B474
C1052	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1053	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1056	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1061	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1062	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1063	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1064	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1065	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1066	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1067	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1068	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1072	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1111	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1112	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1113	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1114	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1115	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1116	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1117	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1118	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1122	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1161	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1162	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1163	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1164	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1165	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1166	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1167	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100

Ref. No.	Description	Part No.
C1168	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1172	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1211	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1212	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1213	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1214	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1215	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1216	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1217	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1218	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1222	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1500	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1502	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1550	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1552	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1600	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1620	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C1702	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1703	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1800	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1801	ELECTROLYTIC CAP. 22μF/35V M	CE1GMASDL220
C1802	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 1000pF/2KV	CA3D102PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.027μF/100V J	CA2A273DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1940	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKP0B103
C1970	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C1981	CHIP CERAMIC CAP. F Z 0.01μF/50V	CHD1JZ30F103
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CERAMIC CAP. B K 820pF/1KV	CCD3AKP0B821
C1992▲	ELECTROLYTIC CAP 470μF/100V	CE2AMZNDL471
<b>CONNECTORS</b>		
CN1001	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN1003	FFC CONNECTOR IMSA-9615S-11A-PP-A	JC96J11ER007
CN1050▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1100▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1150▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1200▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1000	DIODE ZENER 15BSB-T26	NDTB015BST26
D1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1003	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1004	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1005	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1006	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1040	DIODE ZENER 36BSB-T26	NDTB036BST26
D1060	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1061	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1062	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1063	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1064	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1065	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1066	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1067	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1068	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1069	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1070	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1071	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1072	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1073	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1074	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1110	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1111	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1112	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1113	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1114	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1115	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1116	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1117	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1118	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1119	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1120	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1121	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1122	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1123	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1124	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1160	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1161	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1162	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1163	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1164	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1165	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1166	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1167	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1168	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1169	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1170	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1171	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1172	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1173	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1174	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1210	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1212	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1213	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1214	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1215	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1216	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1217	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1218	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1219	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1220	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1221	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1222	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1223	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1224	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1500	DIODE ZENER 20BSB-T26	NDTB020BST26
D1550	DIODE ZENER 20BSB-T26	NDTB020BST26
D1630	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1700	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1701	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1702	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1703	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1801	DIODE ZENER 10BSB-T26	NDTB010BST26
D1802	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1933	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1940	DIODE FAST RECOVERY FR155-B/P	NDWZ0FR155BP
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER 30BSB-T26	NDTB030BST26
D1973	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1990	DIODE FAST RECOVERY 31DF4-FC	QDWZ031DF4FC
D1994	DIODE ZENER 1ZB100BB	NDWZ001ZB100
<b>ICS</b>		
IC1000	IC PULSE-WIDTH-MODULATION CONT TL494CDR	NSCA0T0TY006
IC1700	IC BA10324AF-E2	QSZBA0TRM032
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>TRANSISTORS</b>		
Q1001	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1003	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1004	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1005	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1060	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1061	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1110	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1111	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1160	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1161	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1500	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1501	TRANSISTOR 2SC2120-Y (TE2 F T)	QOSY2SC2120F
Q1502	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q1503	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1550	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1551	TRANSISTOR 2SC2120-Y (TE2 F T)	QOSY2SC2120F
Q1552	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q1553	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1600	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1621	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1801	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1803	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1804	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1815	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y (TE2 F T)	QOSY2SC2120F
Q1970	NPN TRANSISTOR KTC3200-GR-AT/P	NQSGKTC3200P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R1001	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1002	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R1003	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1004	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1005	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1006	RES CARBON FILM T 1/4W J 56k Ω	RCX4563T1001
R1007	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1008	CHIP RES. 1/10W J 2.2k Ω	RRXAJR5Z0222
R1009	CHIP RES. 1/10W J 82k Ω	RRXAJR5Z0823
R1010	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1011	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R1012	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R1013	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1014	CHIP RES. 1/10W F 4.7k Ω	RRXAFR5H4701

Ref. No.	Description	Part No.
R1015	CHIP RES. 1/10W F 7.50 k Ω	RRXAFR5H7501
R1016	CHIP RES. 1/10W J 120k Ω	RRXAJR5Z0124
R1017	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1018	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R1019	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R1021	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1022	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R1023	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R1024	CHIP RES. 1/10W F 100k Ω	RRXAFR5H1003
R1026	CHIP RES. 1/10W F 220 Ω	RRXAFR5H2200
R1028	CHIP RES. 1/10W F 36k Ω	RRXAFR5H3602
R1030	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1031	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R1032	RES CARBON FILM T 1/4W J 24k Ω	RCX4243T1001
R1033	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1034	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1035	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R1036	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1040	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1041	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1043	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1044	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1060	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1061	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1062	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1063	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1064	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1065	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1066	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1067	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1068	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1069	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1070	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1071	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1072	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1080	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1081	CHIP RES. 1/10W J 5.6k Ω	RRXAJR5Z0562
R1110	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1111	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1112	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1113	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1114	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1115	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1116	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1117	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1118	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1119	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1120	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1121	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1122	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1160	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1161	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1162	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1163	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1164	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1165	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1166	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1167	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1168	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1169	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1170	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1171	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1172	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105

Ref. No.	Description	Part No.
R1210	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1211	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1212	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1213	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1214	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1215	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1216	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1217	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1218	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1219	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1220	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1221	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1222	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1500	CHIP RES. 1/10W J 12k Ω	RRXAJR5Z0123
R1501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R1502	RES CARBON FILM T 1/4W J 150 Ω	RCX4151T1001
R1503	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1504	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1505	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1506	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1550	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1551	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R1552	RES CARBON FILM T 1/4W J 150 Ω	RCX4151T1001
R1553	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1554	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1555	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1556	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1600	CHIP RES. 1/10W J 18k Ω	RRXAJR5Z0183
R1601	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1620	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1621	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1630	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1631	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R1700	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R1701	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1800	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1801	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1802	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1803	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R1804	RES CARBON FILM T 1/4W J 1.2 Ω	RCX41R2T1001
R1805	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R1806	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1807	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1808	CHIP RES. 1/10W J 5.1k Ω	RRXAJR5Z0512
R1809	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R1810	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R1811	RES CARBON FILM T 1/4W J 100k Ω	RCX4104T1001
R1812	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1930	RES CARBON FILM T 1/4W J 47 Ω	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 82 Ω	RCX4820T1001
R1933	RES CARBON FILM T 1/4W J 82 Ω	RCX4820T1001
R1934	RES CARBON FILM T 1/4W J 82 Ω	RCX4820T1001
R1935	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R1936	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.33 Ω	RN02R33ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1940	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1941	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 180k Ω	RCX4184T1001
R1943	RES CARBON FILM T 1/4W J 820k Ω	RCX4824T1001
R1944	RES CARBON FILM T 1/4W J 820k Ω	RCX4824T1001
R1945	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001

Ref. No.	Description	Part No.
R1946	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1947	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1948	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1967	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1968	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1969	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1970	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R1971	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1972	CHIP RES. 1/10W J 68k Ω	RRXAJR5Z0683
R1973	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1974	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1975	CHIP RES. 1/10W F 30k Ω	RRXAFR5H3002
R1976	CHIP RES. 1/10W F 30k Ω	RRXAFR5H3002
R1977	CHIP RES. 1/10W F 27k Ω	RRXAFR5H2702
R1979	CHIP RES. 1/10W F 6.8k Ω	RRXAFR5H6801
R1980	CHIP RES. 1/10W F 360 Ω	RRXAFR5H3600
R1981	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1982	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R1983	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1984	RES CARBON FILM T 1/4W J 15k Ω	RCX4153T1001
R1986	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1988	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001

#### MISCELLANEOUS

B13	HEAT SINK PNA A94FOUH	1EM428121
B14	HEAT SINK PNB ASSEMBLY A94FOUH	1EM428123
BC1301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC1500	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1501	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1550	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1551	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1050▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1100▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1150▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1200▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1950▲	TRANS POWER BCK-35-0607	LTT3PC0XB048

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C108	CAP CERAMIC (AX) 0.1μF/50V/F/Z	CA1J104TU062
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k Ω	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k Ω	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k Ω	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k Ω	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k Ω	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k Ω	RCX4183T1002
<b>SWITCHES</b>		
SW101A	TACT SWITCH SKHHLMA010	SST0101AL049
SW103A	TACT SWITCH SKHHLMA010	SST0101AL049
SW104A	TACT SWITCH SKHHLMA010	SST0101AL049
SW105A	TACT SWITCH SKHHLMA010	SST0101AL049
SW106A	TACT SWITCH SKHHLMA010	SST0101AL049
SW107A	TACT SWITCH SKHHLMA010	SST0101AL049

## IR SENSOR CBA

Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C113	ELECTROLYTIC CAP. 47 $\mu$ F/16V M H7	CE1CMAVSL470
C115	CHIP CERAMIC CAP. CH J 330pF/50V	CHD1JJ3CH331
<b>DIODES</b>		
D104	LED GREEN 333GT/E(FNA)	NPWZ33GTEFNA
D105	LED L-53HT	NP4Z000L53HT
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R126	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		
CL101	WIRE ASSEMBLY 8P 8PIN/170MM	WX1A94F0-001
CL103	WIRE ASSEMBLY 4P 4PIN/250MM	WX1A94F0-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJRSKK044


## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002



# ELECTRICAL PARTS LIST

## [ 32MF339B/F7 (Serial No. : DS2A\*\*\*\*\*) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

### NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91F6MMA-001

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91F6MPWS001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C202	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C203	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C204	ELECTROLYTIC CAP. 2.2µF/50V M	CE1JMASDL2R2
C207	CHIP CERAMIC CAP.(1608) B K 0.1µF/16V	CHD1CK30B104
C210	ELECTROLYTIC CAP. 22µF/50V M	CE1JMASDL220
C216	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C217	CHIP CERAMIC CAP.(1608) B K 0.1µF/16V	CHD1CK30B104
C218	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C219	ELECTROLYTIC CAP. 47µF/25V M	CE1EMASDL470
C221	CHIP CERAMIC CAP.(1608) B K 0.01µF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 470µF/25V M	CE1EMASDL471
C223	ELECTROLYTIC CAP. 22µF/50V M	CE1JMASDL220
C224	ELECTROLYTIC CAP. 10µF/50V M	CE1JMASDL100
C302	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 1000µF/6.3V M	CE0KMASDL102
C305	CHIP CERAMIC CAP.(1608) F Z 0.1µF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1µF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470

Ref. No.	Description	Part No.
C501	ELECTROLYTIC CAP. 100µF/25V M	CE1EMASDL101
C601▲	CAP METALIZED FILM 0.47µF/300V K 3.5MM	CT2F474DC004
C602▲	CAP METALIZED FILM 0.47µF/300V K 3.5MM	CT2F474DC004
C605	CAP ELECTROLYTIC 470µF/200V M	CA2D471DYG07
C609	POLYESTER FILM CAP. (PB FREE) 0.047µF/100V J	CA2A473DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.068µF/100V J	CA2A683DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015µF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000µF/25V M	CE1EMZNDL102
C632	ELECTROLYTIC CAP. 220µF/25V M	CE1EMASDL221
C633	ELECTROLYTIC CAP. 2200µF/10V M	CE1AMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 220µF/50V M	CE1JMASDL221
C639	ELECTROLYTIC CAP. 1000µF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 0.47µF/50V M	CE1JMASDLR47
C644	ELECTROLYTIC CAP 3300µF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTOLYTIC 2200µF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022µF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1µF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100µF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000µF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220µF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220µF/10V M	CE1AMASDL221
C656	ELECTROLYTIC CAP. 100µF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22µF/50V M	CE1JMASDL220
C676	ELECTROLYTIC CAP. 2.2µF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C734	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C735	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C736	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C743	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100µF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1µF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102

Ref. No.	Description	Part No.
C809	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C815	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C816	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C829	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C871	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN602	WIRE ASSEMBLY 2PIN 2PIN 145MM RED BLACK	WX1A94F0-201
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D202	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D203	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036

Ref. No.	Description	Part No.
D205	DIODE ZENER 30BSB-T26	NDTB030BST26
D206	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D207	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D208	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D209	DIODE ZENER 39BSB-T26	NDTB039BST26
D210	DIODE ZENER 6V2BSB-T26	NDTB6R2BST26
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D405	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D406	DIODE ZENER 27BSA-T26	NDTA027BST26
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D416	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D602▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D603▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D604▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	DIODE FR154	NDLZ000FR154
D632	DIODE FR104-B	NDLZ000FR104
D633	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D635	DIODE ZENER 24BSB-T26	NDTB024BST26
D637	SCHOTTKY BARRIER DIODE SB160	NDWZ000SB160
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSB-T26	NDTB010BST26
D645	SHUNT REGULATOR KIA431B-AT/P	NSZBA0TJY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002

Ref. No.	Description	Part No.
D675	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D676	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC201	IC TL3472CDR	NSZBA0TTY115
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SSS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRM137
IC871	IC OP AMP NJM4558M(Te1)-#ZZZB	QSZBA0JR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG020Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG020Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L804	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q201	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q202	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q203	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q204	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q205	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	TRANSISTOR 2SD400(E)	QQUE002SD400
Q210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q401	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q501	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-O (TE2 F T)	QQS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P

Ref. No.	Description	Part No.
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
<b>RESISTORS</b>		
R171	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R201	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R202	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R204	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R206	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R207	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R208	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R209	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R210	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R211	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R212	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R213	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R214	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R216	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R217	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R218	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R219	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R220	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R223	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R225	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R226	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 2W J 4.7 Ω	RN024R7ZU001
R228	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R229	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R231	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R232	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R233	CHIP RES. 1/10W F 120 Ω	RRXAFR5H1200
R234	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 100 Ω	RCX4101T1001
R236	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R237	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R238	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R240	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R241	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R242	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R243	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R245	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R247	METAL OXIDE FILM RES. 2W J 4.7 Ω	RN024R7ZU001
R248	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R301	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R302	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R304	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R305	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R311	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R403	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R404	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R405	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R407	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R408	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 43.0 k Ω	RRXAFR5H4302
R411	CHIP RES. 1/10W F 56k Ω	RRXAFR5H5602
R412	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R601▲	RES. CARBON FILM J 1/2W J 560k Ω	RCX2564T1003

Ref. No.	Description	Part No.
R602▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R604	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R606	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R611	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R616	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R636	RES. CARBON FILM J 1/2W J 2.7 Ω	RCX22R7T1003
R637	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R638	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R641	RES CHIP.(1608) 1/10W D 1.1k Ω	RRXADR5H1101
R642	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R644	CHIP RES. 1/10W F 820 Ω	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R651	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R658	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R660	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R661	RES. CARBON FILM J 1/2W J 390 Ω	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 15 Ω	RCX4150T1001
R663	RES CARBON FILM T 1/4W J 1.8k Ω	RCX4182T1001
R664	RES CARBON FILM T 1/4W J 1.8k Ω	RCX4182T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0 Ω	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620 Ω	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	METAL OXIDE FILM RES. 1W J 0.47 Ω	RN01R47ZU001
R673	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R675	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R677	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R678	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R679	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R680	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R682	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22 Ω	RCX4220T1001
R686	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R687	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R693	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R694	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R695	RES CARBON FILM T 1/4W J 33 Ω	RCX4330T1001

Ref. No.	Description	Part No.
R696	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001
R697	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001
R723	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R724	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R763	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R801	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R802	CHIP RES. 1/10W F 27k Ω	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R807	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R810	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R813	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R820	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R842	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R843	CHIP RES. 1/10W J 110 Ω	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220 Ω	RRXAJR5Z0221
R846	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R847	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R875	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R876	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R877	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R879	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104

Ref. No.	Description	Part No.
R887	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R888	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R891	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R892	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD W/O A GND WIRE UL/CSA 1770 NO BLACK	WAC0172LW022
B11	POW HEAT SINK A7120UH	1EM423993
B12	MODULE HEAT SINK PMC P7150UT	1EM423968
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS202	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	INDUCTOR 22 $\mu$ H-K-5FT	LLARKBSTU220
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+-10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9932	LTT2PC0XB043
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM UC020AF	UTUNNTUSP035

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C757	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
C758	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393

Ref. No.	Description	Part No.
R762	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91F6M1V-001
	INVERTER CBA	A91F6M1V-001-IV
	FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91F6M1V-001-FNIRJN

## INVERTER CBA

Ref. No.	Description	Part No.
	INVERTER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C115	CHIP CERAMIC CAP. CH J 330pF/50V	CHD1JJ3CH331
C1001	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1002	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1003	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1004	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1005	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1006	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1007	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1008	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1009	ELECTROLYTIC CAP. 100 $\mu$ F/25V M	CE1EMASDL101
C1011	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1012	POLYESTER FILM CAP. (PB FREE) 0.0039 $\mu$ F/100V J	CA2A392DT018
C1013	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1014	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C1040	CHIP CERAMIC CAP.(1608) B K 0.47 $\mu$ F/10V	CHD1AK30B474
C1052	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1053	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1056	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1061	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1062	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1063	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1064	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1065	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1066	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1067	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1068	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1072	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1111	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1112	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1113	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1114	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1115	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1116	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1117	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1118	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1122	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1161	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1162	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1163	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100

Ref. No.	Description	Part No.
C1164	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1165	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1166	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1167	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1168	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1172	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1211	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1212	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1213	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1214	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1215	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1216	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1217	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1218	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1222	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1500	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1502	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1550	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1552	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1600	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1620	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1J33CH102
C1702	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1703	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1800	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1801	ELECTROLYTIC CAP. 22μF/35V M	CE1GMASDL220
C1802	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 820pF/2KV	CA3D821PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.027μF/100V J	CA2A273DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1940	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKN0B103
C1970	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C1981	CHIP CERAMIC CAP. F Z 0.01μF/50V	CHD1JZ30F103
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CAP CERAMIC HV 820pF/1KV B K	CA3A821TE006
C1992▲	ELECTROLYTIC CAP 470μF/100V	CE2AMZNDL471
<b>CONNECTORS</b>		
CN1001	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN1003	FFC CONNECTOR IMSA-9615S-11A-PP-A	JC96J11ER007
CN1050▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1100▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1150▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1200▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1000	DIODE ZENER 15BSB-T26	NDTB015BST26
D1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1003	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1004	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1005	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1006	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1040	DIODE ZENER 36BSB-T26	NDTB036BST26
D1060	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1061	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1062	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1063	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1064	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1065	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1066	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1067	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1068	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1069	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1070	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1071	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1072	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1073	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1074	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1110	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1111	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1112	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1113	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1114	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1115	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1116	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1117	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1118	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1119	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1120	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1121	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1122	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1123	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1124	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1160	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1161	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1162	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1163	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1164	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1165	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1166	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1167	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1168	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1169	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1170	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1171	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1172	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1173	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1174	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1210	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1212	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1213	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1214	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1215	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1216	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1217	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1218	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1219	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1220	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1221	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1222	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1223	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1224	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1500	DIODE ZENER 20BSB-T26	NDTB020BST26
D1550	DIODE ZENER 20BSB-T26	NDTB020BST26
D1630	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1700	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1701	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1702	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1703	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1801	DIODE ZENER 10BSB-T26	NDTB010BST26
D1802	WIRE COPPER 6111-06003-0120	XZ40C0SHG002

Ref. No.	Description	Part No.
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1933	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1940	DIODE FAST RECOVERY FR155-B/P	NDWZ0FR155BP
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER HZS33NB2TE-EQ	QDTBHZS33NB2
D1972	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1973	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1990	DIODE FAST RECOVERY 31DF4-FC	QDWZ031DF4FC
D1994	DIODE ZENER 1ZB100BB	NDWZ001ZB100
<b>ICS</b>		
IC1000	IC PULSE-WIDTH-MODULATION CONT TL494CDR	NSCA0T0TY006
IC1700	IC BA10324AF-E2	QSZBA0TRM032
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>TRANSISTORS</b>		
Q1001	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1003	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1004	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1005	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1060	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1061	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1110	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1111	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1160	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1161	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1500	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1501	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1502	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1503	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1550	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1551	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1552	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1553	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1600	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1621	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1801	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1803	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1804	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1815	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1970	NPN TRANSISTOR KTC3200-GR-AT/P	NQSGKTC3200P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R126	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1001	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1002	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R1003	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1004	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1005	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1006	RES CARBON FILM T 1/4W J 56k Ω	RCX4563T1001
R1007	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1008	CHIP RES. 1/10W J 2.2k Ω	RRXAJR5Z0222

Ref. No.	Description	Part No.
R1009	CHIP RES. 1/10W J 82k Ω	RRXAJR5Z0823
R1010	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1011	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R1012	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R1013	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1014	CHIP RES. 1/10W F 4.7k Ω	RRXAFR5H4701
R1015	CHIP RES. 1/10W F 7.50 k Ω	RRXAFR5H7501
R1016	CHIP RES. 1/10W J 120k Ω	RRXAJR5Z0124
R1017	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1018	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R1019	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R1021	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1022	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R1023	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R1024	CHIP RES. 1/10W F 100k Ω	RRXAFR5H1003
R1026	CHIP RES. 1/10W F 220 Ω	RRXAFR5H2200
R1028	CHIP RES. 1/10W F 36k Ω	RRXAFR5H3602
R1030	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1031	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R1032	RES CARBON FILM T 1/4W J 24k Ω	RCX4243T1001
R1033	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1034	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1035	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R1036	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1040	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1041	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1043	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1044	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1060	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1061	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1062	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1063	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1064	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1065	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1066	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1067	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1068	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1069	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1070	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1071	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1072	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1080	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1081	CHIP RES. 1/10W J 5.6k Ω	RRXAJR5Z0562
R1110	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1111	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1112	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1113	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1114	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1115	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1116	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1117	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1118	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1119	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1120	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1121	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1122	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1160	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1161	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1162	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1163	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1164	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1165	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1166	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104

Ref. No.	Description	Part No.
R1167	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1168	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1169	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1170	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1171	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1172	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1210	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1211	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1212	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1213	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1214	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1215	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1216	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1217	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1218	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1219	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1220	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1221	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1222	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1500	CHIP RES. 1/10W J 12k $\Omega$	RRXAJR5Z0123
R1501	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1502	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1503	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1504	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1505	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1506	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1550	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1551	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1552	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1553	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1554	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1555	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1556	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1600	CHIP RES. 1/10W J 18k $\Omega$	RRXAJR5Z0183
R1601	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1620	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1621	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1630	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1631	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1700	CHIP RES. 1/10W J 8.2k $\Omega$	RRXAJR5Z0822
R1701	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1800	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1801	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1802	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1803	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1804	RES CARBON FILM T 1/4W J 1.2 $\Omega$	RCX41R2T1001
R1805	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R1806	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1807	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1808	CHIP RES. 1/10W J 5.1k $\Omega$	RRXAJR5Z0512
R1809	CHIP RES. 1/10W J 1.5k $\Omega$	RRXAJR5Z0152
R1810	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1811	RES CARBON FILM T 1/4W J 100k $\Omega$	RCX4104T1001
R1812	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1930	RES CARBON FILM T 1/4W J 47 $\Omega$	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k $\Omega$	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1933	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1934	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R1935	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R1936	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.33 $\Omega$	RN02R33ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001

Ref. No.	Description	Part No.
R1940	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1941	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 180k $\Omega$	RCX4184T1001
R1943	RES CARBON FILM 1/4W J 820k $\Omega$	RCX4824FS002
R1944	RES CARBON FILM 1/4W J 820k $\Omega$	RCX4824FS002
R1945	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R1946	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1947	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1948	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1967	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1968	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1969	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1970	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R1971	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1972	CHIP RES. 1/10W J 68k $\Omega$	RRXAJR5Z0683
R1973	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1975	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1976	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1977	CHIP RES. 1/10W F 27k $\Omega$	RRXAFR5H2702
R1979	CHIP RES. 1/10W F 6.8k $\Omega$	RRXAFR5H6801
R1980	CHIP RES. 1/10W F 360 $\Omega$	RRXAFR5H3600
R1981	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R1982	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1983	RES CARBON FILM T 1/4W J 33k $\Omega$	RCX4333T1001
R1984	RES CARBON FILM T 1/4W J 15k $\Omega$	RCX4153T1001
R1986	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1987	RES CARBON FILM 1/4W J 820k $\Omega$	RCX4824FS002
R1988	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
<b>MISCELLANEOUS</b>		
B13	HEAT SINK PNA A94FOUH	1EM428121
B14	HEAT SINK PNB ASSEMBLY A94FOUH	1EM428123
BC1301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC1500	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1501	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1550	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1551	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1050▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1100▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1150▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1200▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1950▲	TRANS POWER BCK-35-0607	LTT3PC0XB048

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C108	CAP CERAMIC (AX) 0.1 $\mu$ F/50V/F/Z	CA1J104TU062
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k $\Omega$	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k $\Omega$	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k $\Omega$	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k $\Omega$	RCX4183T1002
<b>SWITCHES</b>		
SW101A	TACT SWITCH SKH-HLMA010	SST0101AL049
SW103A	TACT SWITCH SKH-HLMA010	SST0101AL049



Ref. No.	Description	Part No.
SW104A	TACT SWITCH SKHHLMA010	SST0101AL049
SW105A	TACT SWITCH SKHHLMA010	SST0101AL049
SW106A	TACT SWITCH SKHHLMA010	SST0101AL049
SW107A	TACT SWITCH SKHHLMA010	SST0101AL049

## IR SENSOR CBA


Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C113	ELECTROLYTIC CAP.47 $\mu$ F/16V M H7	CE1CMAVSL470
<b>DIODES</b>		
D104	LED GREEN 333GT/E(FNA)	NPWZ33GTEFNA
D105	LED L-53HT	NP4Z000L53HT
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		
CL101	WIRE ASSEMBLY 8P 8PIN/170MM	WX1A94F0-001
CL103	WIRE ASSEMBLY 4P 4PIN/250MM	WX1A94F0-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJRSKK044

## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002

# ELECTRICAL PARTS LIST

## [ LC320SSX (Serial No. : DS1A\*\*\*\*\*) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

### NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91F1MMA-002

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91F0MPWS001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C202	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C203	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C204	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C207	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C210	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C216	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C217	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C218	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C219	ELECTROLYTIC CAP. 47μF/25V M	CE1EMASDL470
C221	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 470μF/25V M	CE1EMASDL471
C223	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C224	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C302	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C305	CHIP CERAMIC CAP.(1608) F Z 0.1μF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470

Ref. No.	Description	Part No.
C501	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C601▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C602▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C605	CAP ELECTROLYTIC 470μF/200V M	CA2D471DYG07
C609	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.068μF/100V J	CA2A683DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015μF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C632	ELECTROLYTIC CAP. 220μF/25V M	CE1EMASDL221
C633	ELECTROLYTIC CAP. 2200μF/10V M	CE1AMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 220μF/50V M	CE1JMASDL221
C639	ELECTROLYTIC CAP. 1000μF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C644	ELECTROLYTIC CAP 3300μF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTROLYTIC 2200μF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022μF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100μF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C656	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C676	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C734	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C735	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C736	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C743	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102

Ref. No.	Description	Part No.
C809	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C815	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C816	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C829	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C871	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN602	WIRE ASSEMBLY 2PIN 2PIN 145MM RED BLACK	WX1A94F0-201
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D202	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D203	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036

Ref. No.	Description	Part No.
D205	DIODE ZENER 24BSB-T26	NDTC024BST26
D206	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D207	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D208	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D209	DIODE ZENER 39BSB-T26	NDTB039BST26
D210	DIODE ZENER 6V2BSB-T26	NDTB6R2BST26
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D405	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D406	DIODE ZENER 15BSB-T26	NDTB015BST26
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D416	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE 1N5406	NDLZ001N5406
D602▲	DIODE 1N5406	NDLZ001N5406
D603▲	DIODE 1N5406	NDLZ001N5406
D604▲	DIODE 1N5406	NDLZ001N5406
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	DIODE FR154	NDLZ000FR154
D632	DIODE FR104-B	NDLZ000FR104
D633	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D635	DIODE ZENER 24BSB-T26	NDTB024BST26
D637	SCHOTTKY BARRIER DIODE SB160	NDWZ000SB160
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSB-T26	NDTB010BST26
D645	SHUNT REGULATOR KIA431-B-AT/P	NSZBA0TJY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002

Ref. No.	Description	Part No.
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC201	IC TL3472CDR	NSZBA0TTY115
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SSS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRM137
IC871	IC OP AMP NJM4558M(TE1)-#ZZZB	QSZBA0TJR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L804	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q201	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q202	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q203	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q204	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q205	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	TRANSISTOR 2SD400(E)	QQUE002SD400
Q210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q401	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q501	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-Q(TE2 F T)	QOS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
<b>RESISTORS</b>		

Ref. No.	Description	Part No.
R171	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R201	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R202	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R204	RES CARBON FILM T 1/4W J 560 Ω	RCX4561T1001
R206	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R207	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R208	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R209	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R210	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R211	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R212	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R213	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R214	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R216	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R217	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R218	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R219	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R220	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R223	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R225	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R226	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 1W J 2.7 Ω	RN012R7ZU001
R228	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R229	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R231	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R232	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R233	CHIP RES. 1/10W F 750 Ω	RRXAFR5H7500
R234	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 330 Ω	RCX4331T1001
R236	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R237	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R238	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R240	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R241	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R242	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R243	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R245	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R247	METAL OXIDE FILM RES. 1W J 2.7 Ω	RN012R7ZU001
R248	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R301	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R302	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R304	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R305	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R311	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R403	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R404	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R405	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R407	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R408	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 43.0 k Ω	RRXAFR5H4302
R411	CHIP RES. 1/10W F 56k Ω	RRXAFR5H5602
R412	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R601▲	RES. CARBON FILM J 1/2W J 560k Ω	RCX2564T1003
R602▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R604	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001

Ref. No.	Description	Part No.
R606	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R611	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 $\Omega$	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R616	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 $\Omega$ H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R636	RES. CARBON FILM J 1/2W J 2.7 $\Omega$	RCX22R7T1003
R637	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R638	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R641	RES CHIP.(1608) 1/10W D 1.1k $\Omega$	RRXADR5H1101
R642	RES CHIP.(1608) 1/10W D 10k $\Omega$	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10k $\Omega$	RRXADR5H1002
R644	CHIP RES. 1/10W F 820 $\Omega$	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0k $\Omega$	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R651	CHIP RES. 1/10W J 1 $\Omega$	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24k $\Omega$	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R658	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R660	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R661	RES. CARBON FILM J 1/2W J 390 $\Omega$	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 15 $\Omega$	RCX4150T1001
R663	RES CARBON FILM T 1/4W J 1.8k $\Omega$	RCX4182T1001
R664	RES CARBON FILM T 1/4W J 1.8k $\Omega$	RCX4182T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0 $\Omega$	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620 $\Omega$	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0k $\Omega$	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	METAL OXIDE FILM RES. 1W J 0.47 $\Omega$	RN01R47ZU001
R673	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R675	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R677	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R678	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R679	CHIP RES. 1/10W F 3.3k $\Omega$	RRXAFR5H3301
R680	CHIP RES. 1/10W F 10k $\Omega$	RRXAFR5H1002
R682	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22 $\Omega$	RCX4220T1001
R686	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R687	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R693	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R694	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R695	RES CARBON FILM T 1/4W J 33 $\Omega$	RCX4330T1001
R696	METAL OXIDE FILM RES. 1W J 3.3 $\Omega$	RN01R33ZU001
R697	METAL OXIDE FILM RES. 1W J 3.3 $\Omega$	RN01R33ZU001
R723	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153

Ref. No.	Description	Part No.
R724	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R763	RES CARBON FILM T 1/4W J 10k $\Omega$	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R801	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R802	CHIP RES. 1/10W F 27k $\Omega$	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11k $\Omega$	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11k $\Omega$	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R807	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R810	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R813	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R820	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R842	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R843	CHIP RES. 1/10W J 110 $\Omega$	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220 $\Omega$	RRXAJR5Z0221
R846	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R847	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560 $\Omega$	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560 $\Omega$	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R875	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R876	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R877	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R879	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100 $\Omega$	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100 $\Omega$	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R887	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R888	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R891	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203

Ref. No.	Description	Part No.
R892	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD W/O A GND WIRE UL/CSA 1770 NO BLACK	WAC0172LW022
B11	POW HEAT SINK A7120UH	1EM423993
B12	MODULE HEAT SINK PMC P7150UT	1EM423968
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS202	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	INDUCTOR 22 $\mu$ H-K-5FT	LLARKBSTU220
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9932	LTT2PC0XB043
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM UC020AF	UTUNNTUSP035

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C757	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
C758	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R762	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03

Ref. No.	Description	Part No.
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91F0M1V-001
	INVERTER CBA	A91F0M1V-001-IV
	FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91F0M1V-001-FNIRJN

## INVERTER CBA

Ref. No.	Description	Part No.
	INVERTER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C1001	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1002	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1003	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1004	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1005	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1006	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1007	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1008	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1009	ELECTROLYTIC CAP. 100 $\mu$ F/25V M	CE1EMASDL101
C1011	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1012	POLYESTER FILM CAP. (PB FREE) 0.0039 $\mu$ F/100V J	CA2A392DT018
C1013	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1014	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C1040	CHIP CERAMIC CAP.(1608) B K 0.47 $\mu$ F/10V	CHD1AK30B474
C1052	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1053	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1056	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1061	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1062	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1063	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1064	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1065	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1066	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1067	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1068	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1072	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1111	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1112	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1113	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1114	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1115	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1116	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1117	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1118	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1122	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1161	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1162	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1163	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1164	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1165	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1166	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1167	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100

Ref. No.	Description	Part No.
C1168	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1172	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1211	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1212	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1213	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1214	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1215	CAP CERAMIC HV 15pF/6KV/SL/J	CCA1500TE009
C1216	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1217	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1218	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1222	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1500	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1502	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1550	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1552	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1600	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1620	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C1702	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1703	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1800	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1801	ELECTROLYTIC CAP. 22μF/35V M	CE1GMASDL220
C1802	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 1000pF/2KV	CA3D102PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.027μF/100V J	CA2A273DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1940	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKP0B103
C1970	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C1981	CHIP CERAMIC CAP. F Z 0.01μF/50V	CHD1JZ30F103
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CERAMIC CAP. B K 820pF/1KV	CCD3AKP0B821
C1992▲	ELECTROLYTIC CAP 470μF/100V	CE2AMZNDL471
<b>CONNECTORS</b>		
CN1001	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN1003	FFC CONNECTOR IMSA-9615S-11A-PP-A	JC96J11ER007
CN1050▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1100▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1150▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1200▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1000	DIODE ZENER 15BSB-T26	NDTB015BST26
D1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1003	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1004	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1005	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1006	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1040	DIODE ZENER 36BSB-T26	NDTB036BST26
D1060	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1061	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1062	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1063	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1064	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1065	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1066	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1067	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1068	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1069	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1070	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1071	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1072	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1073	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1074	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1110	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1111	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1112	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1113	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1114	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1115	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1116	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1117	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1118	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1119	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1120	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1121	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1122	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1123	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1124	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1160	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1161	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1162	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1163	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1164	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1165	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1166	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1167	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1168	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1169	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1170	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1171	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1172	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1173	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1174	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1210	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1212	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1213	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1214	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1215	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1216	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1217	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1218	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1219	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1220	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1221	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1222	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1223	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1224	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1500	DIODE ZENER 20BSB-T26	NDTB020BST26
D1550	DIODE ZENER 20BSB-T26	NDTB020BST26
D1630	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1700	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1701	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1702	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1703	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1801	DIODE ZENER 10BSB-T26	NDTB010BST26
D1802	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1933	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1940	DIODE FAST RECOVERY FR155-B/P	NDWZ0FR155BP
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER 30BSB-T26	NDTB030BST26
D1973	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1990	DIODE FAST RECOVERY 31DF4-FC	QDWZ031DF4FC
D1994	DIODE ZENER 1ZB100BB	NDWZ001ZB100
<b>ICS</b>		
IC1000	IC PULSE-WIDTH-MODULATION CONT TL494CDR	NSCA0T0TY006
IC1700	IC BA10324AF-E2	QSZBA0TRM032
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>TRANSISTORS</b>		
Q1001	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1003	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1004	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1005	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1060	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1061	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1110	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1111	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1160	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1161	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1500	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1501	TRANSISTOR 2SC2120-Y (TE2 F T)	QOSY2SC2120F
Q1502	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q1503	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1550	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1551	TRANSISTOR 2SC2120-Y (TE2 F T)	QOSY2SC2120F
Q1552	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q1553	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1600	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1621	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1801	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1803	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1804	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1815	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y (TE2 F T)	QOSY2SC2120F
Q1970	NPN TRANSISTOR KTC3200-GR-AT/P	NQSGKTC3200P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R1001	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1002	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R1003	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1004	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1005	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1006	RES CARBON FILM T 1/4W J 56k Ω	RCX4563T1001
R1007	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1008	CHIP RES. 1/10W J 2.2k Ω	RRXAJR5Z0222
R1009	CHIP RES. 1/10W J 82k Ω	RRXAJR5Z0823
R1010	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1011	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R1012	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R1013	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1014	CHIP RES. 1/10W F 4.7k Ω	RRXAFR5H4701

Ref. No.	Description	Part No.
R1015	CHIP RES. 1/10W F 7.50 k Ω	RRXAFR5H7501
R1016	CHIP RES. 1/10W J 120k Ω	RRXAJR5Z0124
R1017	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1018	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R1019	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R1021	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1022	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R1023	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R1024	CHIP RES. 1/10W F 100k Ω	RRXAFR5H1003
R1026	CHIP RES. 1/10W F 220 Ω	RRXAFR5H2200
R1028	CHIP RES. 1/10W F 36k Ω	RRXAFR5H3602
R1030	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1031	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R1032	RES CARBON FILM T 1/4W J 24k Ω	RCX4243T1001
R1033	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1034	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1035	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R1036	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1040	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1041	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1043	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1044	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1060	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1061	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1062	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1063	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1064	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1065	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1066	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1067	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1068	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1069	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1070	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1071	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1072	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1080	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1081	CHIP RES. 1/10W J 5.6k Ω	RRXAJR5Z0562
R1110	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1111	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1112	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1113	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1114	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1115	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1116	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1117	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1118	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1119	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1120	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1121	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1122	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1160	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1161	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1162	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1163	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1164	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1165	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1166	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1167	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1168	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1169	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1170	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1171	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1172	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105



Ref. No.	Description	Part No.
R1210	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1211	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1212	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1213	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1214	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1215	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1216	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1217	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1218	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1219	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1220	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1221	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1222	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1500	CHIP RES. 1/10W J 12k Ω	RRXAJR5Z0123
R1501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R1502	RES CARBON FILM T 1/4W J 150 Ω	RCX4151T1001
R1503	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1504	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1505	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1506	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1550	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1551	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R1552	RES CARBON FILM T 1/4W J 150 Ω	RCX4151T1001
R1553	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1554	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1555	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1556	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1600	CHIP RES. 1/10W J 18k Ω	RRXAJR5Z0183
R1601	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1620	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1621	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1630	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1631	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R1700	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R1701	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1800	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1801	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1802	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1803	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R1804	RES CARBON FILM T 1/4W J 1.2 Ω	RCX41R2T1001
R1805	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R1806	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1807	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1808	CHIP RES. 1/10W J 5.1k Ω	RRXAJR5Z0512
R1809	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R1810	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R1811	RES CARBON FILM T 1/4W J 100k Ω	RCX4104T1001
R1812	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1930	RES CARBON FILM T 1/4W J 47 Ω	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 82 Ω	RCX4820T1001
R1933	RES CARBON FILM T 1/4W J 82 Ω	RCX4820T1001
R1934	RES CARBON FILM T 1/4W J 82 Ω	RCX4820T1001
R1935	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R1936	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.33 Ω	RN02R33ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1940	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1941	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 180k Ω	RCX4184T1001
R1943	RES CARBON FILM T 1/4W J 820k Ω	RCX4824T1001
R1944	RES CARBON FILM T 1/4W J 820k Ω	RCX4824T1001
R1945	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001

Ref. No.	Description	Part No.
R1946	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1947	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1948	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1967	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1968	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1969	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1970	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R1971	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1972	CHIP RES. 1/10W J 68k Ω	RRXAJR5Z0683
R1973	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1974	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1975	CHIP RES. 1/10W F 30k Ω	RRXAFR5H3002
R1976	CHIP RES. 1/10W F 30k Ω	RRXAFR5H3002
R1977	CHIP RES. 1/10W F 27k Ω	RRXAFR5H2702
R1979	CHIP RES. 1/10W F 6.8k Ω	RRXAFR5H6801
R1980	CHIP RES. 1/10W F 360 Ω	RRXAFR5H3600
R1981	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1982	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R1983	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1984	RES CARBON FILM T 1/4W J 15k Ω	RCX4153T1001
R1986	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1988	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001

#### MISCELLANEOUS

B13	HEAT SINK PNA A94FOUH	1EM428121
B14	HEAT SINK PNB ASSEMBLY A94FOUH	1EM428123
BC1301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC1500	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1501	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1550	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1551	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1050▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1100▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1150▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1200▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1950▲	TRANS POWER BCK-35-0607	LTT3PC0XB048

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C108	CAP CERAMIC (AX) 0.1μF/50V/F/Z	CA1J104TU062
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k Ω	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k Ω	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k Ω	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k Ω	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k Ω	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k Ω	RCX4183T1002
<b>SWITCHES</b>		
SW101A	TACT SWITCH SKHHLMA010	SST0101AL049
SW103A	TACT SWITCH SKHHLMA010	SST0101AL049
SW104A	TACT SWITCH SKHHLMA010	SST0101AL049
SW105A	TACT SWITCH SKHHLMA010	SST0101AL049
SW106A	TACT SWITCH SKHHLMA010	SST0101AL049
SW107A	TACT SWITCH SKHHLMA010	SST0101AL049

## IR SENSOR CBA


Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C113	ELECTROLYTIC CAP. 47 $\mu$ F/16V M H7	CE1CMAVSL470
C115	CHIP CERAMIC CAP. CH J 330pF/50V	CHD1JJ3CH331
<b>DIODES</b>		
D104	LED GREEN 333GT/E(FNA)	NPWZ33GTEFNA
D105	LED L-53HT	NP4Z000L53HT
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R126	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		
CL101	WIRE ASSEMBLY 8P 8PIN/170MM	WX1A94F0-001
CL103	WIRE ASSEMBLY 4P 4PIN/250MM	WX1A94F0-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJRSKK044

## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002

# ELECTRICAL PARTS LIST

## [ LC320EMX (Serial No. : DS1A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

### NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91F4MMA-001

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91F0MPW-001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C202	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C203	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C204	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C207	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C210	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C216	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C217	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C218	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C219	ELECTROLYTIC CAP. 47μF/25V M	CE1EMASDL470
C221	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 470μF/25V M	CE1EMASDL471
C223	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C224	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C302	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C305	CHIP CERAMIC CAP.(1608) F Z 0.1μF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470

Ref. No.	Description	Part No.
C501	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C601▲	CAP METALLIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C602▲	CAP METALLIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C605	CAP ELECTROLYTIC 470μF/200V M	CA2D471DYG07
C609	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.068μF/100V J	CA2A683DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015μF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C632	ELECTROLYTIC CAP. 220μF/25V M	CE1EMASDL221
C633	ELECTROLYTIC CAP. 2200μF/10V M	CE1AMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 220μF/50V M	CE1JMASDL221
C639	ELECTROLYTIC CAP. 1000μF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C644	ELECTROLYTIC CAP 3300μF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTROLYTIC 2200μF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022μF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100μF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C656	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C676	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C734	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C735	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C736	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C743	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102

Ref. No.	Description	Part No.
C809	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C815	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C816	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C829	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C871	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN602	WIRE ASSEMBLY 2PIN 2PIN 145MM RED BLACK	WX1A94F0-201
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D202	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D203	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036

Ref. No.	Description	Part No.
D205	DIODE ZENER 24BSC-T26	NDTC024BST26
D206	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D207	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D208	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D209	DIODE ZENER 39BSB-T26	NDTB039BST26
D210	DIODE ZENER 6V2BSB-T26	NDTB6R2BST26
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D405	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D406	DIODE ZENER 15BSB-T26	NDTB015BST26
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D416	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D602▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D603▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D604▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	DIODE FR154	NDLZ000FR154
D632	DIODE FR104-B	NDLZ000FR104
D633	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D635	DIODE ZENER 24BSB-T26	NDTB024BST26
D637	SCHOTTKY BARRIER DIODE SB160	NDWZ000SB160
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSB-T26	NDTB010BST26
D645	SHUNT REGULATOR KIA431B-AT/P	NSZBA0TJY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002

Ref. No.	Description	Part No.
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC201	IC TL3472CDR	NSZBA0TTY115
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SSS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRM137
IC871	IC OP AMP NJM4558M(TE1)-#ZZZB	QSZBA0TJR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L804	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q201	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q202	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q203	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q204	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q205	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	TRANSISTOR 2SD400(E)	QQUE002SD400
Q210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q401	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q501	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-Q(TE2 F T)	QOS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
<b>RESISTORS</b>		

Ref. No.	Description	Part No.
R171	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R201	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R202	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R204	RES CARBON FILM T 1/4W J 560 Ω	RCX4561T1001
R206	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R207	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R208	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R209	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R210	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R211	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R212	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R213	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R214	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R216	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R217	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R218	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R219	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R220	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R223	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R225	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R226	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 1W J 2.7 Ω	RN012R7ZU001
R228	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R229	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R231	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R232	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R233	CHIP RES. 1/10W F 750 Ω	RRXAFR5H7500
R234	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 330 Ω	RCX4331T1001
R236	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R237	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R238	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R240	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R241	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R242	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R243	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R245	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R247	METAL OXIDE FILM RES. 1W J 2.7 Ω	RN012R7ZU001
R248	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R301	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R302	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R304	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R305	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R311	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R403	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R404	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R405	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R407	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R408	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 43.0 k Ω	RRXAFR5H4302
R411	CHIP RES. 1/10W F 56k Ω	RRXAFR5H5602
R412	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R601▲	RES. CARBON FILM J 1/2W J 560k Ω	RCX2564T1003
R602▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R604	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001

Ref. No.	Description	Part No.
R606	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R611	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 $\Omega$	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R616	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 $\Omega$ H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R636	RES. CARBON FILM J 1/2W J 2.7 $\Omega$	RCX22R7T1003
R637	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R638	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R641	RES CHIP.(1608) 1/10W D 1.1k $\Omega$	RRXADR5H1101
R642	RES CHIP.(1608) 1/10W D 10k $\Omega$	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10k $\Omega$	RRXADR5H1002
R644	CHIP RES. 1/10W F 820 $\Omega$	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0k $\Omega$	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R651	CHIP RES. 1/10W J 1 $\Omega$	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24k $\Omega$	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R658	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R660	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R661	RES. CARBON FILM J 1/2W J 390 $\Omega$	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 15 $\Omega$	RCX4150T1001
R663	RES CARBON FILM T 1/4W J 1.8k $\Omega$	RCX4182T1001
R664	RES CARBON FILM T 1/4W J 1.8k $\Omega$	RCX4182T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0 $\Omega$	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620 $\Omega$	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0k $\Omega$	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	METAL OXIDE FILM RES. 1W J 0.47 $\Omega$	RN01R47ZU001
R673	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R675	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R677	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R678	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R679	CHIP RES. 1/10W F 3.3k $\Omega$	RRXAFR5H3301
R680	CHIP RES. 1/10W F 10k $\Omega$	RRXAFR5H1002
R682	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22 $\Omega$	RCX4220T1001
R686	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R687	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R693	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R694	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R695	RES CARBON FILM T 1/4W J 33 $\Omega$	RCX4330T1001
R696	METAL OXIDE FILM RES. 1W J 3.3 $\Omega$	RN01R33ZU001
R697	METAL OXIDE FILM RES. 1W J 3.3 $\Omega$	RN01R33ZU001
R723	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153

Ref. No.	Description	Part No.
R724	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R763	RES CARBON FILM T 1/4W J 10k $\Omega$	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R801	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R802	CHIP RES. 1/10W F 27k $\Omega$	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11k $\Omega$	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11k $\Omega$	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R807	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R810	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R813	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R820	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R842	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R843	CHIP RES. 1/10W J 110 $\Omega$	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220 $\Omega$	RRXAJR5Z0221
R846	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R847	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560 $\Omega$	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560 $\Omega$	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R875	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R876	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R877	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R879	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100 $\Omega$	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100 $\Omega$	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R887	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R888	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R891	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203

Ref. No.	Description	Part No.
R892	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD W/O A GND WIRE UL/CSA 1770 NO BLACK	WAC0172LW022
B11	POW HEAT SINK A7120UH	1EM423993
B12	MODULE HEAT SINK PMC P7150UT	1EM423968
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS202	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	INDUCTOR 22UH-K-5FT	LLARKBSTU220
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9932	LTT2PC0XB043
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM UC020AF	UTUNNTUSP035

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C757	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
C758	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R762	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03

Ref. No.	Description	Part No.
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91F4M1V-001
	INVERTER CBA	A91F4M1V-001-IV
	FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91F4M1V-001-FNIRJN

## INVERTER CBA

Ref. No.	Description	Part No.
	INVERTER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C1001	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1002	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1003	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1004	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1005	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1006	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1007	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1008	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1009	ELECTROLYTIC CAP. 100 $\mu$ F/25V M	CE1EMASDL101
C1011	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1012	POLYESTER FILM CAP. (PB FREE) 0.0039 $\mu$ F/100V J	CA2A392DT018
C1013	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1014	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C1040	CHIP CERAMIC CAP.(1608) B K 0.47 $\mu$ F/10V	CHD1AK30B474
C1052	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1053	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1056	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1061	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1062	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1063	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1064	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1065	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1066	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1067	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1068	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1072	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1111	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1112	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1113	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1114	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1115	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1116	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1117	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1118	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1122	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1161	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1162	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1163	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1164	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1165	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1166	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1167	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100

Ref. No.	Description	Part No.
C1168	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1172	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1211	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1212	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1213	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1214	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1215	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1216	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1217	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1218	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1222	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1500	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1502	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1550	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1552	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1600	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1620	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C1702	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1703	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1800	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1801	ELECTROLYTIC CAP. 22μF/35V M	CE1GMASDL220
C1802	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 1000pF/2KV	CA3D102PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.027μF/100V J	CA2A273DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1940	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKP0B103
C1970	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C1981	CHIP CERAMIC CAP. F Z 0.01μF/50V	CHD1JZ30F103
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CERAMIC CAP. B K 820pF/1KV	CCD3AKP0B821
C1992▲	ELECTROLYTIC CAP 470μF/100V	CE2AMZNDL471
<b>CONNECTORS</b>		
CN1001	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN1003	FFC CONNECTOR IMSA-9615S-11A-PP-A	JC96J11ER007
CN1050▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1100▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1150▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1200▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1000	DIODE ZENER 15BSB-T26	NDTB015BST26
D1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1003	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1004	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1005	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1006	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1040	DIODE ZENER 36BSB-T26	NDTB036BST26
D1060	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1061	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1062	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1063	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1064	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1065	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1066	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1067	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1068	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1069	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1070	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1071	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1072	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1073	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1074	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1110	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1111	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1112	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1113	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1114	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1115	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1116	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1117	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1118	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1119	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1120	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1121	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1122	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1123	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1124	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1160	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1161	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1162	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1163	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1164	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1165	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1166	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1167	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1168	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1169	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1170	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1171	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1172	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1173	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1174	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1210	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1212	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1213	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1214	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1215	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1216	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1217	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1218	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1219	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1220	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1221	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1222	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1223	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1224	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1500	DIODE ZENER 20BSB-T26	NDTB020BST26
D1550	DIODE ZENER 20BSB-T26	NDTB020BST26
D1630	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1700	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1701	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1702	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1703	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1801	DIODE ZENER 10BSB-T26	NDTB010BST26
D1802	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1933	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133



Ref. No.	Description	Part No.
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1940	DIODE FAST RECOVERY FR155-B/P	NDWZ0FR155BP
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER 30BSB-T26	NDTB030BST26
D1973	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1990	DIODE FAST RECOVERY 31DF4-FC	QDWZ031DF4FC
D1994	DIODE ZENER 1ZB100BB	NDWZ001ZB100
<b>ICS</b>		
IC1000	IC PULSE-WIDTH-MODULATION CONT TL494CDR	NSCA0T0TY006
IC1700	IC BA10324AF-E2	QSZBA0TRM032
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>TRANSISTORS</b>		
Q1001	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1003	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1004	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1005	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1060	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1061	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1110	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1111	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1160	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1161	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1500	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1501	TRANSISTOR 2SC2120-Y (TE2 F T)	QOSY2SC2120F
Q1502	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q1503	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1550	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1551	TRANSISTOR 2SC2120-Y (TE2 F T)	QOSY2SC2120F
Q1552	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q1553	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1600	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1621	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1801	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1803	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1804	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1815	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y (TE2 F T)	QOSY2SC2120F
Q1970	NPN TRANSISTOR KTC3200-GR-AT/P	NQSGKTC3200P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R1001	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1002	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R1003	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1004	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1005	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1006	RES CARBON FILM T 1/4W J 56k Ω	RCX4563T1001
R1007	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1008	CHIP RES. 1/10W J 2.2k Ω	RRXAJR5Z0222
R1009	CHIP RES. 1/10W J 82k Ω	RRXAJR5Z0823
R1010	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1011	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R1012	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R1013	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1014	CHIP RES. 1/10W F 4.7k Ω	RRXAFR5H4701

Ref. No.	Description	Part No.
R1015	CHIP RES. 1/10W F 7.50 k Ω	RRXAFR5H7501
R1016	CHIP RES. 1/10W J 120k Ω	RRXAJR5Z0124
R1017	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1018	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R1019	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R1021	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1022	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R1023	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R1024	CHIP RES. 1/10W F 100k Ω	RRXAFR5H1003
R1026	CHIP RES. 1/10W F 220 Ω	RRXAFR5H2200
R1028	CHIP RES. 1/10W F 36k Ω	RRXAFR5H3602
R1030	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1031	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R1032	RES CARBON FILM T 1/4W J 24k Ω	RCX4243T1001
R1033	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1034	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1035	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R1036	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1040	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1041	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1043	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1044	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1060	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1061	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1062	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1063	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1064	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1065	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1066	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1067	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1068	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1069	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1070	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1071	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1072	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1080	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1081	CHIP RES. 1/10W J 5.6k Ω	RRXAJR5Z0562
R1110	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1111	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1112	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1113	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1114	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1115	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1116	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1117	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1118	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1119	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1120	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1121	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1122	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1160	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1161	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1162	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1163	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1164	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1165	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1166	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1167	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1168	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1169	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1170	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1171	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1172	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105

Ref. No.	Description	Part No.
R1210	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1211	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1212	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1213	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1214	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1215	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1216	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1217	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1218	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1219	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1220	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1221	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1222	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1500	CHIP RES. 1/10W J 12k $\Omega$	RRXAJR5Z0123
R1501	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1502	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1503	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1504	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1505	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1506	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1550	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1551	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1552	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1553	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1554	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1555	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1556	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1600	CHIP RES. 1/10W J 18k $\Omega$	RRXAJR5Z0183
R1601	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1620	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1621	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1630	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1631	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1700	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R1701	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1800	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1801	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1802	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1803	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1804	RES CARBON FILM T 1/4W J 1.2 $\Omega$	RCX41R2T1001
R1805	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R1806	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1807	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1808	CHIP RES. 1/10W J 5.1k $\Omega$	RRXAJR5Z0512
R1809	CHIP RES. 1/10W J 1.5k $\Omega$	RRXAJR5Z0152
R1810	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1811	RES CARBON FILM T 1/4W J 100k $\Omega$	RCX4104T1001
R1812	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1930	RES CARBON FILM T 1/4W J 47 $\Omega$	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k $\Omega$	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1933	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1934	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1935	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R1936	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.33 $\Omega$	RN02R33ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1940	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1941	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 180k $\Omega$	RCX4184T1001
R1943	RES CARBON FILM T 1/4W J 820k $\Omega$	RCX4824T1001
R1944	RES CARBON FILM T 1/4W J 820k $\Omega$	RCX4824T1001
R1945	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001

Ref. No.	Description	Part No.
R1946	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1947	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1948	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1967	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1968	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1969	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1970	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R1971	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1972	CHIP RES. 1/10W J 68k $\Omega$	RRXAJR5Z0683
R1973	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1974	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R1975	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1976	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1977	CHIP RES. 1/10W F 27k $\Omega$	RRXAFR5H2702
R1979	CHIP RES. 1/10W F 6.8k $\Omega$	RRXAFR5H6801
R1980	CHIP RES. 1/10W F 360 $\Omega$	RRXAFR5H3600
R1981	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R1982	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1983	RES CARBON FILM T 1/4W J 33k $\Omega$	RCX4333T1001
R1984	RES CARBON FILM T 1/4W J 15k $\Omega$	RCX4153T1001
R1986	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1988	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001

#### MISCELLANEOUS

B13	HEAT SINK PNA A94FOUH	1EM428121
B14	HEAT SINK PNB ASSEMBLY A94FOUH	1EM428123
BC1301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC1500	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1501	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1550	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1551	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1050▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1100▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1150▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1200▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1950▲	TRANS POWER BCK-35-0607	LTT3PC0XB048

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C108	CAP CERAMIC (AX) 0.1 $\mu$ F/50V/F/Z	CA1J104TU062
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k $\Omega$	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k $\Omega$	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k $\Omega$	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k $\Omega$	RCX4183T1002
<b>SWITCHES</b>		
SW101B	TACT SWITCH SKQSAB	SST0101AL038
SW103B	TACT SWITCH SKQSAB	SST0101AL038
SW104B	TACT SWITCH SKQSAB	SST0101AL038
SW105B	TACT SWITCH SKQSAB	SST0101AL038
SW106B	TACT SWITCH SKQSAB	SST0101AL038
SW107B	TACT SWITCH SKQSAB	SST0101AL038

## IR SENSOR CBA


Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C113	ELECTROLYTIC CAP. 47 $\mu$ F/16V M H7	CE1CMAVSL470
C115	CHIP CERAMIC CAP. CH J 330pF/50V	CHD1JJ3CH331
<b>DIODES</b>		
D104	LED GREEN 333GT/E(FNA)	NPWZ33GTEFNA
D105	LED L-53HT	NP4Z000L53HT
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R126	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		
CL101	WIRE ASSEMBLY 8P 8PIN/170MM	WX1A94F0-001
CL103	WIRE ASSEMBLY 4P 4PIN/200MM	WX1A91F4-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJRSKK044

## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002

# ELECTRICAL PARTS LIST

## [ LC320EMX (Serial No. : DS2A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

### NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91F9MMA-001

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91F6MPWS001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C202	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C203	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C204	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C207	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C210	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C216	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C217	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C218	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C219	ELECTROLYTIC CAP. 47μF/25V M	CE1EMASDL470
C221	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 470μF/25V M	CE1EMASDL471
C223	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C224	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C302	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C305	CHIP CERAMIC CAP.(1608) F Z 0.1μF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470

Ref. No.	Description	Part No.
C501	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C601▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C602▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C605	CAP ELECTROLYTIC 470μF/200V M	CA2D471DYG07
C609	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.068μF/100V J	CA2A683DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015μF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C632	ELECTROLYTIC CAP. 220μF/25V M	CE1EMASDL221
C633	ELECTROLYTIC CAP. 2200μF/10V M	CE1AMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 220μF/50V M	CE1JMASDL221
C639	ELECTROLYTIC CAP. 1000μF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C644	ELECTROLYTIC CAP 3300μF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTOLYTIC 2200μF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022μF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100μF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C656	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C676	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C734	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C735	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C736	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C743	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102

Ref. No.	Description	Part No.
C809	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C815	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C816	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C829	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C871	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN602	WIRE ASSEMBLY 2PIN 2PIN 145MM RED BLACK	WX1A94F0-201
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D202	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D203	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036

Ref. No.	Description	Part No.
D205	DIODE ZENER 30BSB-T26	NDTB030BST26
D206	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D207	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D208	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D209	DIODE ZENER 39BSB-T26	NDTB039BST26
D210	DIODE ZENER 6V2BSB-T26	NDTB6R2BST26
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D405	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D406	DIODE ZENER 27BSA-T26	NDTA027BST26
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D416	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D602▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D603▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D604▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	DIODE FR154	NDLZ000FR154
D632	DIODE FR104-B	NDLZ000FR104
D633	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D635	DIODE ZENER 24BSB-T26	NDTB024BST26
D637	SCHOTTKY BARRIER DIODE SB160	NDWZ000SB160
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSB-T26	NDTB010BST26
D645	SHUNT REGULATOR KIA431B-AT/P	NSZBA0TJY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002

Ref. No.	Description	Part No.
D675	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D676	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC201	IC TL3472CDR	NSZBA0TTY115
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SSS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRM137
IC871	IC OP AMP NJM4558M(Te1)-#ZZZB	QSZBA0JR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG020Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG020Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L804	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q201	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q202	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q203	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q204	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q205	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	TRANSISTOR 2SD400(E)	QQUE002SD400
Q210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q401	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q501	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-O (TE2 F T)	QQS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P

Ref. No.	Description	Part No.
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
<b>RESISTORS</b>		
R171	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R201	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R202	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R204	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R206	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R207	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R208	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R209	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R210	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R211	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R212	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R213	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R214	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R216	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R217	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R218	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R219	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R220	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R223	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R225	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R226	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 2W J 4.7 Ω	RN024R7ZU001
R228	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R229	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R231	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R232	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R233	CHIP RES. 1/10W F 120 Ω	RRXAFR5H1200
R234	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 100 Ω	RCX4101T1001
R236	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R237	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R238	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R240	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R241	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R242	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R243	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R245	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R247	METAL OXIDE FILM RES. 2W J 4.7 Ω	RN024R7ZU001
R248	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R301	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R302	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R304	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R305	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R311	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R403	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R404	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R405	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R407	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R408	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 43.0 k Ω	RRXAFR5H4302
R411	CHIP RES. 1/10W F 56k Ω	RRXAFR5H5602
R412	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R601▲	RES. CARBON FILM J 1/2W J 560k Ω	RCX2564T1003

Ref. No.	Description	Part No.
R602▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R604	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R606	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R611	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R616	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R636	RES. CARBON FILM J 1/2W J 2.7 Ω	RCX22R7T1003
R637	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R638	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R641	RES CHIP.(1608) 1/10W D 1.1k Ω	RRXADR5H1101
R642	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R644	CHIP RES. 1/10W F 820 Ω	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R651	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R658	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R660	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R661	RES. CARBON FILM J 1/2W J 390 Ω	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 15 Ω	RCX4150T1001
R663	RES CARBON FILM T 1/4W J 1.8k Ω	RCX4182T1001
R664	RES CARBON FILM T 1/4W J 1.8k Ω	RCX4182T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0 Ω	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620 Ω	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	METAL OXIDE FILM RES. 1W J 0.47 Ω	RN01R47ZU001
R673	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R675	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R677	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R678	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R679	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R680	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R682	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22 Ω	RCX4220T1001
R686	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R687	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R693	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R694	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R695	RES CARBON FILM T 1/4W J 33 Ω	RCX4330T1001

Ref. No.	Description	Part No.
R696	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001
R697	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001
R723	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R724	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R763	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R801	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R802	CHIP RES. 1/10W F 27k Ω	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R807	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R810	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R813	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R820	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R842	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R843	CHIP RES. 1/10W J 110 Ω	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220 Ω	RRXAJR5Z0221
R846	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R847	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R875	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R876	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R877	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R879	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104

Ref. No.	Description	Part No.
R887	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R888	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R891	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R892	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD W/O A GND WIRE UL/CSA 1770 NO BLACK	WAC0172LW022
B11	POW HEAT SINK A7120UH	1EM423993
B12	MODULE HEAT SINK PMC P7150UT	1EM423968
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS202	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	INDUCTOR 22 $\mu$ H-K-5FT	LLARKBSTU220
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+-10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9932	LTT2PC0XB043
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM UC020AF	UTUNNTUSP035

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C757	CHIP CERAMIC CAP(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
C758	CHIP CERAMIC CAP(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393

Ref. No.	Description	Part No.
R762	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91F9M1V-001
	INVERTER CBA	A91F9M1V-001-IV
	FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91F9M1V-001-FNIRJN

## INVERTER CBA

Ref. No.	Description	Part No.
	INVERTER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C1001	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1002	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1003	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1004	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1005	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1006	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1007	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1008	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1009	ELECTROLYTIC CAP. 100 $\mu$ F/25V M	CE1EMASDL101
C1011	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1012	POLYESTER FILM CAP. (PB FREE) 0.0039 $\mu$ F/100V J	CA2A392DT018
C1013	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1014	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C1040	CHIP CERAMIC CAP.(1608) B K 0.47 $\mu$ F/10V	CHD1AK30B474
C1052	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1053	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1056	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1061	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1062	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1063	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1064	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1065	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1066	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1067	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1068	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1072	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1111	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1112	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1113	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1114	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1115	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1116	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1117	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1118	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1122	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1161	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1162	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1163	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1164	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103



Ref. No.	Description	Part No.
C1165	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1166	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1167	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1168	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1172	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1211	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1212	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1213	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1214	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1215	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1216	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1217	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1218	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1222	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1500	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1502	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1550	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1552	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1600	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1620	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C1702	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1703	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1800	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1801	ELECTROLYTIC CAP. 22μF/35V M	CE1GMASDL220
C1802	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 820pF/2KV	CA3D821PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.027μF/100V J	CA2A273DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1940	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKN0B103
C1970	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C1981	CHIP CERAMIC CAP. F Z 0.01μF/50V	CHD1JZ30F103
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CAP CERAMIC HV 820pF/1KV B K	CA3A821TE006
C1992▲	ELECTROLYTIC CAP 470μF/100V	CE2AMZNDL471
<b>CONNECTORS</b>		
CN1001	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN1003	FFC CONNECTOR IMSA-9615S-11A-PP-A	JC96J11ER007
CN1050▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1100▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1150▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1200▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1000	DIODE ZENER 15BSB-T26	NDTB015BST26
D1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1003	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1004	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1005	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1006	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1040	DIODE ZENER 36BSB-T26	NDTB036BST26
D1060	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1061	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1062	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1063	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1064	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1065	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1066	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1067	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1068	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1069	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1070	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1071	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1072	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1073	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1074	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1110	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1111	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1112	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1113	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1114	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1115	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1116	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1117	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1118	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1119	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1120	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1121	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1122	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1123	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1124	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1160	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1161	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1162	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1163	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1164	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1165	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1166	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1167	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1168	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1169	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1170	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1171	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1172	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1173	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1174	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1210	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1212	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1213	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1214	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1215	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1216	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1217	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1218	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1219	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1220	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1221	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1222	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1223	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1224	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1500	DIODE ZENER 20BSB-T26	NDTB020BST26
D1550	DIODE ZENER 20BSB-T26	NDTB020BST26
D1630	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1700	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1701	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1702	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1703	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1801	DIODE ZENER 10BSB-T26	NDTB010BST26
D1802	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26

Ref. No.	Description	Part No.
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDT2001SS133
D1933	SWITCHING DIODE 1SS133(T-77)	QDT2001SS133
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1940	DIODE FAST RECOVERY FR155-B/P	NDWZ0FR155BP
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER 30BSB-T26	NDTB030BST26
D1973	SWITCHING DIODE 1SS133(T-77)	QDT2001SS133
D1990	DIODE FAST RECOVERY 31DF4-FC	QDWZ031DF4FC
D1994	DIODE ZENER 1ZB100BB	NDWZ001ZB100
<b>ICS</b>		
IC1000	IC PULSE-WIDTH-MODULATION CONT TL494CDR	NSCA0T0TY006
IC1700	IC BA10324AF-E2	QSZBA0TRM032
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>TRANSISTORS</b>		
Q1001	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1003	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1004	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1005	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1060	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1061	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1110	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1111	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1160	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1161	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1500	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1501	TRANSISTOR 2SC2120-Y(TE2 F T)	QQSY2SC2120F
Q1502	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1503	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1550	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1551	TRANSISTOR 2SC2120-Y(TE2 F T)	QQSY2SC2120F
Q1552	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1553	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1600	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1621	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1801	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1803	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1804	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1815	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y(TE2 F T)	QQSY2SC2120F
Q1970	NPN TRANSISTOR KTC3200-GR-AT/P	NQSGKTC3200P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R1001	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1002	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R1003	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1004	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1005	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1006	RES CARBON FILM T 1/4W J 56k Ω	RCX4563T1001
R1007	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1008	CHIP RES. 1/10W J 2.2k Ω	RRXAJR5Z0222
R1009	CHIP RES. 1/10W J 82k Ω	RRXAJR5Z0823
R1010	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1011	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002

Ref. No.	Description	Part No.
R1012	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R1013	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1014	CHIP RES. 1/10W F 4.7k Ω	RRXAFR5H4701
R1015	CHIP RES. 1/10W F 7.50 k Ω	RRXAFR5H7501
R1016	CHIP RES. 1/10W J 120k Ω	RRXAJR5Z0124
R1017	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1018	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R1019	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R1021	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1022	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R1023	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R1024	CHIP RES. 1/10W F 100k Ω	RRXAFR5H1003
R1026	CHIP RES. 1/10W F 220 Ω	RRXAFR5H2200
R1028	CHIP RES. 1/10W F 36k Ω	RRXAFR5H3602
R1030	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1031	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R1032	RES CARBON FILM T 1/4W J 24k Ω	RCX4243T1001
R1033	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1034	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1035	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R1036	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1040	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1041	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1043	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1044	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1060	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1061	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1062	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1063	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1064	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1065	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1066	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1067	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1068	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1069	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1070	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1071	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1072	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1080	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1081	CHIP RES. 1/10W J 5.6k Ω	RRXAJR5Z0562
R1110	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1111	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1112	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1113	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1114	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1115	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1116	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1117	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1118	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1119	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1120	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1121	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1122	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1160	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1161	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1162	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1163	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1164	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1165	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1166	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1167	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1168	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1169	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802

Ref. No.	Description	Part No.
R1170	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1171	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1172	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1210	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1211	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1212	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1213	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1214	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1215	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1216	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1217	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1218	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1219	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1220	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1221	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1222	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1500	CHIP RES. 1/10W J 12k $\Omega$	RRXAJR5Z0123
R1501	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1502	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1503	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1504	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1505	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1506	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1550	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1551	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1552	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1553	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1554	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1555	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1556	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1600	CHIP RES. 1/10W J 18k $\Omega$	RRXAJR5Z0183
R1601	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1620	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1621	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1630	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1631	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1700	CHIP RES. 1/10W J 8.2k $\Omega$	RRXAJR5Z0822
R1701	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1800	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1801	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1802	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1803	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1804	RES CARBON FILM T 1/4W J 1.2 $\Omega$	RCX41R2T1001
R1805	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R1806	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1807	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1808	CHIP RES. 1/10W J 5.1k $\Omega$	RRXAJR5Z0512
R1809	CHIP RES. 1/10W J 1.5k $\Omega$	RRXAJR5Z0152
R1810	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1811	RES CARBON FILM T 1/4W J 100k $\Omega$	RCX4104T1001
R1812	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1930	RES CARBON FILM T 1/4W J 47 $\Omega$	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k $\Omega$	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1933	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1934	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R1935	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R1936	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.33 $\Omega$	RN02R33ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1940	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1941	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 180k $\Omega$	RCX4184T1001

Ref. No.	Description	Part No.
R1943	RES CARBON FILM T 1/4W J 820k $\Omega$	RCX4824T1001
R1944	RES CARBON FILM T 1/4W J 820k $\Omega$	RCX4824T1001
R1945	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R1946	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1947	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1948	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1967	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1968	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1969	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1970	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R1971	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1972	CHIP RES. 1/10W J 68k $\Omega$	RRXAJR5Z0683
R1973	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1975	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1976	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1977	CHIP RES. 1/10W F 27k $\Omega$	RRXAFR5H2702
R1979	CHIP RES. 1/10W F 6.8k $\Omega$	RRXAFR5H6801
R1980	CHIP RES. 1/10W F 360 $\Omega$	RRXAFR5H3600
R1981	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R1982	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1983	RES CARBON FILM T 1/4W J 33k $\Omega$	RCX4333T1001
R1984	RES CARBON FILM T 1/4W J 15k $\Omega$	RCX4153T1001
R1986	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1988	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
<b>MISCELLANEOUS</b>		
B13	HEAT SINK PNA A94FOUH	1EM428121
B14	HEAT SINK PNB ASSEMBLY A94FOUH	1EM428123
BC1301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
LB1500	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1501	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1550	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1551	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1050▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1100▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1150▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1200▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1950▲	TRANS POWER BCK-35-0607	LTT3PC0XB048

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C108	CAP CERAMIC (AX) 0.1 $\mu$ F/50V/F/Z	CA1J104TU062
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k $\Omega$	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k $\Omega$	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k $\Omega$	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k $\Omega$	RCX4183T1002
<b>SWITCHES</b>		
SW101B	TACT SWITCH SKQSAB	SST0101AL038
SW103B	TACT SWITCH SKQSAB	SST0101AL038
SW104B	TACT SWITCH SKQSAB	SST0101AL038
SW105B	TACT SWITCH SKQSAB	SST0101AL038
SW106B	TACT SWITCH SKQSAB	SST0101AL038
SW107B	TACT SWITCH SKQSAB	SST0101AL038

## IR SENSOR CBA


Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C113	ELECTROLYTIC CAP. 47 $\mu$ F/16V M H7	CE1CMAVSL470
C115	CHIP CERAMIC CAP. CH J 330pF/50V	CHD1JJ3CH331
<b>DIODES</b>		
D104	LED GREEN 333GT/E(FNA)	NPWZ33GTEFNA
D105	LED L-53HT	NP4Z000L53HT
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R126	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		
CL101	WIRE ASSEMBLY 8P 8PIN/170MM	WX1A94F0-001
CL103	WIRE ASSEMBLY 4P 4PIN/200MM	WX1A91F4-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJRSKK044

## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002

# ELECTRICAL PARTS LIST

## [ LC320EMX (Serial No. : DS3A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

### NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91FBMMA-002

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91FBMPWS001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C202	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C203	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C204	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C218	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C219	ELECTROLYTIC CAP. 47μF/25V M	CE1EMASDL470
C221	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 470μF/25V M	CE1EMASDL471
C223	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C224	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C302	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C305	CHIP CERAMIC CAP.(1608) F Z 0.1μF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C501	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C601▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C602▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C605	CAP ELECTROLYTIC 470μF/200V M	CA2D471DYG07

Ref. No.	Description	Part No.
C609	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.068μF/100V J	CA2A683DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015μF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C632	ELECTROLYTIC CAP. 220μF/25V M	CE1EMASDL221
C633	ELECTROLYTIC CAP. 2200μF/10V M	CE1AMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 220μF/50V M	CE1JMASDL221
C639	ELECTROLYTIC CAP. 1000μF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C644	ELECTROLYTIC CAP 3300μF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTROLYTIC 2200μF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022μF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100μF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C656	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C675	ELECTROLYTIC CAP. 330μF/10V M	CE1AMASDL331
C676	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C734	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C735	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C736	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C743	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C809	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP.(1608) B K 0.47μF/16V	CHD1CK30B474

Ref. No.	Description	Part No.
C815	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C816	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C829	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP.(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP.(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP.(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP.(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP.(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP.(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP.(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C871	CHIP CERAMIC CAP.(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP.(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP.(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP.(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN602	WIRE ASSEMBLY 2PIN 2PIN 145MM RED BLACK	WX1A94F0-201
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D203	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D205	DIODE ZENER 30BSB-T26	NDTD030BST26
D206	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D207	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D208	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D209	DIODE ZENER 39BSB-T26	NDTB039BST26
D210	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D405	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D406	DIODE ZENER 27BSA-T26	NDTA027BST26
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D416	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D602▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D603▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D604▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	DIODE FR154	NDLZ000FR154
D632	DIODE FR104-B	NDLZ000FR104
D633	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D635	DIODE ZENER 24BSB-T26	NDTB024BST26
D637	SCHOTTKY BARRIER DIODE SB160	NDWZ000SB160
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSB-T26	NDTB010BST26
D645	SHUNT REGULATOR KIA431B-AT/P	NSZBA0TJY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D675	DIODE SCHOTTKY SB120BB	NDWZ000SB120
D676	DIODE SCHOTTKY SB120BB	NDWZ000SB120
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26

Ref. No.	Description	Part No.
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SSS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRM137
IC871	IC OP AMP NJM4558M(Te1)-#ZZB	QSZBA0TJR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L804	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q201	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q205	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	TRANSISTOR 2SD400(E)	QQUE002SD400
Q210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q401	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q501	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-O(TE2 F T)	QOS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y(TE2 F T)	QOSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
<b>RESISTORS</b>		
R171	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R201	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R206	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R207	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000

Ref. No.	Description	Part No.
R209	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R216	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R217	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R218	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R219	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R220	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R223	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R225	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R226	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 2W J 5.6 Ω	RN025R6ZU001
R228	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R229	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R231	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R232	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R233	CHIP RES. 1/10W F 120 Ω	RRXAFR5H1200
R234	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 27 Ω	RCX4270T1001
R236	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R237	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R238	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R240	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R241	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R242	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R243	RES CARBON FILM T 1/4W J 33 Ω	RCX4330T1001
R245	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R247	METAL OXIDE FILM RES. 2W J 5.6 Ω	RN025R6ZU001
R248	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R249	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R301	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R302	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R304	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R305	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R311	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R403	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R404	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R405	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R407	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R408	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 43.0 k Ω	RRXAFR5H4302
R411	CHIP RES. 1/10W F 56k Ω	RRXAFR5H5602
R412	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R601▲	RES. CARBON FILM J 1/2W J 560k Ω	RCX2564T1003
R602▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R604	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R606	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R611	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R616	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R636	RES. CARBON FILM J 1/2W J 2.7 Ω	RCX22R7T1003
R637	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R638	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001

Ref. No.	Description	Part No.
R641	RES CHIP.(1608) 1/10W D 1.1k $\Omega$	RRXADR5H1001
R642	RES CHIP.(1608) 1/10W D 10k $\Omega$	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10k $\Omega$	RRXADR5H1002
R644	CHIP RES. 1/10W F 820 $\Omega$	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0k $\Omega$	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R651	CHIP RES. 1/10W J 1 $\Omega$	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24k $\Omega$	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R658	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R660	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R661	RES. CARBON FILM J 1/2W J 390 $\Omega$	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 15 $\Omega$	RCX4150T1001
R663	RES CARBON FILM T 1/4W J 1.8k $\Omega$	RCX4182T1001
R664	RES CARBON FILM T 1/4W J 1.8k $\Omega$	RCX4182T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0 $\Omega$	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620 $\Omega$	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0k $\Omega$	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	METAL OXIDE FILM RES. 1W J 0.47 $\Omega$	RN01R47ZU001
R673	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R675	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R677	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R678	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R679	CHIP RES. 1/10W F 3.3k $\Omega$	RRXAFR5H3301
R680	CHIP RES. 1/10W F 6.8k $\Omega$	RRXAFR5H6801
R682	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22 $\Omega$	RCX4220T1001
R686	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R687	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R693	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R694	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R695	RES CARBON FILM T 1/4W J 33 $\Omega$	RCX4330T1001
R696	METAL OXIDE FILM RES. 1W J 3.3 $\Omega$	RN013R3ZU001
R697	METAL OXIDE FILM RES. 1W J 3.3 $\Omega$	RN013R3ZU001
R723	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R724	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393

Ref. No.	Description	Part No.
R763	RES CARBON FILM T 1/4W J 10k $\Omega$	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R801	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R802	CHIP RES. 1/10W F 27k $\Omega$	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11k $\Omega$	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11k $\Omega$	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R807	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R810	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R813	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R820	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R842	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R843	CHIP RES. 1/10W J 110 $\Omega$	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220 $\Omega$	RRXAJR5Z0221
R846	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R847	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560 $\Omega$	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560 $\Omega$	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R875	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R876	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R877	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R879	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100 $\Omega$	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100 $\Omega$	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R887	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R888	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R891	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R892	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD W/O A GND WIRE UL/CSA 1770 NO BLACK	WAC0172LW022
B11	POW HEAT SINK A7120UH	1EM423993
B12	MODULE HEAT SINK PMC P7150UT	1EM423968
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030



Ref. No.	Description	Part No.
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS201	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	INDUCTOR 22μH-K-5FT	LLARKBSTU220
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+-10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9932	LTT2PC0XB043
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM UC020AF	UTUNNTUSP035

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C757	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C758	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R762	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91FBM1V-001
	INVERTER CBA	A91FBM1V-001-IV
	FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91FBM1V-001-FNIRJN

## INVERTER CBA

Ref. No.	Description	Part No.
	INVERTER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C1001	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1002	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1003	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1004	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1005	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1006	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1007	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1008	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1009	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1011	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1012	POLYESTER FILM CAP. (PB FREE) 0.0039μF/100V J	CA2A392DT018
C1013	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1014	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C1040	CHIP CERAMIC CAP.(1608) B K 0.47μF/10V	CHD1AK30B474
C1050	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKN0B103
C1051	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKN0B103
C1052	ELECTROLYTIC CAP 100μF/100V	CE2AMZNDL101
C1053	ELECTROLYTIC CAP 100μF/100V	CE2AMZNDL101
C1056	ELECTROLYTIC CAP 100μF/100V	CE2AMZNDL101
C1061	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1062	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1063	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1064	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1065	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1066	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1067	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1068	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1072	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1111	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1112	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1113	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1114	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1115	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1116	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1117	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1118	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1122	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1161	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1162	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1163	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1164	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1165	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1166	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1167	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1168	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1172	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1211	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1212	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1213	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1214	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1215	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1216	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1217	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1218	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1222	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1500	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1502	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1550	CERAMIC CAP. 470pF/2KV	CA3D471PAN04

Ref. No.	Description	Part No.
C1552	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1600	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1620	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1J33CH102
C1702	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1703	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1800	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1801	ELECTROLYTIC CAP. 22μF/35V M	CE1GMASDL220
C1802	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 820pF/2KV	CA3D821PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.027μF/100V J	CA2A273DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1940	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKN0B103
C1970	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C1981	CHIP CERAMIC CAP. F Z 0.01μF/50V	CHD1JZ30F103
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CAP CERAMIC HV 820pF/1KV B K	CA3A821TE006
C1992▲	ELECTROLYTIC CAP 470μF/100V	CE2AMZNDL471
<b>CONNECTORS</b>		
CN1001	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN1005	FFC CONNECTOR IMSA-9615S-11A-PP-A	JC96J11ER007
CN1050▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1100▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1150▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1200▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1000	DIODE ZENER 15BSB-T26	NDTB015BST26
D1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1003	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1004	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1005	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1006	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1040	DIODE ZENER 36BSB-T26	NDTB036BST26
D1050	DIODE FR104-B	NDLZ000FR104
D1051	DIODE FR104-B	NDLZ000FR104
D1060	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1061	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1062	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1063	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1064	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1065	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1066	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1067	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1068	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1069	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1070	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1071	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1072	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1073	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1074	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1110	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1111	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1112	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1113	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1114	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1115	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1116	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1117	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1118	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1119	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1120	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1121	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1122	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1123	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1124	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1160	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1161	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1162	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1163	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1164	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1165	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1166	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1167	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1168	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1169	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1170	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1171	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1172	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1173	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1174	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1210	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1212	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1213	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1214	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1215	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1216	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1217	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1218	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1219	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1220	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1221	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1222	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1223	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1224	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1500	DIODE ZENER 20BSB-T26	NDTB020BST26
D1550	DIODE ZENER 20BSB-T26	NDTB020BST26
D1630	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1700	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1701	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1702	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1703	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1801	DIODE ZENER 10BSB-T26	NDTB010BST26
D1802	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1933	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1940	DIODE FAST RECOVERY FR155-B/P	NDWZ0FR155BP
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER 30BSB-T26	NDTB030BST26
D1973	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1990	DIODE FAST RECOVERY 31DF4-FC	QDWZ031DF4FC
D1994	DIODE ZENER 1ZB100BB	NDWZ001ZB100
<b>ICS</b>		
IC1000	IC PULSE-WIDTH-MODULATION CONT TL494CDR	NSCA0T0TY006
IC1700	IC BA10324AF-E2	QSZBA0TRM032
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF

Ref. No.	Description	Part No.
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>TRANSISTORS</b>		
Q1001	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1003	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1004	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1005	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1060	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1061	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1110	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1111	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1160	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1161	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1500	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1501	TRANSISTOR 2SC2120-Y(T2 F T)	QGSY2SC2120F
Q1502	TRANSISTOR 2SA950-O (T2 F T)	QGS002SA950F
Q1503	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1550	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1551	TRANSISTOR 2SC2120-Y(T2 F T)	QGSY2SC2120F
Q1552	TRANSISTOR 2SA950-O (T2 F T)	QGS002SA950F
Q1553	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1600	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1621	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1801	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1803	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1804	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1815	TRANSISTOR 2SA950-O (T2 F T)	QGS002SA950F
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y(T2 F T)	QGSY2SC2120F
Q1970	NPN TRANSISTOR KTC3200-GR-AT/P	NQSGKTC3200P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R1001	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1002	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R1003	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1004	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1005	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1006	RES CARBON FILM T 1/4W J 56k Ω	RCX4563T1001
R1007	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1008	CHIP RES. 1/10W J 2.2k Ω	RRXAJR5Z0222
R1009	CHIP RES. 1/10W J 82k Ω	RRXAJR5Z0823
R1010	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1011	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R1012	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R1013	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1014	CHIP RES. 1/10W F 4.7k Ω	RRXAFR5H4701
R1015	CHIP RES. 1/10W F 7.5k Ω	RRXAFR5H7501
R1016	CHIP RES. 1/10W J 120k Ω	RRXAJR5Z0124
R1017	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1018	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R1019	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R1021	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1022	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R1023	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R1024	CHIP RES. 1/10W F 100k Ω	RRXAFR5H1003
R1026	CHIP RES. 1/10W F 220 Ω	RRXAFR5H2200
R1028	CHIP RES. 1/10W F 36k Ω	RRXAFR5H3602

Ref. No.	Description	Part No.
R1030	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1031	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R1032	RES CARBON FILM T 1/4W J 24k Ω	RCX4243T1001
R1033	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1034	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1035	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R1036	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1040	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1041	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1043	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1044	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1050	METAL OXIDE RES. 1W J 8.2k Ω	RN01822ZU001
R1051	METAL OXIDE RES. 1W J 8.2k Ω	RN01822ZU001
R1060	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1061	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1062	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1063	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1064	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1065	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1066	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1067	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1068	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1069	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1070	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1071	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1072	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1080	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1081	CHIP RES. 1/10W J 5.6k Ω	RRXAJR5Z0562
R1110	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1111	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1112	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1113	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1114	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1115	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1116	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1117	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1118	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1119	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1120	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1121	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1122	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1160	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1161	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1162	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1163	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1164	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1165	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1166	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1167	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1168	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1169	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1170	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1171	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1172	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1210	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1211	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1212	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1213	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1214	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1215	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1216	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1217	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1218	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391

Ref. No.	Description	Part No.
R1219	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1220	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1221	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1222	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1500	CHIP RES. 1/10W J 12k $\Omega$	RRXAJR5Z0123
R1501	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1502	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1503	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1504	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1505	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1506	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1550	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1551	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1552	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1553	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1554	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1555	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1556	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1600	CHIP RES. 1/10W J 18k $\Omega$	RRXAJR5Z0183
R1601	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1620	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1621	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1630	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1631	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1700	CHIP RES. 1/10W J 8.2k $\Omega$	RRXAJR5Z0822
R1701	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1800	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1801	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1802	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1803	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1804	RES CARBON FILM T 1/4W J 1.2 $\Omega$	RCX41R2T1001
R1805	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R1806	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1807	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1808	CHIP RES. 1/10W J 5.1k $\Omega$	RRXAJR5Z0512
R1809	CHIP RES. 1/10W J 1.5k $\Omega$	RRXAJR5Z0152
R1810	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1811	RES CARBON FILM T 1/4W J 100k $\Omega$	RCX4104T1001
R1812	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1930	RES CARBON FILM T 1/4W J 47 $\Omega$	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k $\Omega$	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1933	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1934	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R1935	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R1936	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.33 $\Omega$	RN02R33ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1940	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1941	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 180k $\Omega$	RCX4184T1001
R1943	RES CARBON FILM T 1/4W J 820k $\Omega$	RCX4824T1001
R1944	RES CARBON FILM T 1/4W J 820k $\Omega$	RCX4824T1001
R1945	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R1946	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1947	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1948	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1967	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1968	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1969	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1970	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R1971	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1972	CHIP RES. 1/10W J 68k $\Omega$	RRXAJR5Z0683

Ref. No.	Description	Part No.
R1973	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1975	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1976	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1977	CHIP RES. 1/10W F 27k $\Omega$	RRXAFR5H2702
R1979	CHIP RES. 1/10W F 6.8k $\Omega$	RRXAFR5H6801
R1980	CHIP RES. 1/10W F 360 $\Omega$	RRXAFR5H3600
R1981	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R1982	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1983	RES CARBON FILM T 1/4W J 33k $\Omega$	RCX4333T1001
R1984	RES CARBON FILM T 1/4W J 15k $\Omega$	RCX4153T1001
R1986	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1988	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
<b>MISCELLANEOUS</b>		
B13	HEAT SINK PNA A94FOUH	1EM428121
B14	HEAT SINK PNB ASSEMBLY A94FOUH	1EM428123
BC1301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC1500	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1501	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1550	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1551	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1050▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1100▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1150▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1200▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1950▲	TRANS POWER BCK-28-9919	LTT2PC0XB051

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C108	CAP CERAMIC (AX) 0.1 $\mu$ F/50V/F/Z	CA1J104TU062
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k $\Omega$	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k $\Omega$	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k $\Omega$	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k $\Omega$	RCX4183T1002
<b>SWITCHES</b>		
SW101B	TACT SWITCH SKQSAB	SST0101AL038
SW103B	TACT SWITCH SKQSAB	SST0101AL038
SW104B	TACT SWITCH SKQSAB	SST0101AL038
SW105B	TACT SWITCH SKQSAB	SST0101AL038
SW106B	TACT SWITCH SKQSAB	SST0101AL038
SW107B	TACT SWITCH SKQSAB	SST0101AL038

## IR SENSOR CBA

Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C113	ELECTROLYTIC CAP. 47 $\mu$ F/16V M H7	CE1CMAVSL470
C115	CHIP CERAMIC CAP. CH J 330pF/50V	CHD1JJ3CH331
<b>DIODES</b>		
D104	LED GREEN 333GT/(E/FNA)	NPWZ333GTEFNA
D105	LED L-53HT	NP4Z000L53HT


Ref. No.	Description	Part No.
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R126	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		
CL101	WIRE ASSEMBLY 8P 8PIN/170MM	WX1A94F0-001
CL103	WIRE ASSEMBLY 4P 4PIN/200MM	WX1A91F4-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJR5KK044

## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002

# ELECTRICAL PARTS LIST

## [ LC320EMXF (Serial No. : DS1A\*\*\*\*\*) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

### NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91F4MMA-002

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91F0MPW-001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C202	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C203	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C204	ELECTROLYTIC CAP. 2.2µF/50V M	CE1JMASDL2R2
C207	CHIP CERAMIC CAP.(1608) B K 0.1µF/16V	CHD1CK30B104
C210	ELECTROLYTIC CAP. 22µF/50V M	CE1JMASDL220
C216	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C217	CHIP CERAMIC CAP.(1608) B K 0.1µF/16V	CHD1CK30B104
C218	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C219	ELECTROLYTIC CAP. 47µF/25V M	CE1EMASDL470
C221	CHIP CERAMIC CAP.(1608) B K 0.01µF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 470µF/25V M	CE1EMASDL471
C223	ELECTROLYTIC CAP. 22µF/50V M	CE1JMASDL220
C224	ELECTROLYTIC CAP. 10µF/50V M	CE1JMASDL100
C302	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 1000µF/6.3V M	CE0KMASDL102
C305	CHIP CERAMIC CAP.(1608) F Z 0.1µF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1µF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470

Ref. No.	Description	Part No.
C501	ELECTROLYTIC CAP. 100µF/25V M	CE1EMASDL101
C601▲	CAP METALIZED FILM 0.47µF/300V K 3.5MM	CT2F474DC004
C602▲	CAP METALIZED FILM 0.47µF/300V K 3.5MM	CT2F474DC004
C605	CAP ELECTROLYTIC 470µF/200V M	CA2D471DYG07
C609	POLYESTER FILM CAP. (PB FREE) 0.047µF/100V J	CA2A473DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.068µF/100V J	CA2A683DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015µF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000µF/25V M	CE1EMZNDL102
C632	ELECTROLYTIC CAP. 220µF/25V M	CE1EMASDL221
C633	ELECTROLYTIC CAP. 2200µF/10V M	CE1AMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 220µF/50V M	CE1JMASDL221
C639	ELECTROLYTIC CAP. 1000µF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 0.47µF/50V M	CE1JMASDLR47
C644	ELECTROLYTIC CAP 3300µF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTOLYTIC 2200µF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022µF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1µF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100µF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000µF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220µF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220µF/10V M	CE1AMASDL221
C656	ELECTROLYTIC CAP. 100µF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22µF/50V M	CE1JMASDL220
C676	ELECTROLYTIC CAP. 2.2µF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C734	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C735	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C736	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C743	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100µF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1µF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102

Ref. No.	Description	Part No.
C809	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C815	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C816	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C829	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C871	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN602	WIRE ASSEMBLY 2PIN 2PIN 145MM RED BLACK	WX1A94F0-201
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D202	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D203	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036

Ref. No.	Description	Part No.
D205	DIODE ZENER 24BSB-T26	NDTC024BST26
D206	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D207	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D208	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D209	DIODE ZENER 39BSB-T26	NDTB039BST26
D210	DIODE ZENER 6V2BSB-T26	NDTB6R2BST26
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D405	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D406	DIODE ZENER 15BSB-T26	NDTB015BST26
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D416	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D602▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D603▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D604▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	DIODE FR154	NDLZ000FR154
D632	DIODE FR104-B	NDLZ000FR104
D633	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D635	DIODE ZENER 24BSB-T26	NDTB024BST26
D637	SCHOTTKY BARRIER DIODE SB160	NDWZ000SB160
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSB-T26	NDTB010BST26
D645	SHUNT REGULATOR KIA431B-AT/P	NSZBA0TJY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002

Ref. No.	Description	Part No.
D675	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D676	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC201	IC TL3472CDR	NSZBA0TTY115
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SSS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRM137
IC871	IC OP AMP NJM4558M(Te1)-#ZZZB	QSZBA0JR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG020Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG020Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L804	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q201	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q202	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q203	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q204	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q205	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	TRANSISTOR 2SD400(E)	QQUE002SD400
Q210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q401	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q501	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-O (TE2 F T)	QQS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P

Ref. No.	Description	Part No.
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
<b>RESISTORS</b>		
R171	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R201	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R202	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R204	RES CARBON FILM T 1/4W J 560 Ω	RCX4561T1001
R206	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R207	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R208	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R209	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R210	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R211	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R212	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R213	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R214	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R216	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R217	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R218	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R219	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R220	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R223	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R225	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R226	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 1W J 2.7 Ω	RN012R7ZU001
R228	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R229	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R231	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R232	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R233	CHIP RES. 1/10W F 750 Ω	RRXAFR5H7500
R234	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 330 Ω	RCX4331T1001
R236	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R237	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R238	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R240	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R241	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R242	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R243	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R245	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R247	METAL OXIDE FILM RES. 1W J 2.7 Ω	RN012R7ZU001
R248	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R301	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R302	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R304	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R305	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R311	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R403	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R404	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R405	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R407	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R408	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 43.0 k Ω	RRXAFR5H4302
R411	CHIP RES. 1/10W F 56k Ω	RRXAFR5H5602
R412	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R601▲	RES. CARBON FILM J 1/2W J 560k Ω	RCX2564T1003



Ref. No.	Description	Part No.
R602▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R604	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R606	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R611	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R616	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R636	RES. CARBON FILM J 1/2W J 2.7 Ω	RCX22R7T1003
R637	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R638	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R641	RES CHIP.(1608) 1/10W D 1.1k Ω	RRXADR5H1101
R642	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R644	CHIP RES. 1/10W F 820 Ω	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R651	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R658	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R660	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R661	RES. CARBON FILM J 1/2W J 390 Ω	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 15 Ω	RCX4150T1001
R663	RES CARBON FILM T 1/4W J 1.8k Ω	RCX4182T1001
R664	RES CARBON FILM T 1/4W J 1.8k Ω	RCX4182T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0 Ω	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620 Ω	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	METAL OXIDE FILM RES. 1W J 0.47 Ω	RN01R47ZU001
R673	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R675	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R677	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R678	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R679	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R680	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R682	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22 Ω	RCX4220T1001
R686	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R687	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R693	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R694	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R695	RES CARBON FILM T 1/4W J 33 Ω	RCX4330T1001

Ref. No.	Description	Part No.
R696	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001
R697	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001
R723	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R724	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R763	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R801	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R802	CHIP RES. 1/10W F 27k Ω	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R807	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R810	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R813	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R820	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R842	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R843	CHIP RES. 1/10W J 110 Ω	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220 Ω	RRXAJR5Z0221
R846	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R847	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R875	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R876	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R877	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R879	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104

Ref. No.	Description	Part No.
R887	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R888	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R891	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R892	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD W/O A GND WIRE UL/CSA 1770 NO BLACK	WAC0172LW022
B11	POW HEAT SINK A7120UH	1EM423993
B12	MODULE HEAT SINK PMC P7150UT	1EM423968
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS202	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	INDUCTOR 22 $\mu$ H-K-5FT	LLARKBSTU220
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+-10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9932	LTT2PC0XB043
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM UC020AF	UTUNNTUSP035

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C757	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
C758	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393

Ref. No.	Description	Part No.
R762	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91F0M1V-001
	INVERTER CBA	A91F0M1V-001-IV
	FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91F0M1V-001-FNIRJN

## INVERTER CBA

Ref. No.	Description	Part No.
	INVERTER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C115	CHIP CERAMIC CAP. CH J 330pF/50V	CHD1JJ3CH331
C1001	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1002	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1003	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1004	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1005	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1006	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1007	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1008	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1009	ELECTROLYTIC CAP. 100 $\mu$ F/25V M	CE1EMASDL101
C1011	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1012	POLYESTER FILM CAP. (PB FREE) 0.0039 $\mu$ F/100V J	CA2A392DT018
C1013	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1014	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C1040	CHIP CERAMIC CAP.(1608) B K 0.47 $\mu$ F/10V	CHD1AK30B474
C1052	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1053	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1056	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1061	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1062	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1063	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1064	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1065	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1066	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1067	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1068	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1072	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1111	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1112	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1113	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1114	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1115	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1116	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1117	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1118	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1122	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1161	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1162	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1163	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100

Ref. No.	Description	Part No.
C1164	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1165	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1166	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1167	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1168	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1172	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1211	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1212	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1213	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1214	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1215	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1216	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1217	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1218	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1222	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1500	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1502	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1550	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1552	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1600	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1620	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1J33CH102
C1702	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1703	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1800	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1801	ELECTROLYTIC CAP. 22μF/35V M	CE1GMASDL220
C1802	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 820pF/2KV	CA3D821PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.027μF/100V J	CA2A273DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1940	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKN0B103
C1970	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C1981	CHIP CERAMIC CAP. F Z 0.01μF/50V	CHD1JZ30F103
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CAP CERAMIC HV 820pF/1KV B K	CA3A821TE006
C1992▲	ELECTROLYTIC CAP 470μF/100V	CE2AMZNDL471
<b>CONNECTORS</b>		
CN1001	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN1003	FFC CONNECTOR IMSA-9615S-11A-PP-A	JC96J11ER007
CN1050▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1100▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1150▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1200▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1000	DIODE ZENER 15BSB-T26	NDTB015BST26
D1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1003	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1004	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1005	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1006	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1040	DIODE ZENER 36BSB-T26	NDTB036BST26
D1060	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1061	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1062	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1063	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1064	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1065	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1066	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1067	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1068	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1069	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1070	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1071	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1072	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1073	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1074	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1110	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1111	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1112	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1113	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1114	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1115	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1116	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1117	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1118	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1119	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1120	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1121	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1122	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1123	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1124	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1160	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1161	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1162	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1163	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1164	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1165	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1166	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1167	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1168	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1169	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1170	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1171	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1172	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1173	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1174	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1210	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1212	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1213	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1214	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1215	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1216	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1217	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1218	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1219	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1220	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1221	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1222	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1223	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1224	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1500	DIODE ZENER 20BSB-T26	NDTB020BST26
D1550	DIODE ZENER 20BSB-T26	NDTB020BST26
D1630	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1700	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1701	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1702	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1703	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1801	DIODE ZENER 10BSB-T26	NDTB010BST26
D1802	WIRE COPPER 6111-06003-0120	XZ40C0SHG002

Ref. No.	Description	Part No.
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1933	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1940	DIODE FAST RECOVERY FR155-B/P	NDWZ0FR155BP
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER 33BSB-T26	NDTB033BST26
D1973	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1990	DIODE FAST RECOVERY 31DF4-FC	QDWZ031DF4FC
D1994	DIODE ZENER 1ZB100BB	NDWZ001ZB100
<b>ICS</b>		
IC1000	IC PULSE-WIDTH-MODULATION CONT TL494CDR	NSCA0T0TY006
IC1700	IC BA10324AF-E2	QSZBA0TRM032
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>TRANSISTORS</b>		
Q1001	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1003	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1004	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1005	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1060	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1061	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1110	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1111	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1160	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1161	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1500	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1501	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1502	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1503	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1550	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1551	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1552	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1553	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1600	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1621	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1801	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1803	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1804	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1815	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1970	NPN TRANSISTOR KTC3200-GR-AT/P	NQSGKTC3200P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R126	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1001	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1002	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R1003	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1004	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1005	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1006	RES CARBON FILM T 1/4W J 56k Ω	RCX4563T1001
R1007	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1008	CHIP RES. 1/10W J 2.2k Ω	RRXAJR5Z0222
R1009	CHIP RES. 1/10W J 82k Ω	RRXAJR5Z0823

Ref. No.	Description	Part No.
R1010	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1011	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R1012	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R1013	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1014	CHIP RES. 1/10W F 4.7k Ω	RRXAFR5H4701
R1015	CHIP RES. 1/10W F 7.5k Ω	RRXAFR5H7501
R1016	CHIP RES. 1/10W J 120k Ω	RRXAJR5Z0124
R1017	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1018	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R1019	WIRE COPPER 6111-06003-0120	XZ40C05HG002
R1021	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1022	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R1023	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R1024	CHIP RES. 1/10W F 100k Ω	RRXAFR5H1003
R1026	CHIP RES. 1/10W F 220 Ω	RRXAFR5H2200
R1028	CHIP RES. 1/10W F 36k Ω	RRXAFR5H3602
R1030	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1031	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R1032	RES CARBON FILM T 1/4W J 24k Ω	RCX4243T1001
R1033	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1034	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1035	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R1036	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1040	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1041	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1043	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1044	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1060	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1061	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1062	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1063	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1064	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1065	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1066	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1067	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1068	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1069	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1070	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1071	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1072	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1080	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1081	CHIP RES. 1/10W J 5.6k Ω	RRXAJR5Z0562
R1110	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1111	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1112	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1113	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1114	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1115	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1116	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1117	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1118	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1119	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1120	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1121	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1122	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1160	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1161	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1162	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1163	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1164	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1165	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1166	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1167	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203

Ref. No.	Description	Part No.
R1168	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1169	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1170	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1171	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1172	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1210	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1211	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1212	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1213	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1214	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1215	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1216	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1217	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1218	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1219	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1220	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1221	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1222	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1500	CHIP RES. 1/10W J 12k Ω	RRXAJR5Z0123
R1501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R1502	RES CARBON FILM T 1/4W J 150 Ω	RCX4151T1001
R1503	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1504	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1505	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1506	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1550	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1551	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R1552	RES CARBON FILM T 1/4W J 150 Ω	RCX4151T1001
R1553	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1554	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1555	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1556	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1600	CHIP RES. 1/10W J 18k Ω	RRXAJR5Z0183
R1601	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1620	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1621	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1630	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1631	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R1700	CHIP RES. 1/10W J 8.2k Ω	RRXAJR5Z0822
R1701	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1800	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1801	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1802	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1803	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R1804	RES CARBON FILM T 1/4W J 1.2 Ω	RCX41R2T1001
R1805	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R1806	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1807	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1808	CHIP RES. 1/10W J 5.1k Ω	RRXAJR5Z0512
R1809	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R1810	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R1811	RES CARBON FILM T 1/4W J 100k Ω	RCX4104T1001
R1812	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1930	RES CARBON FILM T 1/4W J 47 Ω	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 82 Ω	RCX4820T1001
R1933	RES CARBON FILM T 1/4W J 82 Ω	RCX4820T1001
R1934	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R1935	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R1936	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.33 Ω	RN02R33ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1940	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001

Ref. No.	Description	Part No.
R1941	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 180k Ω	RCX4184T1001
R1943	RES CARBON FILM T 1/4W J 820k Ω	RCX4824T1001
R1944	RES CARBON FILM T 1/4W J 820k Ω	RCX4824T1001
R1945	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R1946	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1947	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1948	METAL OXIDE RES. 1W J 47k Ω	RN01473ZU001
R1967	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1968	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1969	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1970	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R1971	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R1972	CHIP RES. 1/10W J 68k Ω	RRXAJR5Z0683
R1973	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1975	CHIP RES. 1/10W F 30k Ω	RRXAFR5H3002
R1976	CHIP RES. 1/10W F 30k Ω	RRXAFR5H3002
R1977	CHIP RES. 1/10W F 27k Ω	RRXAFR5H2702
R1979	CHIP RES. 1/10W F 6.8k Ω	RRXAFR5H6801
R1980	CHIP RES. 1/10W F 360 Ω	RRXAFR5H3600
R1981	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1982	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R1983	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1984	RES CARBON FILM T 1/4W J 15k Ω	RCX4153T1001
R1986	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1987	RES CARBON FILM T 1/4W J 820k Ω	RCX4824T1001
R1988	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
<b>MISCELLANEOUS</b>		
B13	HEAT SINK PNA A94F0UH	1EM428121
B14	HEAT SINK PNB ASSEMBLY A94F0UH	1EM428123
BC1301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC1500	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1501	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1550	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1551	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1050▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1100▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1150▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1200▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1950▲	TRANS POWER BCK-35-0607	LTT3PC0XB048

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C108	CAP CERAMIC (AX) 0.1μF/50V/F/Z	CA1J104TU062
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k Ω	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k Ω	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k Ω	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k Ω	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k Ω	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k Ω	RCX4183T1002
<b>SWITCHES</b>		
SW101A	TACT SWITCH SKHHLMA010	SST0101AL049
SW103A	TACT SWITCH SKHHLMA010	SST0101AL049
SW104A	TACT SWITCH SKHHLMA010	SST0101AL049

Ref. No.	Description	Part No.
SW105A	TACT SWITCH SKHHLMA010	SST0101AL049
SW106A	TACT SWITCH SKHHLMA010	SST0101AL049
SW107A	TACT SWITCH SKHHLMA010	SST0101AL049

## IR SENSOR CBA


Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C113	ELECTROLYTIC CAP. 47 $\mu$ F/16V M H7	CE1CMAVSL470
<b>DIODES</b>		
D104	LED GREEN 333GT/E(FNA)	NPWZ33GTEFNA
D105	LED L-53HT	NP4Z000L53HT
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		
CL101	WIRE ASSEMBLY 8P 8PIN/170MM	WX1A94F0-001
CL103	WIRE ASSEMBLY 4P 4PIN/250MM	WX1A94F0-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJRSKK044

## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002

# ELECTRICAL PARTS LIST

## [ LC320EMXF (Serial No. : DS2A\*\*\*\*\*) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

### NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91F9MMA-001

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91F6MPWS001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C202	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C203	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C204	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C207	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C210	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C216	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C217	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C218	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C219	ELECTROLYTIC CAP. 47μF/25V M	CE1EMASDL470
C221	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 470μF/25V M	CE1EMASDL471
C223	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C224	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C302	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C305	CHIP CERAMIC CAP.(1608) F Z 0.1μF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470

Ref. No.	Description	Part No.
C501	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C601▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C602▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C605	CAP ELECTROLYTIC 470μF/200V M	CA2D471DYG07
C609	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.068μF/100V J	CA2A683DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015μF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C632	ELECTROLYTIC CAP. 220μF/25V M	CE1EMASDL221
C633	ELECTROLYTIC CAP. 2200μF/10V M	CE1AMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 220μF/50V M	CE1JMASDL221
C639	ELECTROLYTIC CAP. 1000μF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C644	ELECTROLYTIC CAP 3300μF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTROLYTIC 2200μF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022μF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100μF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C656	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C676	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C734	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C735	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C736	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C743	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102

Ref. No.	Description	Part No.
C809	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C815	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C816	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C829	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C871	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN602	WIRE ASSEMBLY 2PIN 2PIN 145MM RED BLACK	WX1A94F0-201
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D202	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D203	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036

Ref. No.	Description	Part No.
D205	DIODE ZENER 30BSB-T26	NDTB030BST26
D206	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D207	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D208	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D209	DIODE ZENER 39BSB-T26	NDTB039BST26
D210	DIODE ZENER 6V2BSB-T26	NDTB6R2BST26
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D405	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D406	DIODE ZENER 27BSA-T26	NDTA027BST26
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D416	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D602▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D603▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D604▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	DIODE FR154	NDLZ000FR154
D632	DIODE FR104-B	NDLZ000FR104
D633	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D635	DIODE ZENER 24BSB-T26	NDTB024BST26
D637	SCHOTTKY BARRIER DIODE SB160	NDWZ000SB160
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSB-T26	NDTB010BST26
D645	SHUNT REGULATOR KIA431B-AT/P	NSZBA0TJY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002



Ref. No.	Description	Part No.
D675	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D676	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC201	IC TL3472CDR	NSZBA0TTY115
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SSS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRM137
IC871	IC OP AMP NJM4558M(Te1)-#ZZZB	QSZBA0JR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG020Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG020Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L804	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q201	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q202	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q203	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q204	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q205	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	TRANSISTOR 2SD400(E)	QQUE002SD400
Q210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q401	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q501	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-O (TE2 F T)	QQS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P

Ref. No.	Description	Part No.
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
<b>RESISTORS</b>		
R171	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R201	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R202	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R204	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R206	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R207	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R208	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R209	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R210	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R211	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R212	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R213	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R214	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R216	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R217	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R218	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R219	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R220	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R223	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R225	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R226	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 2W J 4.7 Ω	RN024R7ZU001
R228	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R229	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R231	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R232	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R233	CHIP RES. 1/10W F 120 Ω	RRXAFR5H1200
R234	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 100 Ω	RCX4101T1001
R236	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R237	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R238	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R240	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R241	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R242	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R243	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R245	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R247	METAL OXIDE FILM RES. 2W J 4.7 Ω	RN024R7ZU001
R248	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R301	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R302	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R304	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R305	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R311	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R403	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R404	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R405	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R407	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R408	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 43.0 k Ω	RRXAFR5H4302
R411	CHIP RES. 1/10W F 56k Ω	RRXAFR5H5602
R412	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R601▲	RES. CARBON FILM J 1/2W J 560k Ω	RCX2564T1003

Ref. No.	Description	Part No.
R602▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R604	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R606	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R611	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R616	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R636	RES. CARBON FILM J 1/2W J 2.7 Ω	RCX22R7T1003
R637	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R638	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R641	RES CHIP.(1608) 1/10W D 1.1k Ω	RRXADR5H1101
R642	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R644	CHIP RES. 1/10W F 820 Ω	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 4.7k Ω	RCX4472T1001
R651	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R658	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R660	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R661	RES. CARBON FILM J 1/2W J 390 Ω	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 15 Ω	RCX4150T1001
R663	RES CARBON FILM T 1/4W J 1.8k Ω	RCX4182T1001
R664	RES CARBON FILM T 1/4W J 1.8k Ω	RCX4182T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0 Ω	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620 Ω	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	METAL OXIDE FILM RES. 1W J 0.47 Ω	RN01R47ZU001
R673	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R675	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R677	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R678	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R679	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R680	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R682	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22 Ω	RCX4220T1001
R686	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R687	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R693	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R694	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R695	RES CARBON FILM T 1/4W J 33 Ω	RCX4330T1001

Ref. No.	Description	Part No.
R696	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001
R697	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001
R723	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R724	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R763	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R801	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R802	CHIP RES. 1/10W F 27k Ω	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R807	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R810	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R813	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R820	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R842	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R843	CHIP RES. 1/10W J 110 Ω	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220 Ω	RRXAJR5Z0221
R846	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R847	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R875	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R876	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R877	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R879	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104

Ref. No.	Description	Part No.
R887	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R888	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R891	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R892	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD W/O A GND WIRE UL/CSA 1770 NO BLACK	WAC0172LW022
B11	POW HEAT SINK A7120UH	1EM423993
B12	MODULE HEAT SINK PMC P7150UT	1EM423968
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS202	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	INDUCTOR 22 $\mu$ H-K-5FT	LLARKBSTU220
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+-10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9932	LTT2PC0XB043
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM UC020AF	UTUNNTUSP035

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C757	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
C758	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393

Ref. No.	Description	Part No.
R762	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91F6M1V-001
	INVERTER CBA	A91F6M1V-001-IV
	FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91F6M1V-001-FNIRJN

## INVERTER CBA

Ref. No.	Description	Part No.
	INVERTER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C115	CHIP CERAMIC CAP. CH J 330pF/50V	CHD1JJ3CH331
C1001	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1002	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1003	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1004	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1005	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1006	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1007	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1008	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1009	ELECTROLYTIC CAP. 100 $\mu$ F/25V M	CE1EMASDL101
C1011	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1012	POLYESTER FILM CAP. (PB FREE) 0.0039 $\mu$ F/100V J	CA2A392DT018
C1013	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1014	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C1040	CHIP CERAMIC CAP.(1608) B K 0.47 $\mu$ F/10V	CHD1AK30B474
C1052	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1053	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1056	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1061	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1062	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1063	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1064	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1065	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1066	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1067	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1068	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1072	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1111	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1112	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1113	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1114	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1115	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1116	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1117	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1118	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1122	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1161	CAP CERAMIC HV 15pF/6KV/SLJ	CCE1500TE009
C1162	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1163	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100

Ref. No.	Description	Part No.
C1164	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1165	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1166	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1167	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1168	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1172	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1211	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1212	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1213	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1214	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1215	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1216	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1217	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1218	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1222	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1500	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1502	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1550	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1552	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1600	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1620	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1J33CH102
C1702	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1703	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1800	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1801	ELECTROLYTIC CAP. 22μF/35V M	CE1GMASDL220
C1802	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 820pF/2KV	CA3D821PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.027μF/100V J	CA2A273DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1940	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKN0B103
C1970	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C1981	CHIP CERAMIC CAP. F Z 0.01μF/50V	CHD1JZ30F103
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CAP CERAMIC HV 820pF/1KV B K	CA3A821TE006
C1992▲	ELECTROLYTIC CAP 470μF/100V	CE2AMZNDL471
<b>CONNECTORS</b>		
CN1001	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN1003	FFC CONNECTOR IMSA-9615S-11A-PP-A	JC96J11ER007
CN1050▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1100▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1150▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1200▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1000	DIODE ZENER 15BSB-T26	NDTB015BST26
D1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1003	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1004	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1005	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1006	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1040	DIODE ZENER 36BSB-T26	NDTB036BST26
D1060	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1061	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1062	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1063	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1064	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1065	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1066	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1067	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1068	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1069	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1070	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1071	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1072	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1073	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1074	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1110	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1111	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1112	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1113	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1114	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1115	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1116	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1117	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1118	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1119	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1120	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1121	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1122	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1123	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1124	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1160	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1161	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1162	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1163	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1164	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1165	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1166	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1167	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1168	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1169	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1170	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1171	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1172	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1173	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1174	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1210	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1212	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1213	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1214	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1215	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1216	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1217	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1218	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1219	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1220	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1221	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1222	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1223	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1224	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1500	DIODE ZENER 20BSB-T26	NDTB020BST26
D1550	DIODE ZENER 20BSB-T26	NDTB020BST26
D1630	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1700	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1701	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1702	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1703	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1801	DIODE ZENER 10BSB-T26	NDTB010BST26
D1802	WIRE COPPER 6111-06003-0120	XZ40C0SHG002

Ref. No.	Description	Part No.
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1933	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1940	DIODE FAST RECOVERY FR155-B/P	NDWZ0FR155BP
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER 33BSB-T26	NDTB033BST26
D1973	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1990	DIODE FAST RECOVERY 31DF4-FC	QDWZ031DF4FC
D1994	DIODE ZENER 1ZB100BB	NDWZ001ZB100
<b>ICS</b>		
IC1000	IC PULSE-WIDTH-MODULATION CONT TL494CDR	NSCA0T0TY006
IC1700	IC BA10324AF-E2	QSZBA0TRM032
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>TRANSISTORS</b>		
Q1001	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1003	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1004	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1005	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1060	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1061	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1110	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1111	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1160	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1161	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1500	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1501	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1502	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1503	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1550	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1551	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1552	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1553	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1600	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1621	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1801	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1803	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1804	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1815	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1970	NPN TRANSISTOR KTC3200-GR-AT/P	NQSGKTC3200P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R126	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R1001	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1002	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R1003	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1004	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1005	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1006	RES CARBON FILM T 1/4W J 56k Ω	RCX4563T1001
R1007	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1008	CHIP RES. 1/10W J 2.2k Ω	RRXAJR5Z0222
R1009	CHIP RES. 1/10W J 82k Ω	RRXAJR5Z0823

Ref. No.	Description	Part No.
R1010	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1011	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R1012	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R1013	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1014	CHIP RES. 1/10W F 4.7k Ω	RRXAFR5H4701
R1015	CHIP RES. 1/10W F 7.5k Ω	RRXAFR5H7501
R1016	CHIP RES. 1/10W J 120k Ω	RRXAJR5Z0124
R1017	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1018	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R1019	WIRE COPPER 6111-06003-0120	XZ40C05HG002
R1021	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1022	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R1023	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R1024	CHIP RES. 1/10W F 100k Ω	RRXAFR5H1003
R1026	CHIP RES. 1/10W F 220 Ω	RRXAFR5H2200
R1028	CHIP RES. 1/10W F 36k Ω	RRXAFR5H3602
R1030	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1031	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R1032	RES CARBON FILM T 1/4W J 24k Ω	RCX4243T1001
R1033	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1034	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1035	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R1036	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1040	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1041	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1043	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1044	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1060	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1061	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1062	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1063	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1064	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1065	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1066	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1067	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1068	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1069	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1070	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1071	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1072	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1080	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1081	CHIP RES. 1/10W J 5.6k Ω	RRXAJR5Z0562
R1110	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1111	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1112	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1113	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1114	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1115	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1116	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1117	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1118	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1119	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1120	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1121	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1122	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1160	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1161	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1162	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1163	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1164	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1165	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1166	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1167	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203

Ref. No.	Description	Part No.
R1168	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1169	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1170	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1171	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1172	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1210	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1211	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1212	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1213	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1214	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1215	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1216	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1217	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1218	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1219	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1220	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1221	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1222	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1500	CHIP RES. 1/10W J 12k $\Omega$	RRXAJR5Z0123
R1501	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1502	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1503	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1504	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1505	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1506	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1550	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1551	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1552	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1553	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1554	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1555	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1556	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1600	CHIP RES. 1/10W J 18k $\Omega$	RRXAJR5Z0183
R1601	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1620	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1621	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1630	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1631	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1700	CHIP RES. 1/10W J 8.2k $\Omega$	RRXAJR5Z0822
R1701	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1800	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1801	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1802	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1803	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1804	RES CARBON FILM T 1/4W J 1.2 $\Omega$	RCX41R2T1001
R1805	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R1806	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1807	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1808	CHIP RES. 1/10W J 5.1k $\Omega$	RRXAJR5Z0512
R1809	CHIP RES. 1/10W J 1.5k $\Omega$	RRXAJR5Z0152
R1810	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1811	RES CARBON FILM T 1/4W J 100k $\Omega$	RCX4104T1001
R1812	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1930	RES CARBON FILM T 1/4W J 47 $\Omega$	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k $\Omega$	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1933	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1934	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R1935	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R1936	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.33 $\Omega$	RN02R33ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1940	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001

Ref. No.	Description	Part No.
R1941	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 180k $\Omega$	RCX4184T1001
R1943	RES CARBON FILM T 1/4W J 820k $\Omega$	RCX4824T1001
R1944	RES CARBON FILM T 1/4W J 820k $\Omega$	RCX4824T1001
R1945	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R1946	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1947	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1948	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1967	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1968	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1969	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1970	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R1971	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1972	CHIP RES. 1/10W J 68k $\Omega$	RRXAJR5Z0683
R1973	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1975	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1976	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1977	CHIP RES. 1/10W F 27k $\Omega$	RRXAFR5H2702
R1979	CHIP RES. 1/10W F 6.8k $\Omega$	RRXAFR5H6801
R1980	CHIP RES. 1/10W F 360 $\Omega$	RRXAFR5H3600
R1981	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R1982	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1983	RES CARBON FILM T 1/4W J 33k $\Omega$	RCX4333T1001
R1984	RES CARBON FILM T 1/4W J 15k $\Omega$	RCX4153T1001
R1986	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1987	RES CARBON FILM T 1/4W J 820k $\Omega$	RCX4824T1001
R1988	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
<b>MISCELLANEOUS</b>		
B13	HEAT SINK PNA A94F0UH	1EM428121
B14	HEAT SINK PNB ASSEMBLY A94F0UH	1EM428123
BC1301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC1500	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1501	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1550	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1551	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1050▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1100▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1150▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1200▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1950▲	TRANS POWER BCK-35-0607	LTT3PC0XB048

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C108	CAP CERAMIC (AX) 0.1 $\mu$ F/50V/FZ	CA1J104TU062
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k $\Omega$	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k $\Omega$	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k $\Omega$	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k $\Omega$	RCX4183T1002
<b>SWITCHES</b>		
SW101A	TACT SWITCH SKHHLMA010	SST0101AL049
SW103A	TACT SWITCH SKHHLMA010	SST0101AL049
SW104A	TACT SWITCH SKHHLMA010	SST0101AL049

Ref. No.	Description	Part No.
SW105A	TACT SWITCH SKHHLMA010	SST0101AL049
SW106A	TACT SWITCH SKHHLMA010	SST0101AL049
SW107A	TACT SWITCH SKHHLMA010	SST0101AL049

## IR SENSOR CBA


Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C113	ELECTROLYTIC CAP. 47 $\mu$ F/16V M H7	CE1CMAVSL470
<b>DIODES</b>		
D104	LED GREEN 333GT/E(FNA)	NPWZ33GTEFNA
D105	LED L-53HT	NP4Z000L53HT
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		
CL101	WIRE ASSEMBLY 8P 8PIN/170MM	WX1A94F0-001
CL103	WIRE ASSEMBLY 4P 4PIN/250MM	WX1A94F0-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJRSKK044

## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002

# ELECTRICAL PARTS LIST

## [ LC320EMXF (Serial No. : DS4A\*\*\*\*\* ) ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

### NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91FMMMA-002

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91FGMPWS001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C202	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C203	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C204	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C207	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C210	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C216	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C217	CHIP CERAMIC CAP.(1608) B K 0.1μF/16V	CHD1CK30B104
C218	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C219	ELECTROLYTIC CAP. 47μF/25V M	CE1EMASDL470
C221	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 470μF/25V M	CE1EMASDL471
C223	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C224	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C302	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C305	CHIP CERAMIC CAP.(1608) F Z 0.1μF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470

Ref. No.	Description	Part No.
C501	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C601▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C602▲	CAP METALIZED FILM 0.47μF/300V K 3.5MM	CT2F474DC004
C605	CAP ELECTROLYTIC 470μF/200V M	CA2D471DYG07
C609	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.068μF/100V J	CA2A683DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015μF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C632	ELECTROLYTIC CAP. 220μF/25V M	CE1EMASDL221
C633	CAP ALUMINUM ELECTROLYTIC 2200μF/6.3V M	CE0KMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 220μF/50V M	CE1JMASDL221
C639	ELECTROLYTIC CAP. 1000μF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C644	ELECTROLYTIC CAP. 3300μF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTROLYTIC 2200μF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022μF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1μF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100μF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000μF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220μF/10V M	CE1AMASDL221
C656	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C676	ELECTROLYTIC CAP. 2.2μF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C734	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C735	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C736	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C743	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1μF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1μF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1μF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102



Ref. No.	Description	Part No.
C809	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C815	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C816	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000μF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP(1608) B K 1μF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C829	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C871	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN602	WIRE ASSEMBLY 2PIN 2PIN 145MM RED BLACK	WX1A94F0-201
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D202	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D203	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036

Ref. No.	Description	Part No.
D205	DIODE ZENER 24BSB-T26	NDTC024BST26
D206	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D207	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D208	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D209	DIODE ZENER 39BSB-T26	NDTB039BST26
D210	DIODE ZENER 6V2BSB-T26	NDTB6R2BST26
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D405	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D406	DIODE ZENER 15BSB-T26	NDTB015BST26
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D416	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D602▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D603▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D604▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	DIODE FR154	NDLZ000FR154
D632	DIODE FR104-B	NDLZ000FR104
D633	DIODE FAST RECOVERY FR151-B/P	NDWZ0FR151BP
D635	DIODE ZENER 24BSB-T26	NDTB024BST26
D637	SCHOTTKY BARRIER DIODE SB160	NDWZ000SB160
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSB-T26	NDTB010BST26
D645	SHUNT REGULATOR KIA431B-AT/P	NSZBA0TJY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002

Ref. No.	Description	Part No.
D675	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D676	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC201	IC TL3472CDR	NSZBA0TTY115
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SSS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRM137
IC871	IC OP AMP NJM4558M(Te1)-#ZZZB	QSZBA0JR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG020Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG020Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L804	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q201	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q202	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q203	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q204	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q205	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	TRANSISTOR 2SD400(E)	QQUE002SD400
Q210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q401	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q501	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-O (TE2 F T)	QQS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P

Ref. No.	Description	Part No.
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
<b>RESISTORS</b>		
R171	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R201	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R202	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R204	RES CARBON FILM T 1/4W J 560 Ω	RCX4561T1001
R206	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R207	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R208	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R209	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R210	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R211	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R212	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R213	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R214	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R216	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R217	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R218	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R219	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R220	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R223	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R225	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R226	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 1W J 2.7 Ω	RN012R7ZU001
R228	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R229	RES CARBON FILM T 1/4W J 2.7k Ω	RCX4272T1001
R231	CHIP RES. 1/10W J 1.5k Ω	RRXAJR5Z0152
R232	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R233	CHIP RES. 1/10W F 750 Ω	RRXAFR5H7500
R234	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 330 Ω	RCX4331T1001
R236	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R237	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R238	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R240	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R241	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R242	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R243	RES CARBON FILM T 1/4W J 220 Ω	RCX4221T1001
R245	RES CARBON FILM T 1/4W J 8.2k Ω	RCX4822T1001
R247	METAL OXIDE FILM RES. 1W J 2.7 Ω	RN012R7ZU001
R248	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R301	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R302	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R304	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R305	CHIP RES. 1/10W J 47 Ω	RRXAJR5Z0470
R311	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R403	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R404	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R405	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R407	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R408	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 43.0 k Ω	RRXAFR5H4302
R411	CHIP RES. 1/10W F 56k Ω	RRXAFR5H5602
R412	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R501	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R601▲	RES. CARBON FILM J 1/2W J 560k Ω	RCX2564T1003

Ref. No.	Description	Part No.
R602▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R604	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R606	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R611	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 3.9k Ω	RCX4392T1001
R616	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 Ω H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001
R636	RES. CARBON FILM J 1/2W J 2.7 Ω	RCX22R7T1003
R637	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R638	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k Ω	RCX4152T1001
R641	RES CHIP.(1608) 1/10W D 1.1k Ω	RRXADR5H1101
R642	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10k Ω	RRXADR5H1002
R644	CHIP RES. 1/10W F 820 Ω	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 6.8k Ω	RCX4682T1001
R651	CHIP RES. 1/10W J 1 Ω	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R658	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R660	RES CARBON FILM T 1/4W J 680 Ω	RCX4681T1001
R661	RES. CARBON FILM J 1/2W J 390 Ω	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R663	RES CARBON FILM T 1/4W J 680 Ω	RCX4681T1001
R664	RES CARBON FILM T 1/4W J 680 Ω	RCX4681T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0 Ω	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620 Ω	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R673	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R675	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R677	RES CARBON FILM T 1/4W J 270 Ω	RCX4271T1001
R678	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R679	CHIP RES. 1/10W F 3.6k Ω	RRXAFR5H3601
R680	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R682	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22 Ω	RCX4220T1001
R686	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R687	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10 Ω	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7 Ω	RCX42R7T1001
R693	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R694	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R696	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001

Ref. No.	Description	Part No.
R697	METAL OXIDE FILM RES. 1W J 3.3 Ω	RN013R3ZU001
R723	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R724	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10 Ω	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R763	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R801	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R802	CHIP RES. 1/10W F 27k Ω	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11k Ω	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R807	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R810	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R813	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3k Ω	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R820	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R842	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R843	CHIP RES. 1/10W J 110 Ω	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220 Ω	RRXAJR5Z0221
R846	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R847	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7k Ω	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560 Ω	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R875	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R876	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R877	CHIP RES. 1/10W J 1k Ω	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0k Ω	RCX4102T1001
R879	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47k Ω	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100 Ω	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R887	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223

Ref. No.	Description	Part No.
R888	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R891	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R892	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD W/O A GND WIRE UL/CSA 1770 NO BLACK	WAC0172LW022
B11	POW HEAT SINK A7120UH	1EM423993
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS202	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	INDUCTOR 22 $\mu$ H-K-5FT	LLARKBSTU220
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9932	LTT2PC0XB043
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM UC020AF	UTUNNTUSP035

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C757	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
C758	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R762	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		

Ref. No.	Description	Part No.
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91FGM1V-001
	INVERTER CBA	A91FGM1V-001-IV
	FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91FGM1V-001-FNIRJN

## INVERTER CBA

Ref. No.	Description	Part No.
	INVERTER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C1001	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1002	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1003	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1004	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1005	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1006	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1007	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1008	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1009	ELECTROLYTIC CAP. 100 $\mu$ F/25V M	CE1EMASDL101
C1011	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1012	POLYESTER FILM CAP. (PB FREE) 0.0039 $\mu$ F/100V J	CA2A392DT018
C1013	CHIP CERAMIC CAP.(1608) B K 0.1 $\mu$ F/50V	CHD1JK30B104
C1014	CHIP CERAMIC CAP.(1608) B K 6800pF/50V	CHD1JK30B682
C1040	CHIP CERAMIC CAP.(1608) B K 0.47 $\mu$ F/10V	CHD1AK30B474
C1050	CERAMIC CAP. B K 0.01 $\mu$ F/1KV	CCD3AKN0B103
C1051	CERAMIC CAP. B K 0.01 $\mu$ F/1KV	CCD3AKN0B103
C1052	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1053	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1056	ELECTROLYTIC CAP 100 $\mu$ F/100V	CE2AMZNDL101
C1061	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1062	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1063	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1064	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1065	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1066	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1067	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1068	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1072	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1111	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1112	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1113	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1114	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1115	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1116	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1117	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1118	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1122	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103
C1161	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1162	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1163	ELECTROLYTIC CAP. 10 $\mu$ F/50V M	CE1JMASDL100
C1164	CHIP CERAMIC CAP.(1608) B K 0.01 $\mu$ F/50V	CHD1JK30B103

Ref. No.	Description	Part No.
C1165	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1166	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1167	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1168	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1172	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1211	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1212	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1213	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1214	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1215	CAP CERAMIC HV 15pF/6KV/SL/J	CCE1500TE009
C1216	CAP CERAMIC (AX) 1500pF/50V/B/K	CA1J152TU061
C1217	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C1218	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1222	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1500	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1502	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1550	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C1552	CHIP CERAMIC CAP.(1608) B K 0.01μF/50V	CHD1JK30B103
C1600	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1620	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C1702	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1703	CHIP CERAMIC CAP.(1608) F Z 0.22μF/50V	CHD1JZ30F224
C1800	ELECTROLYTIC CAP. 100μF/25V M	CE1EMASDL101
C1801	ELECTROLYTIC CAP. 22μF/35V M	CE1GMASDL220
C1802	CHIP CERAMIC CAP.(1608) B K 0.1μF/50V	CHD1JK30B104
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 820pF/2KV	CA3D821PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.027μF/100V J	CA2A273DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1970	POLYESTER FILM CAP. (PB FREE) 0.047μF/100V J	CA2A473DT018
C1981	CHIP CERAMIC CAP. F Z 0.01μF/50V	CHD1JZ30F103
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CAP CERAMIC HV 820pF/1KV B K	CA3A821TE006
C1992▲	ELECTROLYTIC CAP 470μF/100V	CE2AMZNDL471
<b>CONNECTORS</b>		
CN1001	FFC CONNECTOR 15P IMSA-9615S-15A-PP-A	JC96J15ER007
CN1003	FFC CONNECTOR IMSA-9615S-11A-PP-A	JC96J11ER007
CN1050▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1100▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1150▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1200▲	CONNECTOR/JACK 1747386-1	JB17J02AP002
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1000	DIODE ZENER 15BSB-T26	NDTB015BST26
D1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1003	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1004	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1005	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1006	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1040	DIODE ZENER 36BSB-T26	NDTB036BST26
D1050	DIODE FR104-B	NDLZ000FR104
D1051	DIODE FR104-B	NDLZ000FR104
D1060	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1061	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1062	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1063	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1064	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1065	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133

Ref. No.	Description	Part No.
D1066	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1067	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1068	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1069	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1070	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1071	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1072	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1073	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1074	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1110	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1111	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1112	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1113	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1114	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1115	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1116	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1117	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1118	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1119	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1120	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1121	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1122	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1123	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1124	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1160	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1161	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1162	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1163	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1164	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1165	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1166	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1167	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1168	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1169	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1170	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1171	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1172	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1173	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1174	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1210	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1212	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1213	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1214	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1215	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1216	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1217	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1218	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1219	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1220	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1221	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1222	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1223	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1224	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1500	DIODE ZENER 20BSB-T26	NDTB020BST26
D1550	DIODE ZENER 20BSB-T26	NDTB020BST26
D1630	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1700	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1701	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1702	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1703	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1801	DIODE ZENER 10BSB-T26	NDTB010BST26
D1802	WIRE COPPER 6111-06003-0120	XZ40C0SHG002

Ref. No.	Description	Part No.
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1933	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER HZS33NB2TE-EQ	QDTBHZS33NB2
D1972	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1973	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1990	DIODE FAST RECOVERY 31DF4-FC	QDWZ031DF4FC
D1994	DIODE ZENER 1ZB100BB	NDWZ001ZB100
<b>ICS</b>		
IC1000	IC PULSE-WIDTH-MODULATION CONT TL494CDR	NSCA0T0TY006
IC1700	IC BA10324AF-E2	QSZBA0TRM032
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>TRANSISTORS</b>		
Q1001	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1003	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1004	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1005	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1060	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1061	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1110	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1111	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1160	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1161	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1210	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1500	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1501	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1502	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1503	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1550	FET MOS 2SK2417(FT)	QFWZSK2417FT
Q1551	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1552	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1553	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1600	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1621	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1801	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1803	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1804	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1815	TRANSISTOR 2SA950-O (TE2 F T)	QQS002SA950F
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y (TE2 F T)	QQSY2SC2120F
Q1970	NPN TRANSISTOR KTC3200-GR-AT/P	NQSGKTC3200P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R1001	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1002	CHIP RES. 1/10W F 1.0k Ω	RRXAFR5H1001
R1003	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1004	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1005	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1006	RES CARBON FILM T 1/4W J 56k Ω	RCX4563T1001
R1007	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1008	CHIP RES. 1/10W J 2.2k Ω	RRXAJR5Z0223
R1009	CHIP RES. 1/10W J 82k Ω	RRXAJR5Z0823
R1010	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000

Ref. No.	Description	Part No.
R1011	CHIP RES. 1/10W F 10k Ω	RRXAFR5H1002
R1012	CHIP RES. 1/10W F 24k Ω	RRXAFR5H2402
R1013	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R1014	CHIP RES. 1/10W F 4.7k Ω	RRXAFR5H4701
R1015	CHIP RES. 1/10W F 7.50 k Ω	RRXAFR5H7501
R1016	CHIP RES. 1/10W J 120k Ω	RRXAJR5Z0124
R1017	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1018	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R1019	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R1021	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1022	CHIP RES. 1/10W F 2.2k Ω	RRXAFR5H2201
R1023	CHIP RES. 1/10W F 3.3k Ω	RRXAFR5H3301
R1024	CHIP RES. 1/10W F 100k Ω	RRXAFR5H1003
R1026	CHIP RES. 1/10W F 220 Ω	RRXAFR5H2200
R1028	CHIP RES. 1/10W F 36k Ω	RRXAFR5H3602
R1030	CHIP RES. 1/10W J 22k Ω	RRXAJR5Z0223
R1031	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R1032	RES CARBON FILM T 1/4W J 24k Ω	RCX4243T1001
R1033	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1034	CHIP RES. 1/10W J 10k Ω	RRXAJR5Z0103
R1035	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R1036	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1040	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1041	RES CARBON FILM T 1/4W J 33k Ω	RCX4333T1001
R1043	RES CARBON FILM T 1/4W J 12k Ω	RCX4123T1001
R1044	METAL OXIDE FILM RES. 2W J 0.39 Ω	RN02R39ZU001
R1050	METAL OXIDE FILM RES. 1W J 15k Ω	RN01153ZU001
R1051	METAL OXIDE FILM RES. 1W J 15k Ω	RN01153ZU001
R1060	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1061	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1062	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1063	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1064	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1065	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1066	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1067	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1068	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1069	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1070	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1071	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1072	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1080	CHIP RES. 1/10W F 22k Ω	RRXAFR5H2202
R1081	CHIP RES. 1/10W J 5.6k Ω	RRXAJR5Z0562
R1110	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1111	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1112	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1113	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1114	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1115	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1116	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1117	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1118	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1119	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1120	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1121	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1122	CHIP RES. 1/10W J 1M Ω	RRXAJR5Z0105
R1160	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104
R1161	CHIP RES. 1/10W J 20k Ω	RRXAJR5Z0203
R1162	CHIP RES. 1/10W J 390 Ω	RRXAJR5Z0391
R1163	CHIP RES. 1/10W F 18k Ω	RRXAFR5H1802
R1164	CHIP RES. 1/10W F 8.2k Ω	RRXAFR5H8201
R1165	RES CARBON FILM T 1/4W J 27k Ω	RCX4273T1001
R1166	CHIP RES. 1/10W J 100k Ω	RRXAJR5Z0104

Ref. No.	Description	Part No.
R1167	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1168	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1169	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1170	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1171	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1172	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1210	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1211	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1212	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1213	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1214	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1215	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1216	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1217	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R1218	CHIP RES. 1/10W J 390 $\Omega$	RRXAJR5Z0391
R1219	CHIP RES. 1/10W F 18k $\Omega$	RRXAFR5H1802
R1220	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R1221	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R1222	CHIP RES. 1/10W J 1M $\Omega$	RRXAJR5Z0105
R1500	CHIP RES. 1/10W J 12k $\Omega$	RRXAJR5Z0123
R1501	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1502	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1503	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1504	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1505	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1506	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1550	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1551	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R1552	RES CARBON FILM T 1/4W J 150 $\Omega$	RCX4151T1001
R1553	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1554	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1555	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1556	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1600	CHIP RES. 1/10W J 18k $\Omega$	RRXAJR5Z0183
R1601	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1620	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R1621	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1630	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1631	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1700	CHIP RES. 1/10W J 8.2k $\Omega$	RRXAJR5Z0822
R1701	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1800	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R1801	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1802	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1803	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1804	RES CARBON FILM T 1/4W J 1.2 $\Omega$	RCX41R2T1001
R1805	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R1806	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1807	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1808	CHIP RES. 1/10W J 5.1k $\Omega$	RRXAJR5Z0512
R1809	CHIP RES. 1/10W J 1.5k $\Omega$	RRXAJR5Z0152
R1810	RES CARBON FILM T 1/4W J 4.7k $\Omega$	RCX4472T1001
R1811	RES CARBON FILM T 1/4W J 100k $\Omega$	RCX4104T1001
R1812	RES CARBON FILM T 1/4W J 12k $\Omega$	RCX4123T1001
R1930	RES CARBON FILM T 1/4W J 47 $\Omega$	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k $\Omega$	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1933	RES CARBON FILM T 1/4W J 82 $\Omega$	RCX4820T1001
R1934	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R1935	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R1936	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.33 $\Omega$	RN02R33ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001

Ref. No.	Description	Part No.
R1940	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1941	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 180k $\Omega$	RCX4184T1001
R1943	RES CARBON FILM 1/4W J 820k $\Omega$	RCX4824FS002
R1944	RES CARBON FILM 1/4W J 820k $\Omega$	RCX4824FS002
R1945	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R1967	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1968	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1969	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1970	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R1971	RES CARBON FILM T 1/4W J 3.9k $\Omega$	RCX4392T1001
R1972	CHIP RES. 1/10W J 68k $\Omega$	RRXAJR5Z0683
R1973	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R1975	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1976	CHIP RES. 1/10W F 30k $\Omega$	RRXAFR5H3002
R1977	CHIP RES. 1/10W F 27k $\Omega$	RRXAFR5H2702
R1979	CHIP RES. 1/10W F 6.8k $\Omega$	RRXAFR5H6801
R1980	CHIP RES. 1/10W F 360 $\Omega$	RRXAFR5H3600
R1981	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R1982	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R1983	RES CARBON FILM T 1/4W J 33k $\Omega$	RCX4333T1001
R1984	RES CARBON FILM T 1/4W J 15k $\Omega$	RCX4153T1001
R1986	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R1987	RES CARBON FILM 1/4W J 820k $\Omega$	RCX4824FS002
R1988	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
<b>MISCELLANEOUS</b>		
B13	HEAT SINK PNA A94FOUH	1EM428121
B14	HEAT SINK PNB ASSEMBLY A94FOUH	1EM428123
BC1301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC1500	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1501	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1550	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1551	COIL BEADS CORE FBR07VA850TB-00	LLBF00ZTU020
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1050▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1100▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1150▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1200▲	TRANS INVERTER HVT-153	LTZ3P20XB009
T1950▲	TRANS POWER BCK-28-9919	LTT2PC0XB051

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C108	CAP CERAMIC (AX) 0.1 $\mu$ F/50V/F/Z	CA1J104TU062
C115	CHIP CERAMIC CAP. CH J 330pF/50V	CHD1JJ3CH331
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k $\Omega$	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k $\Omega$	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k $\Omega$	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k $\Omega$	RCX4183T1002
R126	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
<b>SWITCHES</b>		
SW101A	TACT SWITCH SKHHLMA010	SST0101AL049
SW103A	TACT SWITCH SKHHLMA010	SST0101AL049
SW104A	TACT SWITCH SKHHLMA010	SST0101AL049

Ref. No.	Description	Part No.
SW105A	TACT SWITCH SKHHLMA010	SST0101AL049
SW106A	TACT SWITCH SKHHLMA010	SST0101AL049
SW107A	TACT SWITCH SKHHLMA010	SST0101AL049

## IR SENSOR CBA


Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C113	ELECTROLYTIC CAP. 47 $\mu$ F/16V M H7	CE1CMAVSL470
<b>DIODES</b>		
D104	LED GREEN 333GT/E(FNA)	NPWZ33GTEFNA
D105	LED L-53HT	NP4Z000L53HT
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		
CL101	WIRE ASSEMBLY 8P 8PIN/170MM	WX1A94F0-001
CL103	WIRE ASSEMBLY 4P 4PIN/250MM	WX1A94F0-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJRSKK044

## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002



# ELECTRICAL PARTS LIST [ LC321SSX ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

## NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91FSMMA-001

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91FSMPWA001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C202	ELECTROLYTIC CAP. 22µF/50V M	CE1JMASDL220
C203	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C221	CHIP CERAMIC CAP.(1608) B K 0.01µF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 100µF/16V M	CE1CMASDL101
C302	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 330µF/10V M	CE1AMASDL331
C305	CHIP CERAMIC CAP.(1608) F Z 0.1µF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1µF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C601▲	CAP METALIZED FILM 0.47µF/300V K 3.5MM	CT2F474DC004
C602▲	CAP METALIZED FILM 0.47µF/300V K 3.5MM	CT2F474DC004
C605	CAP ELECTROLYTIC 470µF/200V M	CA2D471DYG07
C609	POLYESTER FILM CAP. (PB FREE) 0.047µF/100V J	CA2A473DT018
C610	POLYESTER FILM CAP. (PB FREE) 0.0012µF/100V J	CA2A122DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.082µF/100V J	CA2A823DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015µF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000µF/25V M	CE1EMZNDL102

Ref. No.	Description	Part No.
C633	CAP ALUMINUM ELECTROLYTIC 2200µF/6.3V M	CE0KMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 330µF/50V M	CE1JMZPDL331
C639	ELECTROLYTIC CAP. 1000µF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 1µF/50V M	CE1JMASDL1R0
C644	ELECTROLYTIC CAP. 3300µF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTROLYTIC 2200µF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022µF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1µF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100µF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000µF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220µF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220µF/10V M	CE1AMASDL221
C655	ELECTROLYTIC CAP. 22µF/50V M	CE1JMASDL220
C656	ELECTROLYTIC CAP. 100µF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22µF/50V M	CE1JMASDL220
C676	ELECTROLYTIC CAP. 2.2µF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C743	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100µF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1µF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C809	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP.(1608) B K 0.47µF/16V	CHD1CK30B474
C816	ELECTROLYTIC CAP. 10µF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10µF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000µF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10µF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104

Ref. No.	Description	Part No.
C829	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C848	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C849	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C850	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C851	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C852	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C853	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C854	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C855	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C871	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FPC/FFC CONNECTOR IMSA-9615S-05A-PP-A	JC96J05ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26

Ref. No.	Description	Part No.
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D602▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D603▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D604▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D633	DIODE FAST RECOVERY FR151-B/P	NDWZ0FR151BP
D635	DIODE ZENER 18BSC-T26	NDTC018BST26
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSA-T26	NDTA010BST26
D645	SHUNT REGULATOR KIA431B-AT/P	NSZBA0TJY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D675	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D676	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D680	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRFM137
IC871	IC OP AMP NJM4558M(TE1)-#ZZZB	QSZBA0TJR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330

Ref. No.	Description	Part No.
L804	RADIAL LEAD INDUCTORS 33 $\mu$ H	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q210	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-O (TE2 F T)	QOS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (TE2 F T)	QOS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y (TE2 F T)	QOSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y (TE2 F T)	QOSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y (TE2 F T)	QOSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
<b>RESISTORS</b>		
R171	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R201	CHIP RES. 1/10W J 2.2k $\Omega$	RRXAJR5Z0222
R202	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R203	RES CARBON FILM T 1/4W J 5.6k $\Omega$	RCX4562T1001
R204	RES CARBON FILM T 1/4W J 100k $\Omega$	RCX4104T1001
R205	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R206	RES CARBON FILM T 1/4W J 100k $\Omega$	RCX4104T1001
R207	RES CARBON FILM T 1/4W J 82k $\Omega$	RCX4823T1001
R208	RES CARBON FILM T 1/4W J 10k $\Omega$	RCX4103T1001
R209	RES CARBON FILM T 1/4W J 10k $\Omega$	RCX4103T1001
R223	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R225	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R226	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 1W J 0.39 $\Omega$	RN01R39ZU001
R228	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R229	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R230	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R231	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R232	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R233	CHIP RES. 1/10W F 270 $\Omega$	RRXAFR5H2700
R234	CHIP RES. 1/10W F 2.2k $\Omega$	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R247	METAL OXIDE FILM RES. 1W J 0.39 $\Omega$	RN01R39ZU001

Ref. No.	Description	Part No.
R248	METAL OXIDE FILM RES. 1W J 0.39 $\Omega$	RN01R39ZU001
R302	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R306	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R307	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R308	CHIP RES. 1/10W J 82 $\Omega$	RRXAJR5Z0820
R309	CHIP RES. 1/10W J 82 $\Omega$	RRXAJR5Z0820
R310	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R407	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R408	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 2.2k $\Omega$	RRXAFR5H2201
R411	CHIP RES. 1/10W F 56k $\Omega$	RRXAFR5H5602
R601▲	RES. CARBON FILM J 1/2W J 560k $\Omega$	RCX2564T1003
R602▲	CEMENT RESISTOR 5W J 2.2 $\Omega$ H 10MM	RW052R2PAK10
R604	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R606	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R611	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 $\Omega$	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 1.8k $\Omega$	RCX4182T1001
R616	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 $\Omega$ H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R635	RES. CARBON FILM J 1/2W J 2.2 $\Omega$	RCX22R2T1003
R636	RES. CARBON FILM J 1/2W J 2.7 $\Omega$	RCX22R7T1003
R637	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R638	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R641	RES CHIP.(1608) 1/10W D 1.1k $\Omega$	RRXADR5H1101
R642	RES CHIP.(1608) 1/10W D 10k $\Omega$	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10k $\Omega$	RRXADR5H1002
R644	CHIP RES. 1/10W F 820 $\Omega$	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0k $\Omega$	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 2.7k $\Omega$	RCX4272T1001
R651	CHIP RES. 1/10W J 1 $\Omega$	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24k $\Omega$	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R655	RES CARBON FILM T 1/4W J 2.7k $\Omega$	RCX4272T1001
R657	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R658	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R660	RES CARBON FILM T 1/4W J 680 $\Omega$	RCX4681T1001
R661	RES. CARBON FILM J 1/2W J 390 $\Omega$	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R663	RES CARBON FILM T 1/4W J 680 $\Omega$	RCX4681T1001
R664	RES CARBON FILM T 1/4W J 680 $\Omega$	RCX4681T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0 $\Omega$	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620 $\Omega$	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0k $\Omega$	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R673	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.8k $\Omega$	RCX4182T1001

Ref. No.	Description	Part No.
R675	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R677	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R678	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R679	CHIP RES. 1/10W F 3.6k $\Omega$	RRXAFR5H3601
R680	CHIP RES. 1/10W F 10k $\Omega$	RRXAFR5H1002
R682	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22 $\Omega$	RCX4220T1001
R687	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R696	METAL RESISTOR 1W J 3.9 $\Omega$	RN013R9ZU001
R697	METAL RESISTOR 1W J 3.9 $\Omega$	RN013R9ZU001
R723	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R724	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R763	RES CARBON FILM T 1/4W J 10k $\Omega$	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R802	CHIP RES. 1/10W F 27k $\Omega$	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11k $\Omega$	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11k $\Omega$	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R810	CHIP CERAMIC CAP. F Z 1 $\mu$ F/10V	CHD1AZ30F105
R813	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R820	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R843	CHIP RES. 1/10W J 110 $\Omega$	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220 $\Omega$	RRXAJR5Z0221
R847	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560 $\Omega$	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560 $\Omega$	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R877	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001

Ref. No.	Description	Part No.
R879	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100 $\Omega$	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100 $\Omega$	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R887	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R888	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R891	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R892	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R894	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD UL 1855MM BLACK	WAC0182LW007
B11	POW HEAT SINK A7120UH	1EM423993
B12	MODULE HEAT SINK PMC P7150UT	1EM423968
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL602	WIRE ASSEMBLY 2PIN 2PIN 90MM RED BLACK	WX1A91FS-204
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS102	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS302	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS303	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+-10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9910A	LTT2PC0XB057
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM TDAU4-D02A	UTUNNTUAL052

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
C757	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
C758	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R762	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91FSM1V-001
	INVERTER POWER CBA	A91FSM1V-001-IV
	----- FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91FSM1V-001-FNIRJN

## INVERTER POWER CBA

Ref. No.	Description	Part No.
	INVERTER POWER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C1620	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1650	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C1651	POLYESTER FILM CAP. (PB FREE) 0.022μF/100V J	CA2A223DT018
C1652	CAP CERAMIC (AX) 0.01μF/50V/B/K	CA1J103TU061
C1653	CAP CERAMIC (AX) 0.01μF/50V/B/K	CA1J103TU061
C1801	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C1802	POLYESTER FILM CAP. (PB FREE) 0.022μF/100V J	CA2A223DT018
C1803	POLYESTER FILM CAP. (PB FREE) 0.01μF/100V J	CA2A103DT018
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 820pF/2KV	CA3D821PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.056μF/100V J	CA2A563DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1941	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKN0B103

Ref. No.	Description	Part No.
C1970	POLYESTER FILM CAP. (PB FREE) 0.0022μF/100V J	CA2A222DT018
C1981	POLYESTER FILM CAP. (PB FREE) 0.01μF/100V J	CA2A103DT018
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CERAMIC CAP. 3300pF/1KV	CCD3AKA0R332
C1992	ELECTROLYTIC CAP. 2200μF/35V M	CE1GMZNDL222
C1995	ELECTROLYTIC CAP. 2200μF/35V M	CE1GMZNDL222
<b>CONNECTORS</b>		
CN1001	FPC/FFC CONNECTOR IMSA-9615S-05A-PP-A	JC96J05ER007
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1651	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1933	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1940	DIODE FAST RECOVERY FR155-B/P	NDWZ0FR155BP
D1960	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER HZS33NB2TE-EQ	QDTBH33NB2
D1990	DIODE SCHOTTKY YG862C15R	QDWZYG862C15
D1994▲	DIODE ZENER 1ZB30BB	NDWZ0001ZB30
<b>ICS</b>		
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>COILS</b>		
L1601	INDUCTOR 100μH-J-26T	LLAXJATTU101
L1602	INDUCTOR 100μH-J-26T	LLAXJATTU101
<b>TRANSISTORS</b>		
Q1650	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1651	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1652	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y(Te2 F T)	QQSY2SC2120F
Q1970	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R1650	RES CARBON FILM T 1/4W J 100 Ω	RCX4101T1001
R1651	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1652	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R1653	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R1654	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1655	RES CARBON FILM T 1/4W J 6.8k Ω	RCX4682T1001
R1656	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R1657	RES CARBON FILM T 1/4W J 100k Ω	RCX4104T1001
R1658	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1800	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1801	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R1803	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1930	RES CARBON FILM T 1/4W J 47 Ω	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 120 Ω	RCX4121T1001
R1933	RES CARBON FILM T 1/4W J 120 Ω	RCX4121T1001
R1934	RES CARBON FILM T 1/4W J 120 Ω	RCX4121T1001
R1935	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R1936	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.47 Ω	RN02R47ZU001

Ref. No.	Description	Part No.
R1938	METAL RESISTER. 2W J 0.56 $\Omega$	RN02R56ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1940	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1941	RES CARBON FILM T 1/4W J 220k $\Omega$	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 270k $\Omega$	RCX4274T1001
R1943	RES CARBON FILM 1/4W J 820k $\Omega$	RCX4824FS002
R1944	RES CARBON FILM 1/4W J 820k $\Omega$	RCX4824FS002
R1945	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R1946	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1947	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1969	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R1970	RES CARBON FILM T 1/4W J 120 $\Omega$	RCX4121T1001
R1975	RES CARBON FILM T 1/4W G 20k $\Omega$	RCX4203T1002
R1979	RES CARBON FILM T 1/4W G 6.8k $\Omega$	RCX4682T1002
R1980	RES CARBON FILM T 1/4W G 270 $\Omega$	RCX4271T1002
R1981	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R1982	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1986	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R1987	RES CARBON FILM 1/4W J 820k $\Omega$	RCX4824FS002
R1988	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
<b>MISCELLANEOUS</b>		
B33	HEAT SINK PND ASSEMBLY A91F2UH	1EM428182
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL1003	WIRE ASSEMBLY 13P 13PIN/120MM	WX1A91FS-201
JS1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS1002	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1950▲	TRANS INVPOW BCK-28-9909D	LTT2PC0XB056

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C108	CAP CERAMIC (AX) 0.1 $\mu$ F/50V/F/Z	CA1J104TU062
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k $\Omega$	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k $\Omega$	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k $\Omega$	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k $\Omega$	RCX4183T1002
<b>SWITCHES</b>		
SW101A	TACT SWITCH SKHHLMA010	SST0101AL049
SW103A	TACT SWITCH SKHHLMA010	SST0101AL049
SW104A	TACT SWITCH SKHHLMA010	SST0101AL049
SW105A	TACT SWITCH SKHHLMA010	SST0101AL049
SW106A	TACT SWITCH SKHHLMA010	SST0101AL049
SW107A	TACT SWITCH SKHHLMA010	SST0101AL049

## IR SENSOR CBA


Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C113	ELECTROLYTIC CAP. 47 $\mu$ F/16V M H7	CE1CMAVSL470
C115	CAP CERAMIC (AX) 330pF/50V/B/K	CA1J331TU061
<b>DIODES</b>		
D104	LED GREEN 333GT/E(FNA)	NPWZ33GTEFNA

Ref. No.	Description	Part No.
D105	LED L-53HT	NP4Z000L53HT
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R126	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		
CL102	WIRE ASSEMBLY 8P 8PIN/240MM	WX1A91FS-001
CL103	WIRE ASSEMBLY 4P 4PIN/250MM	WX1A94F0-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJRSKK044

## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002

# ELECTRICAL PARTS LIST [ 32MF369B/F7 ]

**PRODUCT SAFETY NOTE:** Products marked with a  have special characteristics important to safety. Before replacing any of these components, read carefully the product safety notice in this service manual. Don't degrade the safety of the product through improper servicing.

## NOTES:

- Parts that are not assigned part numbers (-----) are not available.
- Tolerance of Capacitors and Resistors are noted with the following symbols.

C.....±0.25%    D.....±0.5%    F.....±1%  
 G.....±2%    J.....±5%    K.....±10%  
 M.....±20%    N.....±30%    Z.....+80/-20%

## DIGITAL MAIN CBA UNIT

Ref. No.	Description	Part No.
	DIGITAL MAIN CBA UNIT	A91FTMMA-001

## MPW CBA

Ref. No.	Description	Part No.
	MPW CBA Consists of the following:	A91FSMPWA001
	POWER SUPPLY CBA(MPW-1)	-----
	JACK CBA(MPW-2)	-----

## POWER SUPPLY CBA(MPW-1)

Ref. No.	Description	Part No.
	POWER SUPPLY CBA(MPW-1) Consists of the following:	-----
<b>CAPACITORS</b>		
C201	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C202	ELECTROLYTIC CAP. 22µF/50V M	CE1JMASDL220
C203	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C221	CHIP CERAMIC CAP.(1608) B K 0.01µF/50V	CHD1JK30B103
C222	ELECTROLYTIC CAP. 100µF/16V M	CE1CMASDL101
C302	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C303	ELECTROLYTIC CAP. 330µF/10V M	CE1AMASDL331
C305	CHIP CERAMIC CAP.(1608) F Z 0.1µF/50V	CHD1JZ30F104
C306	ELECTROLYTIC CAP. 1µF/50V M	CE1JMASDL1R0
C309	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C310	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C311	CHIP CERAMIC CAP.(1608) CH J 47pF/50V	CHD1JJ3CH470
C601▲	CAP METALIZED FILM 0.47µF/300V K 3.5MM	CT2F474DC004
C602▲	CAP METALIZED FILM 0.47µF/300V K 3.5MM	CT2F474DC004
C605	CAP ELECTROLYTIC 470µF/200V M	CA2D471DYG07
C609	POLYESTER FILM CAP. (PB FREE) 0.047µF/100V J	CA2A473DT018
C610	POLYESTER FILM CAP. (PB FREE) 0.0012µF/100V J	CA2A122DT018
C611	CERAMIC CAP. 470pF/2KV	CA3D471PAN04
C612	POLYESTER FILM CAP. (PB FREE) 0.082µF/100V J	CA2A823DT018
C613	POLYESTER FILM CAP. (PB FREE) 0.0015µF/100V J	CA2A152DT018
C631	ELECTROLYTIC CAP. 1000µF/25V M	CE1EMZNDL102

Ref. No.	Description	Part No.
C633	CAP ALUMINUM ELECTROLYTIC 2200µF/6.3V M	CE0KMZNDL222
C637	CERAMIC CAP. 2200pF/1KV	CCD3AKA0R222
C638	ELECTROLYTIC CAP. 330µF/50V M	CE1JMZPDL331
C639	ELECTROLYTIC CAP. 1000µF/35V M	CE1GMZADL102
C642	ELECTROLYTIC CAP. 1µF/50V M	CE1JMASDL1R0
C644	ELECTROLYTIC CAP. 3300µF/16V M	CE1CMZNDL332
C645	CAP ALUMINUM ELECTROLYTIC 2200µF/6.3V M	CE0KMZNDL222
C646	POLYESTER FILM CAP. (PB FREE) 0.0022µF/100V J	CA2A222DT018
C647	ELECTROLYTIC CAP. 1µF/50V M	CE1JMASDL1R0
C648	ELECTROLYTIC CAP. 100µF/10V M	CE1AMASDL101
C652	ELECTROLYTIC CAP. 1000µF/6.3V M	CE0KMASDL102
C653	ELECTROLYTIC CAP. 220µF/10V M	CE1AMASDL221
C654	ELECTROLYTIC CAP. 220µF/10V M	CE1AMASDL221
C655	ELECTROLYTIC CAP. 22µF/50V M	CE1JMASDL220
C656	ELECTROLYTIC CAP. 100µF/16V M	CE1CMASDL101
C657	ELECTROLYTIC CAP. 22µF/50V M	CE1JMASDL220
C676	ELECTROLYTIC CAP. 2.2µF/50V M	CE1JMASDL2R2
C681	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C682	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C683	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C684	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C691▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C693▲	SAFTY CAP. 1000pF/250V KX	CA2E102MR101
C723	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C724	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C731	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C732	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C733	CHIP CERAMIC CAP. CH J 39pF/50V	CHD1JJ3CH390
C743	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C744	CHIP CERAMIC CAP.(1608) B K 2.2µF/10V	CHD1AK30B225
C771	ELECTROLYTIC CAP. 100µF/16V M	CE1CMASDL101
C772	CHIP CERAMIC CAP.(1608) F Z 0.1µF/25V	CHD1EZ30F104
C775	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C776	CHIP CERAMIC CAP.(1608) CH J 100pF/50V	CHD1JJ3CH101
C801	CHIP CERAMIC CAP. F Z 1µF/10V	CHD1AZ30F105
C802	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C803	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C804	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C805	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C806	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C807	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C808	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C809	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C810	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C811	CHIP CERAMIC CAP.(1608) B K 0.47µF/16V	CHD1CK30B474
C816	ELECTROLYTIC CAP. 10µF/50V M	CE1JMASDL100
C817	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C818	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C819	ELECTROLYTIC CAP. 10µF/50V M	CE1JMASDL100
C820	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C821	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C822	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C823	ELECTROLYTIC CAP. 1000µF/25V M	CE1EMZNDL102
C824	CHIP CERAMIC CAP.(1608) B K 1µF/25V	CHD1EK30B105
C825	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104
C826	CHIP CERAMIC CAP.(1608) CH J 1000pF/50V	CHD1JJ3CH102
C827	ELECTROLYTIC CAP. 10µF/50V M	CE1JMASDL100
C828	CHIP CERAMIC CAP.(1608) B K 0.1µF/25V	CHD1EK30B104

Ref. No.	Description	Part No.
C829	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C830	CHIP CERAMIC CAP(1608) B K 0.47μF/16V	CHD1CK30B474
C832	ELECTROLYTIC CAP. 3.3μF/50V M	CE1JMASDL3R3
C833	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C834	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C835	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C836	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C837	CHIP CERAMIC CAP(1608) B K 2700pF/50V	CHD1JK30B272
C838	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C839	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C841	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C842	CHIP CERAMIC CAP. F Z 1μF/10V	CHD1AZ30F105
C843	CHIP CERAMIC CAP(1608) B K 0.01μF/50V	CHD1JK30B103
C844	ELECTROLYTIC CAP. 10μF/50V M	CE1JMASDL100
C845	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C846	CHIP CERAMIC CAP(1608) CH J 470pF/50V	CHD1JJ3CH471
C847	CHIP CERAMIC CAP(1608) B K 0.1μF/25V	CHD1EK30B104
C848	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C849	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C850	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C851	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C852	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C853	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C854	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C855	CHIP CERAMIC CAP. CH J 56pF/50V	CHD1JJ3CH560
C871	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C872	CHIP CERAMIC CAP(1608) B K 3300pF/50V	CHD1JK30B332
C873	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C874	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C875	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C876	CHIP CERAMIC CAP(1608) CH J 270pF/50V	CHD1JJ3CH271
C877	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C878	CHIP CERAMIC CAP(1608) B K 6800pF/50V	CHD1JK30B682
C879	CHIP CERAMIC CAP(1608) F Z 0.1μF/25V	CHD1EZ30F104
C880	ELECTROLYTIC CAP. 100μF/16V M	CE1CMASDL101
C882	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C883	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C884	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
C885	CHIP CERAMIC CAP(1608) B K 2.2μF/10V	CHD1AK30B225
<b>CONNECTORS</b>		
CN101	242 SERIES CONNECTOR 224202108W1	J322C08TG001
CN201	FPC/FFC CONNECTOR IMSA-9615S-05A-PP-A	JC96J05ER007
CN301	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN302	FFC CONNECTOR IMSA-9615S-29A-PP-A	JC96J29ER007
CN801	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
CN802	PH CONNECTOR TOP 2P B2B-PH-K-S (LF)(SN)	J3PHC02JG029
<b>DIODES</b>		
D204	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D211	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D404	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D407	DIODE ZENER 10BSB-T26	NDTB010BST26
D409	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D410	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D411	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D412	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D413	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D414	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D415	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D417	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26
D418	DIODE ZENER 3V9BSB-T26	NDTB3R9BST26

Ref. No.	Description	Part No.
D419	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D420	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D421	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D601▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D602▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D603▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D604▲	DIODE GENERAL PURPOSE 1N5406-BU	NDLZ1N5406BU
D606▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D607	DIODE ZENER 4V3BSB-T26	NDTB4R3BST26
D609▲	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D611	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D612▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D631	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D633	DIODE FAST RECOVERY FR151-B/P	NDWZ0FR151BP
D635	DIODE ZENER 18BSC-T26	NDTC018BST26
D638	DIODE FR154	NDLZ000FR154
D639	DIODE ZENER 1ZB43BB	NDWZ0001ZB43
D641	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D642	SCHOTTKY BARRIER DIODE SB390	NDWZ000SB390
D643	DIODE FR104-B	NDLZ000FR104
D644	DIODE ZENER 10BSA-T26	NDTA010BST26
D645	SHUNT REGULATOR KIA431B-AT/P	NSZBA0TJY038
D646	DIODE SCHOTTKY SB360BH	NDWZ000SB360
D647	SCHOTTKY BARRIER DIODE SB240-B/P	NDWZ000SB240
D648	SCHOTTKY BARRIER DIODE SB140	NDWZ000SB140
D649	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D650	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D652	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D655	RECTIFIER DIODE 1N4005	NDQZ001N4005
D657	DIODE ZENER 33BSB-T26	NDTB033BST26
D658	DIODE ZENER 3V3BSB-T26	NDTB3R3BST26
D659	DIODE ZENER 6V8BSA-T26	NDTA6R8BST26
D660	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D661	DIODE FR154	NDLZ000FR154
D662	DIODE FR154	NDLZ000FR154
D664	DIODE ZENER 4V7BSB-T26	NDTB4R7BST26
D665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D666	IC SHUNT REGULATOR KIA431-AT/P	NSZBA0TJY036
D670	DIODE ZENER 10BSB-T26	NDTB010BST26
D671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D675	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D676	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D680	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D801	DIODE ZENER 20BSB-T26	NDTB020BST26
D802	DIODE ZENER 20BSB-T26	NDTB020BST26
D803	DIODE ZENER 20BSB-T26	NDTB020BST26
D804	DIODE ZENER 20BSB-T26	NDTB020BST26
D806	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
<b>ICS</b>		
IC601▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC631	IC LD1117V	NSZBA0SS046
IC771	IC SWITCHING TC4052BF(ELNF)	QSZBA0TTS162
IC801	IC D-AMP BD5426EFS-E2	QSZBA0TRM137
IC871	IC OP AMP NJM4558M(TE1)-#ZZZB	QSZBA0TJR089
<b>COILS</b>		
L302	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L303	CHIP INDUCTOR LK1608R22K-T	LLACKB3TUR22
L601▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L602▲	COIL LINE FILTER ST0807ET28-009 10MH	LLEG0Z0Y2029
L801	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L802	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330
L803	RADIAL LEAD INDUCTORS 33μH	LLARKGQTU330



Ref. No.	Description	Part No.
L804	RADIAL LEAD INDUCTORS 33 $\mu$ H	LLARKGQTU330
L871	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
<b>TRANSISTORS</b>		
Q171	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q172	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q207	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q208	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q209	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q210	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q211	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q212	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q402	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q601▲	FET MOS 2SK3563(Q)	QFWZ2SK3563Q
Q602▲	TRANSISTOR 2SC2120-Q(Te2 F T)	QQS02SC2120F
Q631	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q634	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q635	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q636	TRANSISTOR 2SA950-O (Te2 F T)	QQS002SA950F
Q637	NPN TRANSISTOR POWER 2SC4881F HFE MAX320	QQWZ2SC4881F
Q638	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q639	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q640	TRANSISTOR 2SC2120-Y(Te2 F T)	QQSY2SC2120F
Q641	TRANSISTOR 2SC2120-Y(Te2 F T)	QQSY2SC2120F
Q642	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q643	TRANSISTOR 2SC2120-Y(Te2 F T)	QQSY2SC2120F
Q771	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q772	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q801	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q802	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q841	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q871	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q872	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q873	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q874	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
<b>RESISTORS</b>		
R171	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R172	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R175	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R201	CHIP RES. 1/10W J 2.2k $\Omega$	RRXAJR5Z0222
R202	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R203	RES CARBON FILM T 1/4W J 5.6k $\Omega$	RCX4562T1001
R204	RES CARBON FILM T 1/4W J 100k $\Omega$	RCX4104T1001
R205	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R206	RES CARBON FILM T 1/4W J 100k $\Omega$	RCX4104T1001
R207	RES CARBON FILM T 1/4W J 82k $\Omega$	RCX4823T1001
R208	RES CARBON FILM T 1/4W J 10k $\Omega$	RCX4103T1001
R209	RES CARBON FILM T 1/4W J 10k $\Omega$	RCX4103T1001
R223	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R224	RES CARBON FILM T 1/4W J 27k $\Omega$	RCX4273T1001
R225	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R226	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R227	METAL OXIDE FILM RES. 1W J 0.39 $\Omega$	RN01R39ZU001
R228	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R229	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R230	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R231	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R232	CHIP RES. 1/10W F 8.2k $\Omega$	RRXAFR5H8201
R233	CHIP RES. 1/10W F 270 $\Omega$	RRXAFR5H2700
R234	CHIP RES. 1/10W F 2.2k $\Omega$	RRXAFR5H2201
R235	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R247	METAL OXIDE FILM RES. 1W J 0.39 $\Omega$	RN01R39ZU001

Ref. No.	Description	Part No.
R248	METAL OXIDE FILM RES. 1W J 0.39 $\Omega$	RN01R39ZU001
R302	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R303	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R306	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R307	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R308	CHIP RES. 1/10W J 82 $\Omega$	RRXAJR5Z0820
R309	CHIP RES. 1/10W J 82 $\Omega$	RRXAJR5Z0820
R310	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R401	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R402	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R407	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R408	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R410	CHIP RES. 1/10W F 2.2k $\Omega$	RRXAFR5H2201
R411	CHIP RES. 1/10W F 56k $\Omega$	RRXAFR5H5602
R601▲	RES. CARBON FILM J 1/2W J 560k $\Omega$	RCX2564T1003
R602▲	CEMENT RESISTOR 5W J 2.2 $\Omega$ H 10MM	RW052R2PAK10
R604	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R605	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R606	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R610	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R611	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R613	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R614▲	METAL OXIDE FILM RES. 2W J 0.39 $\Omega$	RN02R39ZU001
R615	RES CARBON FILM T 1/4W J 1.8k $\Omega$	RCX4182T1001
R616	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R617▲	CEMENT RESISTOR 5W J 2.2 $\Omega$ H 10MM	RW052R2PAK10
R618	RES CARBON FILM T 1/4W J 390k $\Omega$	RCX4394T1001
R635	RES. CARBON FILM J 1/2W J 2.2 $\Omega$	RCX22R2T1003
R636	RES. CARBON FILM J 1/2W J 2.7 $\Omega$	RCX22R7T1003
R637	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R638	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R639	RES CARBON FILM T 1/4W J 1.5k $\Omega$	RCX4152T1001
R641	RES CHIP.(1608) 1/10W D 1.1k $\Omega$	RRXADR5H1101
R642	RES CHIP.(1608) 1/10W D 10k $\Omega$	RRXADR5H1002
R643	RES CHIP.(1608) 1/10W D 10k $\Omega$	RRXADR5H1002
R644	CHIP RES. 1/10W F 820 $\Omega$	RRXAFR5H8200
R645	RES CARBON FILM T 1/4W J 270 $\Omega$	RCX4271T1001
R646	RES CARBON FILM T 1/4W J 180 $\Omega$	RCX4181T1001
R648	CHIP RES. 1/10W F 1.0k $\Omega$	RRXAFR5H1001
R650	RES CARBON FILM T 1/4W J 2.7k $\Omega$	RCX4272T1001
R651	CHIP RES. 1/10W J 1 $\Omega$	RRXAJR5Z01R0
R652	CHIP RES. 1/10W F 24k $\Omega$	RRXAFR5H2402
R653	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R654	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R655	RES CARBON FILM T 1/4W J 2.7k $\Omega$	RCX4272T1001
R657	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
R658	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R659	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R660	RES CARBON FILM T 1/4W J 680 $\Omega$	RCX4681T1001
R661	RES. CARBON FILM J 1/2W J 390 $\Omega$	RCX2391T1003
R662	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R663	RES CARBON FILM T 1/4W J 680 $\Omega$	RCX4681T1001
R664	RES CARBON FILM T 1/4W J 680 $\Omega$	RCX4681T1001
R665	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R666	RES CARBON FILM T 1/4W J 1.0 $\Omega$	RCX41R0T1001
R667	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R668	CHIP RES. 1/10W F 620 $\Omega$	RRXAFR5H6200
R669	CHIP RES. 1/10W F 1.0k $\Omega$	RRXAFR5H1001
R670	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R671	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R672	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R673	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R674	RES CARBON FILM T 1/4W J 1.8k $\Omega$	RCX4182T1001

Ref. No.	Description	Part No.
R675	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R676	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R677	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R678	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R679	CHIP RES. 1/10W F 3.6k $\Omega$	RRXAFR5H3601
R680	CHIP RES. 1/10W F 10k $\Omega$	RRXAFR5H1002
R682	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R683	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R685	RES CARBON FILM T 1/4W J 22 $\Omega$	RCX4220T1001
R687	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R688	RES CARBON FILM T 1/4W J 10 $\Omega$	RCX4100T1001
R689	RES CARBON FILM T 1/4W J 1.2k $\Omega$	RCX4122T1001
R691	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R692	RES CARBON FILM T 1/4W J 2.7 $\Omega$	RCX42R7T1001
R696	METAL RESISTOR 1W J 3.9 $\Omega$	RN013R9ZU001
R697	METAL RESISTOR 1W J 3.9 $\Omega$	RN013R9ZU001
R723	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R724	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R725	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R726	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R731	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R732	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R733	CHIP RES. 1/10W J 75 $\Omega$	RRXAJR5Z0750
R734	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R735	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R736	CHIP RES. 1/10W J 10 $\Omega$	RRXAJR5Z0100
R743	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R744	CHIP RES. 1/10W J 15k $\Omega$	RRXAJR5Z0153
R745	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R746	CHIP RES. 1/10W J 39k $\Omega$	RRXAJR5Z0393
R763	RES CARBON FILM T 1/4W J 10k $\Omega$	RCX4103T1001
R771	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R772	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R773	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R774	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R775	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R776	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R777	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R778	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R779	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R802	CHIP RES. 1/10W F 27k $\Omega$	RRXAFR5H2702
R803	CHIP RES. 1/10W F 11k $\Omega$	RRXAFR5H1102
R804	CHIP RES. 1/10W F 11k $\Omega$	RRXAFR5H1102
R806	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R810	CHIP CERAMIC CAP. F Z 1 $\mu$ F/10V	CHD1AZ30F105
R813	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R814	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R815	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R816	CHIP RES. 1/10W J 3.3k $\Omega$	RRXAJR5Z0332
R817	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R818	CHIP RES. 1/10W J 10k $\Omega$	RRXAJR5Z0103
R819	RES CARBON FILM T 1/4W J 22k $\Omega$	RCX4223T1001
R820	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R843	CHIP RES. 1/10W J 110 $\Omega$	RRXAJR5Z0111
R844	CHIP RES. 1/10W J 220 $\Omega$	RRXAJR5Z0221
R847	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R848	CHIP RES. 1/10W J 4.7k $\Omega$	RRXAJR5Z0472
R871	CHIP RES. 1/10W J 560 $\Omega$	RRXAJR5Z0561
R872	CHIP RES. 1/10W J 560 $\Omega$	RRXAJR5Z0561
R873	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R874	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R877	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R878	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001

Ref. No.	Description	Part No.
R879	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R880	CHIP RES. 1/10W J 47k $\Omega$	RRXAJR5Z0473
R881	CHIP RES. 1/10W J 100 $\Omega$	RRXAJR5Z0101
R882	CHIP RES. 1/10W J 100 $\Omega$	RRXAJR5Z0101
R883	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R884	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R885	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R886	CHIP RES. 1/10W J 100k $\Omega$	RRXAJR5Z0104
R887	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R888	CHIP RES. 1/10W J 1k $\Omega$	RRXAJR5Z0102
R891	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R892	CHIP RES. 1/10W J 20k $\Omega$	RRXAJR5Z0203
R893	CHIP RES. 1/10W J 22k $\Omega$	RRXAJR5Z0223
R894	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
<b>MISCELLANEOUS</b>		
AC601▲	AC CORD UL 1855MM BLACK	WAC0182LW007
B11	POW HEAT SINK A7120UH	1EM423993
B12	MODULE HEAT SINK PMC P7150UT	1EM423968
BC301	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
BC601	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC801	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC802	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC803	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC804	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC805	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC841	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL602	WIRE ASSEMBLY 2PIN 2PIN 90MM RED BLACK	WX1A91FS-204
CL701	WIRE ASSEMBLY 9P 9PIN/170MM	WX1A94F0-002
F601▲	FUSE STC4A125V U/CT	PAGE20CW3402
FH601	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
FH602	FUSE HOLDER MSF-015 LF (B110)	XH01Z00LY002
JK721	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK722	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK731	JACK RCA PCB S GREEN 01/RCA-101H(GN)	JXRJ010YUQ03
JK732	JACK RCA PCB S BLUE 01/RCA-101H(BL)	JXRJ010YUQ04
JK733	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JK741	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK742	JACK SW RCA PCB S RED RCA-102H(RD)	JYRJ010YUQ03
JK841	JACK RCA PCB S ORANGE 01/RCA-101H(OR)	JXRJ010YUQ06
JK871	JACK RCA PCB S WHITE 01/RCA-101H(WH)	JXRJ010YUQ02
JK872	JACK RCA PCB S RED 01/RCA-101H(RD)	JXRJ010YUQ01
JS102	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS302	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS303	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS304	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
SA601▲	SURGE ABSORBER 470V+-10PER	NVQZ10D471KB
T601▲	TRANS POWER BCK-28-9910A	LTT2PC0XB057
TM601	EYELET TYPE D-1	0VM406868
TM602	EYELET TYPE D-1	0VM406868
TU301	TUNER UNIT ATSC/NTSC/QAM TDAU4-D02A	UTUNNTUAL052

## JACK CBA(MPW-2)

Ref. No.	Description	Part No.
	JACK CBA(MPW-2) Consists of the following:	-----
<b>CAPACITORS</b>		
C754	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C755	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C756	CHIP RES.(1608) 1/10W 0 $\Omega$	RRXAZR5Z0000
C757	CHIP CERAMIC CAP.(1608) B K 2.2 $\mu$ F/10V	CHD1AK30B225

Ref. No.	Description	Part No.
C758	CHIP CERAMIC CAP.(1608) B K 2.2μF/10V	CHD1AK30B225
<b>RESISTORS</b>		
R751	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R752	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R753	CHIP RES. 1/10W J 75 Ω	RRXAJR5Z0750
R756	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R757	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R758	CHIP RES.(1608) 1/10W 0 Ω	RRXAZR5Z0000
R759	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R760	CHIP RES. 1/10W J 15k Ω	RRXAJR5Z0153
R761	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
R762	CHIP RES. 1/10W J 39k Ω	RRXAJR5Z0393
<b>MISCELLANEOUS</b>		
JK751	JACK SW DIN PCB L DIN-435C(777D)	JYEL040YUQ03
JK752	JACK RCA PCB L RCA-101S(1)-03	JXRL010YUQ12
JK753	JACK RCA PCB L RCA-101S(1)-04	JXRL010YUQ13
JK754	JACK SW RCA PCB L RCA-102F(RD)	JYRL010YUQ05

## INVERTER ASSEMBLY

Ref. No.	Description	Part No.
	INVERTER ASSEMBLY Consists of the following:	A91FSM1V-001
	INVERTER POWER CBA	A91FSM1V-001-IV
	FUNCTION CBA IR SENSOR CBA JUNCTION CBA	A91FSM1V-001-FNIRJN

## INVERTER POWER CBA

Ref. No.	Description	Part No.
	INVERTER POWER CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C1620	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1650	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C1651	POLYESTER FILM CAP. (PB FREE) 0.022μF/100V J	CA2A223DT018
C1652	CAP CERAMIC (AX) 0.01μF/50V/B/K	CA1J103TU061
C1653	CAP CERAMIC (AX) 0.01μF/50V/B/K	CA1J103TU061
C1801	ELECTROLYTIC CAP. 22μF/50V M	CE1JMASDL220
C1802	POLYESTER FILM CAP. (PB FREE) 0.022μF/100V J	CA2A223DT018
C1803	POLYESTER FILM CAP. (PB FREE) 0.01μF/100V J	CA2A103DT018
C1905▲	SAFTY CAP. 2200pF/250V KX	CA2E222MR101
C1910	CAP ELECTROLYTIC 270μF/200V	CEA271DYG005
C1930	CERAMIC CAP. 820pF/2KV	CA3D821PAN04
C1931▲	POLYESTER FILM CAP. (PB FREE) 0.001μF/100V J	CA2A102DT018
C1932	POLYESTER FILM CAP. (PB FREE) 0.056μF/100V J	CA2A563DT018
C1933	POLYESTER FILM CAP. (PB FREE) 0.1μF/100V J	CA2A104DT018
C1941	CERAMIC CAP. B K 0.01μF/1KV	CCD3AKN0B103
C1970	POLYESTER FILM CAP. (PB FREE) 0.0022μF/100V J	CA2A222DT018
C1981	POLYESTER FILM CAP. (PB FREE) 0.01μF/100V J	CA2A103DT018
C1982	ELECTROLYTIC CAP. 0.47μF/50V M	CE1JMASDLR47
C1990	CERAMIC CAP. 3300pF/1KV	CCD3AKA0R332
C1992	ELECTROLYTIC CAP. 2200μF/35V M	CE1GMZNDL222
C1995	ELECTROLYTIC CAP. 2200μF/35V M	CE1GMZNDL222
<b>CONNECTORS</b>		

Ref. No.	Description	Part No.
CN1001	FPC/FFC CONNECTOR IMSA-9615S-05A-PP-A	JC96J05ER007
CN1900▲	CONNECTOR B2P3-VH(LF)(SN)	J3VH020JG001
<b>DIODES</b>		
D1651	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1930▲	DIODE ZENER 27BSB-T26	NDTB027BST26
D1931	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1932	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1933	SWITCHING DIODE 1SS133(T-77)	QDTZ001SS133
D1934▲	DIODE ZENER 39BSB-T26	NDTB039BST26
D1940	DIODE FAST RECOVERY FR155-B/P	NDWZ0FR155BP
D1960	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
D1970	DIODE ZENER 5V6BSB-T26	NDTB5R6BST26
D1971	DIODE ZENER HZS33NB2TE-EQ	QDTBHZS33NB2
D1990	DIODE SCHOTTKY YG862C15R	QDWZYG862C15
D1994▲	DIODE ZENER 1ZB30BB	NDWZ0001ZB30
<b>ICS</b>		
IC1930▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
IC1931▲	PHOTO COUPLER LTV817MCF	NPECLTV817MF
<b>COILS</b>		
L1601	INDUCTOR 100μH-J-26T	LLAXJATTU101
L1602	INDUCTOR 100μH-J-26T	LLAXJATTU101
<b>TRANSISTORS</b>		
Q1650	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1651	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1652	TRANSISTOR KTA1267-GR-AT/P	NQS1KTA1267P
Q1800	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1930▲	FET MOS 2SK3561(Q) IDSS100UA	QFWZ2SK3561Q
Q1931▲	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1932▲	TRANSISTOR 2SC2120-Y(Te2 F T)	QQSY2SC2120F
Q1970	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1971	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
Q1972	TRANSISTOR KTC3198-Y-AT/P	NQSYKTC3198P
<b>RESISTORS</b>		
R1650	RES CARBON FILM T 1/4W J 100 Ω	RCX4101T1001
R1651	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1652	RES CARBON FILM T 1/4W J 22k Ω	RCX4223T1001
R1653	RES CARBON FILM T 1/4W J 3.3k Ω	RCX4332T1001
R1654	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1655	RES CARBON FILM T 1/4W J 6.8k Ω	RCX4682T1001
R1656	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R1657	RES CARBON FILM T 1/4W J 100k Ω	RCX4104T1001
R1658	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1800	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1801	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R1803	RES CARBON FILM T 1/4W J 10k Ω	RCX4103T1001
R1930	RES CARBON FILM T 1/4W J 47 Ω	RCX4470T1001
R1931	RES CARBON FILM T 1/4W J 47k Ω	RCX4473T1001
R1932	RES CARBON FILM T 1/4W J 120 Ω	RCX4121T1001
R1933	RES CARBON FILM T 1/4W J 120 Ω	RCX4121T1001
R1934	RES CARBON FILM T 1/4W J 120 Ω	RCX4121T1001
R1935	RES CARBON FILM T 1/4W J 1.2k Ω	RCX4122T1001
R1936	RES CARBON FILM T 1/4W J 180 Ω	RCX4181T1001
R1937▲	METAL OXIDE FILM RES. 2W J 0.47 Ω	RN02R47ZU001
R1938	METAL RESISTER. 2W J 0.56 Ω	RN02R56ZU001
R1939	RES CARBON FILM T 1/4W J 2.2k Ω	RCX4222T1001
R1940	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1941	RES CARBON FILM T 1/4W J 220k Ω	RCX4224T1001
R1942	RES CARBON FILM T 1/4W J 270k Ω	RCX4274T1001
R1943	RES CARBON FILM 1/4W J 820k Ω	RCX4824FS002
R1944	RES CARBON FILM 1/4W J 820k Ω	RCX4824FS002
R1945	RES CARBON FILM T 1/4W J 390k Ω	RCX4394T1001

Ref. No.	Description	Part No.
R1946	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1947	METAL OXIDE RES. 1W J 47k $\Omega$	RN01473ZU001
R1969	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R1970	RES CARBON FILM T 1/4W J 120 $\Omega$	RCX4121T1001
R1975	RES CARBON FILM T 1/4W G 20k $\Omega$	RCX4203T1002
R1979	RES CARBON FILM T 1/4W G 6.8k $\Omega$	RCX4682T1002
R1980	RES CARBON FILM T 1/4W G 270 $\Omega$	RCX4271T1002
R1981	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
R1982	RES CARBON FILM T 1/4W J 2.2k $\Omega$	RCX4222T1001
R1986	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R1987	RES CARBON FILM 1/4W J 820k $\Omega$	RCX4824FS002
R1988	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
<b>MISCELLANEOUS</b>		
B33	HEAT SINK PND ASSEMBLY A91F2UH	1EM428182
BC1930	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
BC1931	BEADS INDUCTOR FBR07HA121SB-00	LLBF00STU030
CL1003	WIRE ASSEMBLY 13P 13PIN/120MM	WX1A91FS-201
JS1001	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
JS1002	WIRE COPPER 6111-06003-0120	XZ40C0SHG002
L3	SCREW B-TIGHT D3X8 BIND HEAD+	GBJB3080
T1950▲	TRANS INVPOW BCK-28-9909D	LTT2PC0XB056

## FUNCTION CBA

Ref. No.	Description	Part No.
	FUNCTION CBA Consists of the following:	-----
<b>CAPACITOR</b>		
C108	CAP CERAMIC (AX) 0.1 $\mu$ F/50V/F/Z	CA1J104TU062
<b>RESISTORS</b>		
R108	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R109	RES CARBON FILM T 1/4W G 10k $\Omega$	RCX4103T1002
R111	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R112	RES CARBON FILM T 1/4W G 2.7k $\Omega$	RCX4272T1002
R113	RES CARBON FILM T 1/4W G 4.7k $\Omega$	RCX4472T1002
R114	RES CARBON FILM T 1/4W G 8.2k $\Omega$	RCX4822T1002
R115	RES CARBON FILM T 1/4W G 18k $\Omega$	RCX4183T1002
<b>SWITCHES</b>		
SW101A	TACT SWITCH SKHHLMA010	SST0101AL049
SW103A	TACT SWITCH SKHHLMA010	SST0101AL049
SW104A	TACT SWITCH SKHHLMA010	SST0101AL049
SW105A	TACT SWITCH SKHHLMA010	SST0101AL049
SW106A	TACT SWITCH SKHHLMA010	SST0101AL049
SW107A	TACT SWITCH SKHHLMA010	SST0101AL049

## IR SENSOR CBA

Ref. No.	Description	Part No.
	IR SENSOR CBA Consists of the following:	-----
<b>CAPACITORS</b>		
C113	ELECTROLYTIC CAP. 47 $\mu$ F/16V M H7	CE1CMAVSL470
C115	CAP CERAMIC (AX) 330pF/50V/B/K	CA1J331TU061
<b>DIODES</b>		
D104	LED GREEN 333GT/E(FNA)	NPWZ33GTEFNA
D105	LED L-53HT	NP4Z000L53HT
<b>RESISTORS</b>		
R123	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R124	RES CARBON FILM T 1/4W J 220 $\Omega$	RCX4221T1001
R126	RES CARBON FILM T 1/4W J 1.0k $\Omega$	RCX4102T1001
R127	RES CARBON FILM T 1/4W J 3.3k $\Omega$	RCX4332T1001
R128	RES CARBON FILM T 1/4W J 100 $\Omega$	RCX4101T1001
<b>MISCELLANEOUS</b>		

Ref. No.	Description	Part No.
CL102	WIRE ASSEMBLY 8P 8PIN/240MM	WX1A91FS-001
CL103	WIRE ASSEMBLY 4P 4PIN/250MM	WX1A94F0-003
RS102	SENSOR REMOTE RECEIVER KSM-712TH2E	USESJRSKK044

## JUNCTION CBA

Ref. No.	Description	Part No.
	JUNCTION CBA Consists of the following:	-----
<b>CONNECTOR</b>		
CN101	242 SERIES CONNECTOR TUC-P08X-B1 WHT ST	JCTUB08TG002

# REVISION HISTORY

## Chassis FL9.1

- 2009-06-11 LC320EMX (Serial No. : DS3A\*\*\*\*\*) added
- 2009-06-30 Individual parts numbers added for the INVERTER ASSEMBLY
- 2009-07-03 LC320SLX (Serial No. : DS3A\*\*\*\*\*) added
- 2009-07-14 LC320EMX (Serial No. : DS2A\*\*\*\*\*) added
- 2009-07-24 LC320SLX (Serial No. : DS2A\*\*\*\*\*) added
- 2009-07-31 Change parts numbers  
(DIGITAL MAIN CBA UNIT, MPW CBA, INVERTER ASSEMBLY)
- 2009-08-17 LC320EMXF (Serial No. : DS1A\*\*\*\*\*) added
- 2009-08-17 LC320EMXF (Serial No. : DS2A\*\*\*\*\*) added
- 2009-09-14 LC321SSX added
- 2009-09-18 32MF339B/F7 (Serial No. : DS2A\*\*\*\*\*) added
- 2009-09-30 LC320EMXF (Serial No. : DS4A\*\*\*\*\*) added
- 2009-09-30 32MF369B/F7 added
- 2009-10-13 32MF339B/F7 (Serial No. : DS1A\*\*\*\*\*, DS2A\*\*\*\*\*),  
LC320EMX (Serial No. : DS1A\*\*\*\*\*, DS2A\*\*\*\*\*, DS3A\*\*\*\*\*),  
LC320EMXF (Serial No. : DS1A\*\*\*\*\*, DS2A\*\*\*\*\*, DS4A\*\*\*\*\*),  
LC320SLX (Serial No. : DS1A\*\*\*\*\*, DS2A\*\*\*\*\*, DS3A\*\*\*\*\*),  
LC320SSX (Serial No. : DS1A\*\*\*\*\*)  
Change parts numbers  
(DIGITAL MAIN CBA UNIT, MPW CBA)
- 2010-10-12 LC320SLX (Serial No. : DS2A\*\*\*\*\*),  
32MF339B/F7 (Serial No. : DS2A\*\*\*\*\*),  
LC320EMX (Serial No. : DS2A\*\*\*\*\*),  
LC320EMXF (Serial No. : DS2A\*\*\*\*\*, DS4A\*\*\*\*\*)  
Change parts numbers  
(INVERTER ASSEMBLY)
- TBD LC320SSX (Serial No. : DS2A\*\*\*\*\*) added
- TBD LC320SLX (Serial No. : DS4A\*\*\*\*\*) added
- TBD LC320EMX (Serial No. : DS4A\*\*\*\*\*) added
- TBD 32MF339B/F7 (Serial No. : DS3A\*\*\*\*\*) added
- TBD LC320SSX (Serial No. : DS3A\*\*\*\*\*) added